

Information technology — Universal Multiple-Octet Coded Character Set (UCS) —

Part 1:

Architecture and Basic Multilingual Plane

AMENDMENT 2: Limbu, Tai Le, Yijing and other characters

Page v, Foreword

Add the following text after the last paragraph.

The standard contains material which may be only available to users who obtain their copy in a machine readable format. That material consists of the following printable files:

CJKC0SR.txt

CJKUA_SR.txt

[...]

(Editor's note: more files are likely to be added for the next edition)

Page 1, clause 1 Scope

Replace the first sentence of the Note 1 as follows:

The Unicode Standard Version 4.0 includes a set of characters, names, and coded representations for the Basic Multilingual Plane that are identical with those in this Part of this International Standard.

Page 2, clause 3 Normative references

Add the following reference:

Unicode Standard Annex, UAX#15, Unicode Normalization Forms, Version 3.2.0, 2002-03-27.

(Editor's note: The Version number is likely to be updated before publication)

Page 4, clause 5 General structure of the UCS

Insert the following note after the 6th paragraph (excluding the existing note which is renamed NOTE 1):

NOTE 2 – The use of the term “canonical” for this form does not imply any restriction or preference for this form over transformation formats that a conforming implementation may choose for the representation of UCS characters.

Page 9, sub-clause 13.2 Four-octet canonical form

Change the sub-clause header to “13.2 Four-octet canonical form (UCS-4)” and add a new note after the existing note which is renamed NOTE 1:

NOTE 2 – When confined to the code positions in Planes 0 to 10 (U+0000 to U+10FFFF), UCS-4 is also referred to as UCS Transformation Format 32 (UTF-32). The Unicode Standard, Version 3.2, defines the following forms of UTF-32:

- UTF-32: the ordering of octets (specified in sub-clause 6.3) is not defined and the signatures (specified in Annex H) may appear;
- UTF-32BE: in the ordering of octets the more significant octets precede the less significant octets, as specified in sub-clause 6.2, and no signatures appear;
- UTF-32LE: in the ordering of octets the less significant octets precede the more significant octets, and no signatures appear.

Page 13, clause 22 Compatibility characters

In the sub-clause 22.2 added by the first amendment insert the new KP sources after the U source as follows:

The Hanja KP source is:

KP1 KPS 10721-2000

In the next paragraph first sentence, change ‘8-line’ by ‘9-line’.

In the line ‘01-06 octet: BMP...’, replace ‘code value’ by ‘code position’.

After the line ‘29-36 octet: Unicode U sources..’, add:

37-44 octet: Hanja KP sources (KP1-hhhh)

Add the KP source entries in the CJK Compatibility reference file.

In the same reference file, for the entry 0F951, change the corresponding CJK Unified Ideograph from 096FB to 0964B.

[Click on this highlighted text to access the updated reference file \(CJKC0SR.txt\).](#)

Page 13, after clause 23 Order of characters

Insert a new clause 24 between the current clause 23 and 24 (the following clauses are incremented by one):

24 Normalization forms

Normalization forms are the mechanisms allowing the selection of a unique coded representation among alternative, but equivalent coded text representations of the same text. Normalization forms for use with ISO/IEC 10646 are specified in the Unicode Standard UAX#15.

NOTE 1 – By definition, the result of applying any of these normalization forms is stable over time. It means that a normalized representation of text remains normalized even when the standard is amended.

NOTE 2 – Some normalizations forms favor composite sequences over shorter representations of text, others favor the shorter representations. The backward compatibility requirement is provided by establishing ISO/IEC 10646-1:2000 and ISO/IEC 10646-2:2001 as the reference versions for the definition of the shorter representation of text.

Page 14, before sub-clause 24.3

In the current clause 24 (which becomes 25), insert a new clause 25.3 (after the current clause 24.2):

25.3 Alternate coded representations

Alternate coded representations of text are generated by using multiple combining characters in different orders, or using various equivalent combinations of characters and composite sequences. These alternate coded representations result in multiple representation of the same text. Normalizing these coded representations creates a unique representation.

NOTE – For example, in implementation level 3 the French word “là” may be represented by the characters LATIN SMALL LETTER L followed by LATIN SMALL LETTER A WITH GRAVE, or may be represented by the characters LATIN SMALL LETTER L followed by LATIN SMALL LETTER A followed by COMBINING GRAVE ACCENT. When the normalizations forms are applied on those alternate coded representations, only one representation remains. The form of the remaining representation depends on the normalization form used.

In the current clause 24.3 (new 25.4), remove the Note (replaced by note mentioned above)

Page 14, clause 24 Combining characters

Change the second paragraph of sub-clause 24.5 introduced by the first amendment (now sub-clause 25.5) to read as follows:

No sequences using characters from VARIATION SELECTOR-2 to VARIATION SELECTOR-16 from the Basic Multilingual Plane and VARIATION SELECTOR-17 to VARIATION SELECTOR-256 from the Supplementary Special-purpose Plane are defined at this time.

In the table showing the variant appearances change the entry <2269, FE00> as follows:

<2269, FE00	GREATER-THAN BUT NOT EQUAL TO with vertical stroke
-------------	--

Remove the entries <2278, FE00> and <2279, FE00> from the same table.

Page 304, clause 27 CJK Unified ideographs

After the clause title, add a new sub-clause title:

28.1 Code tables

Add the following Hanzi G sources after ‘GE GB16500-95’:

- G_KX Kangxi Dictionary ideographs (康熙字典) including the addendum (康熙字典) 補遺.
- G_HZ Han Yu Da Zi Dian ideographs (漢語大字典).

Insert the new Hanzi H source reference after the Hanzi GK sources as follows:

The Hanzi H source is:

H Hong Kong Supplementary Character Set

Add the following Hanja K source after ‘K3 PKS C 5700-2 1994’:

K4 PKS 5700-3:1998

Insert the new Hanja KP source references after the Hanja K sources as follows:

Hanja KP sources are

KP0 KPS 9566-97

KP1 KPS 10721-2000

Add the following ChuNom V sources after ‘V1 TCVN 6056:1995’:

V2 VHN 01:1998

V3 VHN 02:1998

After the last paragraph of the current clause 27, add the following new text:

28.2 Source references for CJK Unified Ideographs

The source references to CJK Unified Ideographs and CJK Unified Ideographs Extension A provide source information in a machine-readable format that is accessible as a link to this document. The content pointed to by these links is also normative.

The content linked to is a plain text file, using ISO/IEC 646-IRV characters with LINE FEED as end of line mark, that specifies, after a 11-line header, as many lines as CJK Unified Ideographs in the sum of the two blocks; each containing the following information organized in fixed width fields:

- 01-05 octet: Plane 0 code position (0hxxx)
- 06-12 octet: Hanzi G sources (G0-hxxx), (G1-hxxx), (G3-hxxx), (G5-hxxx), (G7-hxxx), (G8-hxxx), (GE-hxxx), (G_KX) or (G_HZ).
- 13-19 octet: Hanzi T sources (T1-hxxx), (T2-hxxx), (T3-hxxx), (T4-hxxx), (T5-hxxx), (T6-hxxx), (T7-hxxx) or (TF-hxxx) .
- 20-26 octet: Kanji J sources (J0-hxxx), (J1-hxxx) or (JA-hxxx) .
- 27-33 octet: Hanja K source (K0-hxxx), (K1-hxxx), (K2-hxxx), (K3-hxxx) or (K4-dddd) .
- 34-40 octet: ChuNom V sources (V0-hxxx), (V1-hxxx), (V2-hxxx) or (V3-hxxx) .
- 41-47 octet: Hanzi H source (H-hxxx) .
- 48-55 octet: Hanja KP sources (KP0-hxxx) or (KP1-hxxx) .

The format definition uses 'd' as a decimal unit and 'h' as a hexadecimal unit. Uppercase characters and all other symbols between parentheses including the space character appear as shown.

[Click on this highlighted text to access the reference file.](#)

NOTE 1 – The content is also available as a separate viewable file in the same file directory as this document. The file is named: "CJKUA_SR.txt".

NOTE 2 – The referenced file is only available to users who obtain their copy of the standard in a machine-readable format. However, the file format makes it printable.

Page 880, Annex A.1

Add a '*' (for fixed collections) to the following collections:

6 SPACING MODIFIER LETTERS
15 ARABIC EXTENDED
43 ENCLOSED ALPHANUMERICS
56 CJK COMPATIBILITY
66 CJK COMPATIBILITY FORMS

In the list of collection numbers and names, after

103 VARIATION SELECTORS

insert new entries as follows:

104 LTR ALPHABETIC PRESENTATION FORMS
FB00-FB1C
105 LTR ALPHABETIC PRESENTATION FORMS
FB1D-FB4F
106 LIMBU
1900-194F
107 TAI LE
1950-197F
108 KHMER SYMBOLS
19E0-19FF *
109 PHONETIC EXTENSIONS
1D00-1D7F
110 MISCELLANEOUS SYMBOL AND ARROWS
2B00-2B2F
111 YIJING HEXAGRAM SYMBOLS
4DC0-4DFF *

Move the collection 63:

63 ALPHABETIC PRESENTATION FORMS

within the list already describing collections which are union of particular collections (collection 250 and 251) as follows:

63 ALPHABETIC PRESENTATION FORMS
Collections 104-105

After

282 MES-1

add

283 MODERN EUROPEAN SCRIPTS See A.4.3 *

After

304 UNICODE 3.2

add

305 UNICODE 4.0 See A.5.3 *

Page 881, Annex A.1

Under Note 1, add '104' to the list of numbers (after 96).

In the alphabetical list of keywords:

add collection "110" to the entry "Arrows",

add collections "104" and "105" to the entry "Presentation forms",

and add collection "108" to the entry "Khmer".

In the alphabetical list of keywords, after

Letter

insert

Limbu

106

After

Oriya

<i>Insert</i>		
Phonetic extensions	109	
<i>After</i>		
Tagbanwa		
<i>insert</i>		
Tai Le	107	
<i>After</i>		
Yi		
<i>insert</i>		
Yijing hexagram symbols	111	

Page 881, Annex A.2

In the list of blocks in the BMP, after MONGOLIAN

insert new entries as follows:

LIMBU	1900-194F
TAI LE	1950-197F
KHMER SYMBOLS	19E0-19FF
PHONETIC EXTENSIONS	1D00-1D7F

after

SUPPLEMENTAL MATHEMATICAL OPERATORS

insert a new entry as follows:

MISCELLANEOUS SYMBOLS AND ARROWS	2B00-2B2F
----------------------------------	-----------

after

CJK UNIFIED IDEOGRAPHS EXTENSION A

insert a new entry as follows:

YIJING HEXAGRAM SYMBOLS	4DC0-4DFF
-------------------------	-----------

Page 884, Annex A

At the end of sub-clause A.4.2 added by the first amendment, add new sub-clause A.4.3 as follows:

A.4.3 283 MODERN EUROPEAN SCRIPTS

283 MODERN EUROPEAN SCRIPTS is specified by the following collections:

Collection number and name

1	BASIC LATIN
2	LATIN-1 SUPPLEMENT
3	LATIN EXTENDED-A
4	LATIN EXTENDED-B
5	IPA EXTENSIONS
6	SPACING MODIFIER LETTERS
7	COMBINING DIACRITICAL MARKS
8	BASIC GREEK
9	GREEK SYMBOLS AND COPTIC
10	CYRILLIC
11	ARMENIAN
27	BASIC GEORGIAN
30	LATIN EXTENDED ADDITIONAL
31	GREEK EXTENDED
32	GENERAL PUNCTUATION
33	SUPERSCRIPTS AND SUBSCRIPTS
34	CURRENCY SYMBOLS
35	COMBINING DIACRITICAL MARKS FOR SYMBOLS

36	LETTERLIKE SYMBOLS
37	NUMBER FORMS
38	ARROWS
39	MATHEMATICAL OPERATORS
40	MISCELLANEOUS TECHNICAL
42	OPTICAL CHARACTER RECOGNITION
44	BOX DRAWING
45	BLOCK ELEMENTS
46	GEOMETRIC SHAPES
47	MISCELLANEOUS SYMBOLS
65	COMBINING HALF MARKS
70	SPECIALS
92	CYRILLIC SUPPLEMENT
104	LTR ALPHABETIC PRESENTATION FORMS

Page 884, Annex A

At the end of sub-clause A.5.2 added by the first amendment, add new sub-clause A.5.3 as follows:

A.5.3 305 UNICODE 4.0

305 The fixed collection UNICODE 4.0 consists of fixed collections from A.5.2 above and several ranges of code positions arranged by planes as follows.

Plane 0-10Collection number and name

304 UNICODE 3.2

Plane 0Collection number and name

108 KHMER SYMBOLS
111 YIJING HEXAGRAM SYMBOLS

Rows Positions

02	21 34-36 AE-AF EF-FF
03	50-57 5D-5F F7-F8
06	00-03 0D-14 56-59 EE-EF FF
07	2D-2F 4D-4F
09	04 BD
0A	01 03 8C E1-E3 F1
0B	35 F3-FA
0C	BC-BD
17	DD F0-F9
19	00-1C 20-2B 30-3B 40 44-4F 50-6D 70-74
1D	00-6A
20	53-54
21	3B
23	CF
24	FF
26	14-15 8A-91 A0-A1
2B	00-0D
32	1D-1E 50 7C-7D CC-CF
33	77-7A DE-DF FF
FA	70-E9
FD	FD
FE	47-48

Plane 1Collection number and name

1011 SHAVIAN

Rows Positions

00 00-0B 0D-26 28-3A 3C-3D 3F-4D 50-5D 80-FA
 01 00-02 07-33 37-3F
 03 80-9D 9F
 04 26-27 4E-4F 80-9D A0-A9
 08 00-05 08 0A-35 37-38 3C 3F
 D3 00-56
 D4 C1

Plane ECollection number and name

3003 VARIATION SELECTORS SUPPLEMENT

Page 888, Annex B

In B.1, List of all combining characters, maintaining the increasing code position order, insert the following new entries:

0610 ARABIC SIGN SALLALLAHOU ALAYHE WASALLAM
 0611 ARABIC SIGN ALAYHE ASSALAM
 0612 ARABIC SIGN RAHMATULLAH ALAYHE
 0613 ARABIC SIGN RADI ALLAHOU ANHU
 0614 ARABIC SIGN TAKHALLUS
 0656 ARABIC SUBSCRIPT ALEF
 0657 ARABIC INVERTED DAMMA
 0658 ARABIC NOON-GHUNNA
 0659 ARABIC SMALL HIGH TAH
 0A01 GURMUKHI SIGN ADAK BINDI
 0A03 GURMUKHI SIGN VISARGA
 0AE2 GUJARATI VOWEL SIGN VOCALIC L
 0AE3 GUJARATI VOWEL SIGN VOCALIC LL
 0CBC KANNADA SIGN NUKTA
 17DD KHMER SIGN ATTHACAN
 1920 LIMBU VOWEL SIGN A
 1921 LIMBU VOWEL SIGN I
 1922 LIMBU VOWEL SIGN U
 1923 LIMBU VOWEL SIGN EE
 1924 LIMBU VOWEL SIGN AI
 1925 LIMBU VOWEL SIGN OO
 1926 LIMBU VOWEL SIGN AU
 1927 LIMBU VOWEL SIGN E
 1928 LIMBU VOWEL SIGN O
 1929 LIMBU SUBJOINED LETTER YA
 192A LIMBU SUBJOINED LETTER RA
 192B LIMBU SUBJOINED LETTER WA
 1930 LIMBU SMALL LETTER KA
 1931 LIMBU SMALL LETTER NGA
 1932 LIMBU SMALL LETTER ANUSVARA
 1933 LIMBU SMALL LETTER TA
 1934 LIMBU SMALL LETTER NA
 1935 LIMBU SMALL LETTER PA
 1936 LIMBU SMALL LETTER MA
 1937 LIMBU SMALL LETTER RA
 1938 LIMBU SMALL LETTER LA
 1939 LIMBU SIGN MUKPHRENG
 193A LIMBU SIGN KEMPHRENG
 193B LIMBU SIGN SA-I

Remove the entries:

06DD ARABIC END OF AYAH
 17B4 KHMER VOWEL INHERENT AQ
 17B5 KHMER VOWEL INHERENT AA

Page 899, Annex F

Insert a new entry at the beginning of F.1.1 as follows:

COMBINING GRAPHEME JOINER (034F): The Combining Grapheme Joiner is used to indicate that adjacent characters belong to the same grapheme cluster. Grapheme clusters are sequences of one or more coded characters that correspond to what users think of as characters. They include, but are not limited to, composite sequences such as (g + °), digraphs such as Slovak “ch”, or sequences with letter modifiers such as k^w. The Combining Grapheme Joiner has no width in its presentation.

Add a new clause F.5 as follows:

F.5 Subtending format characters

The following characters are used to subtend a sequence of subsequent characters:

0600 ARABIC NUMBER SIGN
 0601 ARABIC SIGN SANAH
 0602 ARABIC FOOTNOTE MARKER
 06DD ARABIC END OF AYAH
 070F SYRIAC ABBREVIATION MARK

The scope of these characters is the subsequent sequence of digits (plus certain other characters), with the exact specification as defined in the Unicode Standard, Version 3.2, for ARABIC END OF AYAH.

Page 904, Annex G

Insert each of the new character name entries at the appropriate position, ordered alphabetically by the character name, in the list of character names in Annex G. These new names are provided in a machine-readable format that is accessible as a link to this document.

NOTE 1 – The reference file is only available to users who obtain their copy of the amendment in a machine-readable form. However, the file format makes it printable.

[Click on this highlighted text to access the file containing the new names.](#)

NOTE 2 – The content is also available as a separate viewable file in the same directory as this document. The file is named: “Am2names.txt”.

Page 961, Annex P

Insert the following text after the 11C2 entry:

17A3 KHMER INDEPENDENT VOWEL QAQ

This character is only used for Pali/Sanskrit transliteration. The use of this character is discouraged; 17A2 KHMER LETTER QA should be used instead.

17A4 KHMER INDEPENDENT VOWEL QAA

This character is only used for Pali/Sanskrit transliteration. The use of this character is discouraged; the sequence <17A2, 17B6> (KHMER LETTER QA followed by KHMER VOWEL SIGN AA) should be used instead.

17B4 KHMER VOWEL INHERENT AQ**17B5 KHMER VOWEL INHERENT AA**

Khmer inherent vowels. These characters are for phonetic transcription to distinguish Indic language inherent vowels from Khmer inherent vowels. They are included solely for compatibility with particular applications; their use in other contexts is discouraged.

17D3 KHMER SIGN BATHAMASAT

This character represents a rare sign representing the first August of leap year in the lunar calendar. The use of this character is discouraged in favor of the characters from the KHMER SYMBOLS collection.

17D8 KHMER SIGN BEYYAL

This character represents the concept of 'et cetera'. The use of this character is discouraged; other abbreviations for 'et cetera' also exist. The preferred spelling is the sequence <17D4, 179B, 17D4>.

Page 20-303 Code Tables and list of character names

1. Corrigenda and modifications to existing tables

Insert the additional character glyphs and names at the indicated positions in the tables given below, the character names replacing the existing entries which read "(This position shall not be used)". The table numbers are affected by the insertion of new tables (see below) preceding these modified tables. (The table numbers corresponding to the 2nd edition of ISO/IEC 10646-1 are mentioned in parenthesis.)

Table 6 - Row 01-2: Latin Extended B (6)

Table 7 - Row 02: IPA Extensions (7)

Table 8 - Row 02: Spacing Modifier Letters (8)

Table 9 - Row 03: Combining Diacritical Marks (9)

Table 10 - Row 03: Greek and Coptic (10)

Table 16 - Row 06: Arabic (15)

Table 17 - Row 06: Arabic (16)

Table 18 - Row 07: Syriac (17)

Table 20 - Row 09: Devanagari (19)

Table 21 - Row 09: Bengali (20)

Table 22 - Row 0A: Gurmukhi (21)

Table 23 - Row 0A: Gujarati (22)

Table 24 - Row 0B: Oriya (23)

Table 25 - Row 0B: Tamil (24)

Table 27 - Row 0C: Kannada (26)

Table 52 - Row 17: Khmer (47)

Table 62 - Row 20: General Punctuation (53)

Table 66 - Row 21: Letterlike Symbols (57)

Table 72 - Row 23: Miscellaneous Technical (63)

Table 75 - Row 24: Enclosed Alphanumerics (66)

Table 77 - Row 26: Miscellaneous Symbols (62)

Table 79 - Row 26: Miscellaneous Symbols (70)

Table 80 - Row 27: Dingbats (71)

Table 104 - Row 32: Enclosed CJK Letters and Months (86)

Table 105 - Row 32: Enclosed CJK Letters and Months (87)

Table 106 - Row 33: CJK Compatibility (88)

Table 107 - Row 33: CJK Compatibility (89)

Table 151 - Row FA: CJK Compatibility characters

Table 156 - Row FD: Arabic Presentation Forms-A (136)

Table 159 - Row FE: CJK Compatibility Forms (138)

These tables contain updated graphic symbols at the following code positions:

06DD, 0A33, 0ABD, 17B4-17B5

and the new characters and names at the following code positions:

0221, 0234-0236, 02AE-02AF, 02EF-02FF, 0350-0357, 035D-035F, 03F7-03F8, 0600-0603, 060D-0614, 0656-0659, 06EE-06EF, 06FF, 072D-072F, 074D-074F, 0904, 09BD, 0A01, 0A03, 0A8C, 0AE1-0AE3, 0AF1, 0B35, 0BF3-0BFA, 0CBC-0CBD, 17DD, 17F0-17F9, 2053-2054, 213B, 23CF, 24FF, 2614-2615, 268A-2691, 26A0-26A1, 321D-321E, 3250, 327C-327D, 32CC-32CF, 3377-337A, 33DE-33DF, 33FF, FA70-FAE9, FDFD, FE47-FE48.

2. New tables.

Insert the following additional tables and adjust the numbering of the existing tables that follow. When correctly applied, all tables will be arranged by ascending code position.

Table 54 - Row 19: Limbu

Table 55 - Row 19: Tai Le

Table 56 - Row 19: Khmer Symbols

Table 57 - Row 1D: Phonetic Extensions

Table 91 - Row 2B: Miscellaneous Symbols and Arrows

Table 108 - Row 4D: Yijing Hexagram Symbols

These tables add new characters and names at the following code positions:

1900-191C, 1920-192B, 1930-193B, 1940, 1944-194F, 1950-196D, 1970-1974, 19E0-19FF, 1D00-1D6A, 2B00-2B0D, 4DC0-4DFF.

(This page left intentionally blank)

Table 6 - Rows 01-02: Latin Extended-B

	01F	020	021	022	023	024
0	ĵ 01F0	À 0200	Ř 0210	ŋ 0220	Ō 0230	
1	DZ 01F1	à 0201	ř 0211	đ 0221	ō 0231	
2	Dz 01F2	Â 0202	Ŕ 0212	8 0222	Ȳ 0232	
3	dz 01F3	â 0203	ŕ 0213	8 0223	ȳ 0233	
4	Ć 01F4	È 0204	Û 0214	Ź 0224	ł 0234	
5	ć 01F5	è 0205	ù 0215	ź 0225	ń 0235	
6	H 01F6	Ê 0206	Û 0216	Ą 0226	ţ 0236	
7	Ŕ 01F7	ê 0207	û 0217	ą 0227		
8	Ń 01F8	İ 0208	Ş 0218	Ę 0228		
9	ń 01F9	ì 0209	ş 0219	ę 0229		
A	Á 01FA	Î 020A	Ţ 021A	Ö 022A		
B	á 01FB	î 020B	ţ 021B	ö 022B		
C	Æ 01FC	Ò 020C	Ɔ 021C	Õ 022C		
D	æ 01FD	ò 020D	Ɔ 021D	õ 022D		
E	Ø 01FE	Ô 020E	Ĥ 021E	Ó 022E		
F	ø 01FF	ô 020F	ĥ 021F	ó 022F		

G = 00
P = 00

Table 6 - Rows 01-02: Latin Extended-B

HEX	NAME	HEX	NAME
01F0	LATIN SMALL LETTER J WITH CARON	024D	(This position shall not be used)
01F1	LATIN CAPITAL LETTER DZ	024E	(This position shall not be used)
01F2	LATIN CAPITAL LETTER D WITH SMALL LETTER Z	024F	(This position shall not be used)
01F3	LATIN SMALL LETTER DZ		
01F4	LATIN CAPITAL LETTER G WITH ACUTE		
01F5	LATIN SMALL LETTER G WITH ACUTE		
01F6	LATIN CAPITAL LETTER HWAIR		
01F7	LATIN CAPITAL LETTER WYNN		
01F8	LATIN CAPITAL LETTER N WITH GRAVE		
01F9	LATIN SMALL LETTER N WITH GRAVE		
01FA	LATIN CAPITAL LETTER A WITH RING ABOVE AND ACUTE		
01FB	LATIN SMALL LETTER A WITH RING ABOVE AND ACUTE		
01FC	LATIN CAPITAL LETTER AE WITH ACUTE (ash) *		
01FD	LATIN SMALL LETTER AE WITH ACUTE (ash) *		
01FE	LATIN CAPITAL LETTER O WITH STROKE AND ACUTE		
01FF	LATIN SMALL LETTER O WITH STROKE AND ACUTE		
0200	LATIN CAPITAL LETTER A WITH DOUBLE GRAVE		
0201	LATIN SMALL LETTER A WITH DOUBLE GRAVE		
0202	LATIN CAPITAL LETTER A WITH INVERTED BREVE		
0203	LATIN SMALL LETTER A WITH INVERTED BREVE		
0204	LATIN CAPITAL LETTER E WITH DOUBLE GRAVE		
0205	LATIN SMALL LETTER E WITH DOUBLE GRAVE		
0206	LATIN CAPITAL LETTER E WITH INVERTED BREVE		
0207	LATIN SMALL LETTER E WITH INVERTED BREVE		
0208	LATIN CAPITAL LETTER I WITH DOUBLE GRAVE		
0209	LATIN SMALL LETTER I WITH DOUBLE GRAVE		
020A	LATIN CAPITAL LETTER I WITH INVERTED BREVE		
020B	LATIN SMALL LETTER I WITH INVERTED BREVE		
020C	LATIN CAPITAL LETTER O WITH DOUBLE GRAVE		
020D	LATIN SMALL LETTER O WITH DOUBLE GRAVE		
020E	LATIN CAPITAL LETTER O WITH INVERTED BREVE		
020F	LATIN SMALL LETTER O WITH INVERTED BREVE		
0210	LATIN CAPITAL LETTER R WITH DOUBLE GRAVE		
0211	LATIN SMALL LETTER R WITH DOUBLE GRAVE		
0212	LATIN CAPITAL LETTER R WITH INVERTED BREVE		
0213	LATIN SMALL LETTER R WITH INVERTED BREVE		
0214	LATIN CAPITAL LETTER U WITH DOUBLE GRAVE		
0215	LATIN SMALL LETTER U WITH DOUBLE GRAVE		
0216	LATIN CAPITAL LETTER U WITH INVERTED BREVE		
0217	LATIN SMALL LETTER U WITH INVERTED BREVE		
0218	LATIN CAPITAL LETTER S WITH COMMA BELOW *		
0219	LATIN SMALL LETTER S WITH COMMA BELOW *		
021A	LATIN CAPITAL LETTER T WITH COMMA BELOW *		
021B	LATIN SMALL LETTER T WITH COMMA BELOW *		
021C	LATIN CAPITAL LETTER YOGH		
021D	LATIN SMALL LETTER YOGH		
021E	LATIN CAPITAL LETTER H WITH CARON		
021F	LATIN SMALL LETTER H WITH CARON		
0220	LATIN CAPITAL LETTER N WITH LONG RIGHT LEG		
0221	LATIN SMALL LETTER D WITH CURL		
0222	LATIN CAPITAL LETTER OU		
0223	LATIN SMALL LETTER OU		
0224	LATIN CAPITAL LETTER Z WITH HOOK		
0225	LATIN SMALL LETTER Z WITH HOOK		
0226	LATIN CAPITAL LETTER A WITH DOT ABOVE		
0227	LATIN SMALL LETTER A WITH DOT ABOVE		
0228	LATIN CAPITAL LETTER E WITH CEDILLA		
0229	LATIN SMALL LETTER E WITH CEDILLA		
022A	LATIN CAPITAL LETTER O WITH DIAERESIS AND MACRON		
022B	LATIN SMALL LETTER O WITH DIAERESIS AND MACRON		
022C	LATIN CAPITAL LETTER O WITH TILDE AND MACRON		
022D	LATIN SMALL LETTER O WITH TILDE AND MACRON		
022E	LATIN CAPITAL LETTER O WITH DOT ABOVE		
022F	LATIN SMALL LETTER O WITH DOT ABOVE		
0230	LATIN CAPITAL LETTER O WITH DOT ABOVE AND MACRON		
0231	LATIN SMALL LETTER O WITH DOT ABOVE AND MACRON		
0232	LATIN CAPITAL LETTER Y WITH MACRON		
0233	LATIN SMALL LETTER Y WITH MACRON		
0234	LATIN SMALL LETTER L WITH CURL		
0235	LATIN SMALL LETTER N WITH CURL		
0236	LATIN SMALL LETTER T WITH CURL		
0237	(This position shall not be used)		
0238	(This position shall not be used)		
0239	(This position shall not be used)		
023A	(This position shall not be used)		
023B	(This position shall not be used)		
023C	(This position shall not be used)		
023D	(This position shall not be used)		
023E	(This position shall not be used)		
023F	(This position shall not be used)		
0240	(This position shall not be used)		
0241	(This position shall not be used)		
0242	(This position shall not be used)		
0243	(This position shall not be used)		
0244	(This position shall not be used)		
0245	(This position shall not be used)		
0246	(This position shall not be used)		
0247	(This position shall not be used)		
0248	(This position shall not be used)		
0249	(This position shall not be used)		
024A	(This position shall not be used)		
024B	(This position shall not be used)		
024C	(This position shall not be used)		

Group 00

Plane 00

Row 01

Table 7 - Row 02: IPA Extensions

	025	026	027	028	029	02A
0	ɐ 0250	ɟ 0260	ɥ 0270	ʀ 0280	ʐ 0290	ɕ 02A0
1	ɑ 0251	ɡ 0261	ŋ 0271	ʁ 0281	ʑ 0291	ʑ̥ 02A1
2	ɒ 0252	ɠ 0262	ɲ 0272	ʂ 0282	ʑ̥ 0292	ɕ̥ 02A2
3	ɓ 0253	ɣ 0263	ɳ 0273	ʃ 0283	ʑ̥ 0293	ɕ̥ 02A3
4	ɔ̥ 0254	ɣ̥ 0264	ɴ 0274	ʃ̥ 0284	ʑ̥ 0294	ɕ̥ 02A4
5	ɔ̥ 0255	ɥ̥ 0265	ɵ 0275	ɺ 0285	ɕ̥ 0295	ɕ̥ 02A5
6	ɔ̥ 0256	ɦ 0266	æ 0276	ɺ̥ 0286	ɺ̥ 0296	ɕ̥ 02A6
7	ɔ̥ 0257	ɦ̥ 0267	ω 0277	ɺ̥ 0287	ɕ̥ 0297	ɕ̥ 02A7
8	ə̥ 0258	ɨ̥ 0268	ϕ 0278	ɺ̥ 0288	⊙ 0298	ɕ̥ 02A8
9	ə̥ 0259	ɺ̥ 0269	ɺ̥ 0279	ɺ̥ 0289	ɺ̥ 0299	ɕ̥ 02A9
A	ɺ̥ 025A	ɺ̥ 026A	ɺ̥ 027A	ɺ̥ 028A	ɺ̥ 029A	ɕ̥ 02AA
B	ɺ̥ 025B	ɺ̥ 026B	ɺ̥ 027B	ɺ̥ 028B	ɺ̥ 029B	ɕ̥ 02AB
C	ɺ̥ 025C	ɺ̥ 026C	ɺ̥ 027C	ɺ̥ 028C	ɺ̥ 029C	ɕ̥ 02AC
D	ɺ̥ 025D	ɺ̥ 026D	ɺ̥ 027D	ɺ̥ 028D	ɺ̥ 029D	ɕ̥ 02AD
E	ɺ̥ 025E	ɺ̥ 026E	ɺ̥ 027E	ɺ̥ 028E	ɺ̥ 029E	ɕ̥ 02AE
F	ɺ̥ 025F	ɺ̥ 026F	ɺ̥ 027F	ɺ̥ 028F	ɺ̥ 029F	ɕ̥ 02AF

G = 00
P = 00

Table 7 - Row 02: IPA Extensions

HEX	NAME	HEX	NAME
0250	LATIN SMALL LETTER TURNED A	02AD	LATIN LETTER BIDENTAL PERCUSSIVE
0251	LATIN SMALL LETTER ALPHA	02AE	LATIN SMALL LETTER TURNED H WITH FISHHOOK
0252	LATIN SMALL LETTER TURNED ALPHA	02AF	LATIN SMALL LETTER TURNED H WITH FISHHOOK AND TAIL
0253	LATIN SMALL LETTER B WITH HOOK		
0254	LATIN SMALL LETTER OPEN O		
0255	LATIN SMALL LETTER C WITH CURL		
0256	LATIN SMALL LETTER D WITH TAIL		
0257	LATIN SMALL LETTER D WITH HOOK		
0258	LATIN SMALL LETTER REVERSED E		
0259	LATIN SMALL LETTER SCHWA		
025A	LATIN SMALL LETTER SCHWA WITH HOOK		
025B	LATIN SMALL LETTER OPEN E		
025C	LATIN SMALL LETTER REVERSED OPEN E		
025D	LATIN SMALL LETTER REVERSED OPEN E WITH HOOK		
025E	LATIN SMALL LETTER CLOSED REVERSED OPEN E		
025F	LATIN SMALL LETTER DOTLESS J WITH STROKE		
0260	LATIN SMALL LETTER G WITH HOOK		
0261	LATIN SMALL LETTER SCRIPT G		
0262	LATIN LETTER SMALL CAPITAL G		
0263	LATIN SMALL LETTER GAMMA		
0264	LATIN SMALL LETTER RAMS HORN		
0265	LATIN SMALL LETTER TURNED H		
0266	LATIN SMALL LETTER H WITH HOOK		
0267	LATIN SMALL LETTER HENG WITH HOOK		
0268	LATIN SMALL LETTER I WITH STROKE		
0269	LATIN SMALL LETTER IOTA		
026A	LATIN LETTER SMALL CAPITAL I		
026B	LATIN SMALL LETTER L WITH MIDDLE TILDE		
026C	LATIN SMALL LETTER L WITH BELT		
026D	LATIN SMALL LETTER L WITH RETROFLEX HOOK		
026E	LATIN SMALL LETTER LEZH		
026F	LATIN SMALL LETTER TURNED M		
0270	LATIN SMALL LETTER TURNED M WITH LONG LEG		
0271	LATIN SMALL LETTER M WITH HOOK		
0272	LATIN SMALL LETTER N WITH LEFT HOOK		
0273	LATIN SMALL LETTER N WITH RETROFLEX HOOK		
0274	LATIN LETTER SMALL CAPITAL N		
0275	LATIN SMALL LETTER BARRED O		
0276	LATIN LETTER SMALL CAPITAL OE		
0277	LATIN SMALL LETTER CLOSED OMEGA		
0278	LATIN SMALL LETTER PHI		
0279	LATIN SMALL LETTER TURNED R		
027A	LATIN SMALL LETTER TURNED R WITH LONG LEG		
027B	LATIN SMALL LETTER TURNED R WITH HOOK		
027C	LATIN SMALL LETTER R WITH LONG LEG		
027D	LATIN SMALL LETTER R WITH TAIL		
027E	LATIN SMALL LETTER R WITH FISHHOOK		
027F	LATIN SMALL LETTER REVERSED R WITH FISHHOOK		
0280	LATIN LETTER SMALL CAPITAL R *		
0281	LATIN LETTER SMALL CAPITAL INVERTED R		
0282	LATIN SMALL LETTER S WITH HOOK		
0283	LATIN SMALL LETTER ESH		
0284	LATIN SMALL LETTER DOTLESS J WITH STROKE AND HOOK		
0285	LATIN SMALL LETTER SQUAT REVERSED ESH		
0286	LATIN SMALL LETTER ESH WITH CURL		
0287	LATIN SMALL LETTER TURNED T		
0288	LATIN SMALL LETTER T WITH RETROFLEX HOOK		
0289	LATIN SMALL LETTER U BAR		
028A	LATIN SMALL LETTER UPSILON		
028B	LATIN SMALL LETTER V WITH HOOK		
028C	LATIN SMALL LETTER TURNED V		
028D	LATIN SMALL LETTER TURNED W		
028E	LATIN SMALL LETTER TURNED Y		
028F	LATIN LETTER SMALL CAPITAL Y		
0290	LATIN SMALL LETTER Z WITH RETROFLEX HOOK		
0291	LATIN SMALL LETTER Z WITH CURL		
0292	LATIN SMALL LETTER EZH		
0293	LATIN SMALL LETTER EZH WITH CURL		
0294	LATIN LETTER GLOTTAL STOP		
0295	LATIN LETTER PHARYNGEAL VOICED FRICATIVE		
0296	LATIN LETTER INVERTED GLOTTAL STOP		
0297	LATIN LETTER STRETCHED C		
0298	LATIN LETTER BILABIAL CLICK		
0299	LATIN LETTER SMALL CAPITAL B		
029A	LATIN SMALL LETTER CLOSED OPEN E		
029B	LATIN LETTER SMALL CAPITAL G WITH HOOK		
029C	LATIN LETTER SMALL CAPITAL H		
029D	LATIN SMALL LETTER J WITH CROSSED-TAIL		
029E	LATIN SMALL LETTER TURNED K		
029F	LATIN LETTER SMALL CAPITAL L		
02A0	LATIN SMALL LETTER Q WITH HOOK		
02A1	LATIN LETTER GLOTTAL STOP WITH STROKE		
02A2	LATIN LETTER REVERSED GLOTTAL STOP WITH STROKE		
02A3	LATIN SMALL LETTER DZ DIGRAPH		
02A4	LATIN SMALL LETTER DEZH DIGRAPH		
02A5	LATIN SMALL LETTER DZ DIGRAPH WITH CURL		
02A6	LATIN SMALL LETTER TS DIGRAPH		
02A7	LATIN SMALL LETTER TESH DIGRAPH		
02A8	LATIN SMALL LETTER TC DIGRAPH WITH CURL		
02A9	LATIN SMALL LETTER FENG DIGRAPH		
02AA	LATIN SMALL LETTER LS DIGRAPH		
02AB	LATIN SMALL LETTER LZ DIGRAPH		
02AC	LATIN LETTER BILABIAL PERCUSSIVE		

Group 00

Plane 00

Row 02

Table 8 - Row 02: Spacing Modifier Letters

	02B	02C	02D	02E	02F
0	h 02B0	? 02C0	▽ 02D0	Ÿ 02E0	^ 02F0
1	ĥ 02B1	ƒ 02C1	▽ 02D1	l 02E1	< 02F1
2	j 02B2	< 02C2	› 02D2	S 02E2	> 02F2
3	r 02B3	> 02C3	◁ 02D3	X 02E3	◦ 02F3
4	Ĭ 02B4	^ 02C4	⊥ 02D4	ƒ 02E4	˘ 02F4
5	Ĵ 02B5	∨ 02C5	⊥ 02D5	└ 02E5	↘ 02F5
6	Ɔ 02B6	^ 02C6	+ 02D6	└ 02E6	↗ 02F6
7	W 02B7	∨ 02C7	- 02D7	└ 02E7	~ 02F7
8	y 02B8	˙ 02C8	◌ 02D8	└ 02E8	⋮ 02F8
9	/ 02B9	- 02C9	• 02D9	└ 02E9	┌ 02F9
A	// 02BA	/ 02CA	◦ 02DA	└ 02EA	┌ 02FA
B	‘ 02BB	˘ 02CB	◌ 02DB	└ 02EB	┌ 02FB
C	, 02BC	˙ 02CC	~ 02DC	∨ 02EC	└ 02FC
D	◌ 02BD	- 02CD	↗ 02DD	= 02ED	└ 02FD
E	› 02BE	˘ 02CE	~ 02DE	” 02EE	└ 02FE
F	◁ 02BF	/ 02CF	× 02DF	∨ 02EF	← 02FF

G = 00
P = 00

Table 8 - Row 02: Spacing Modifier Letters

HEX	NAME	HEX	NAME
02B0	MODIFIER LETTER SMALL H		
02B1	MODIFIER LETTER SMALL H WITH HOOK		
02B2	MODIFIER LETTER SMALL J		
02B3	MODIFIER LETTER SMALL R		
02B4	MODIFIER LETTER SMALL TURNED R		
02B5	MODIFIER LETTER SMALL TURNED R WITH HOOK		
02B6	MODIFIER LETTER SMALL CAPITAL INVERTED R		
02B7	MODIFIER LETTER SMALL W		
02B8	MODIFIER LETTER SMALL Y		
02B9	MODIFIER LETTER PRIME		
02BA	MODIFIER LETTER DOUBLE PRIME		
02BB	MODIFIER LETTER TURNED COMMA		
02BC	MODIFIER LETTER APOSTROPHE		
02BD	MODIFIER LETTER REVERSED COMMA		
02BE	MODIFIER LETTER RIGHT HALF RING		
02BF	MODIFIER LETTER LEFT HALF RING		
02C0	MODIFIER LETTER GLOTTAL STOP		
02C1	MODIFIER LETTER REVERSED GLOTTAL STOP		
02C2	MODIFIER LETTER LEFT ARROWHEAD		
02C3	MODIFIER LETTER RIGHT ARROWHEAD		
02C4	MODIFIER LETTER UP ARROWHEAD		
02C5	MODIFIER LETTER DOWN ARROWHEAD		
02C6	MODIFIER LETTER CIRCUMFLEX ACCENT		
02C7	CARON (Mandarin Chinese third tone)		
02C8	MODIFIER LETTER VERTICAL LINE		
02C9	MODIFIER LETTER MACRON (Mandarin Chinese first tone)		
02CA	MODIFIER LETTER ACUTE ACCENT (Mandarin Chinese second tone)		
02CB	MODIFIER LETTER GRAVE ACCENT (Mandarin Chinese fourth tone)		
02CC	MODIFIER LETTER LOW VERTICAL LINE		
02CD	MODIFIER LETTER LOW MACRON		
02CE	MODIFIER LETTER LOW GRAVE ACCENT		
02CF	MODIFIER LETTER LOW ACUTE ACCENT		
02D0	MODIFIER LETTER TRIANGULAR COLON		
02D1	MODIFIER LETTER HALF TRIANGULAR COLON		
02D2	MODIFIER LETTER CENTRED RIGHT HALF RING		
02D3	MODIFIER LETTER CENTRED LEFT HALF RING		
02D4	MODIFIER LETTER UP TACK		
02D5	MODIFIER LETTER DOWN TACK		
02D6	MODIFIER LETTER PLUS SIGN		
02D7	MODIFIER LETTER MINUS SIGN		
02D8	BREVE		
02D9	DOT ABOVE (Mandarin Chinese light tone)		
02DA	RING ABOVE		
02DB	OGONEK		
02DC	SMALL TILDE		
02DD	DOUBLE ACUTE ACCENT		
02DE	MODIFIER LETTER RHOTIC HOOK		
02DF	MODIFIER LETTER CROSS ACCENT		
02E0	MODIFIER LETTER SMALL GAMMA		
02E1	MODIFIER LETTER SMALL L		
02E2	MODIFIER LETTER SMALL S		
02E3	MODIFIER LETTER SMALL X		
02E4	MODIFIER LETTER SMALL REVERSED GLOTTAL STOP		
02E5	MODIFIER LETTER EXTRA-HIGH TONE BAR		
02E6	MODIFIER LETTER HIGH TONE BAR		
02E7	MODIFIER LETTER MID TONE BAR		
02E8	MODIFIER LETTER LOW TONE BAR		
02E9	MODIFIER LETTER EXTRA-LOW TONE BAR		
02EA	MODIFIER LETTER YIN DEPARTING TONE MARK		
02EB	MODIFIER LETTER YANG DEPARTING TONE MARK		
02EC	MODIFIER LETTER VOICING		
02ED	MODIFIER LETTER UNASPIRATED		
02EE	MODIFIER LETTER DOUBLE APOSTROPHE		
02EF	MODIFIER LETTER LOW DOWN ARROWHEAD		
02F0	MODIFIER LETTER LOW UP ARROWHEAD		
02F1	MODIFIER LETTER LOW LEFT ARROWHEAD		
02F2	MODIFIER LETTER LOW RIGHT ARROWHEAD		
02F3	MODIFIER LETTER LOW RING		
02F4	MODIFIER LETTER MIDDLE GRAVE ACCENT		
02F5	MODIFIER LETTER MIDDLE DOUBLE GRAVE ACCENT		
02F6	MODIFIER LETTER MIDDLE DOUBLE ACUTE ACCENT		
02F7	MODIFIER LETTER LOW TILDE		
02F8	MODIFIER LETTER RAISED COLON		
02F9	MODIFIER LETTER BEGIN HIGH TONE		
02FA	MODIFIER LETTER END HIGH TONE		
02FB	MODIFIER LETTER BEGIN LOW TONE		
02FC	MODIFIER LETTER END LOW TONE		
02FD	MODIFIER LETTER SHELF		
02FE	MODIFIER LETTER OPEN SHELF		
02FF	MODIFIER LETTER LOW LEFT ARROW		

Group 00

Plane 00

Row 02

Table 9 - Row 03: Combining Diacritical Marks

	030	031	032	033	034	035	036
0	0300	0310	0320	0330	0340	0350	0360
1	0301	0311	0321	0331	0341	0351	0361
2	0302	0312	0322	0332	0342	0352	0362
3	0303	0313	0323	0333	0343	0353	0363
4	0304	0314	0324	0334	0344	0354	0364
5	0305	0315	0325	0335	0345	0355	0365
6	0306	0316	0326	0336	0346	0356	0366
7	0307	0317	0327	0337	0347	0357	0367
8	0308	0318	0328	0338	0348	0358	0368
9	0309	0319	0329	0339	0349	0359	0369
A	030A	031A	032A	033A	034A	035A	036A
B	030B	031B	032B	033B	034B	035B	036B
C	030C	031C	032C	033C	034C	035C	036C
D	030D	031D	032D	033D	034D	035D	036D
E	030E	031E	032E	033E	034E	035E	036E
F	030F	031F	032F	033F	034F	035F	036F

G = 00
P = 00

Table 9 - Row 03: Combining Diacritical Marks

HEX	NAME	HEX	NAME
0300	COMBINING GRAVE ACCENT (Varia)	035D	COMBINING DOUBLE BREVE
0301	COMBINING ACUTE ACCENT (Oxia, Tonos)	035E	COMBINING DOUBLE MACRON
0302	COMBINING CIRCUMFLEX ACCENT	035F	COMBINING DOUBLE MACRON BELOW
0303	COMBINING TILDE	0360	COMBINING DOUBLE TILDE
0304	COMBINING MACRON	0361	COMBINING DOUBLE INVERTED BREVE
0305	COMBINING OVERLINE	0362	COMBINING DOUBLE RIGHTWARDS ARROW BELOW
0306	COMBINING BREVE (Vrachy)	0363	COMBINING LATIN SMALL LETTER A
0307	COMBINING DOT ABOVE	0364	COMBINING LATIN SMALL LETTER E
0308	COMBINING DIAERESIS (Dialytika)	0365	COMBINING LATIN SMALL LETTER I
0309	COMBINING HOOK ABOVE	0366	COMBINING LATIN SMALL LETTER O
030A	COMBINING RING ABOVE	0367	COMBINING LATIN SMALL LETTER U
030B	COMBINING DOUBLE ACUTE ACCENT	0368	COMBINING LATIN SMALL LETTER C
030C	COMBINING CARON	0369	COMBINING LATIN SMALL LETTER D
030D	COMBINING VERTICAL LINE ABOVE	036A	COMBINING LATIN SMALL LETTER H
030E	COMBINING DOUBLE VERTICAL LINE ABOVE	036B	COMBINING LATIN SMALL LETTER M
030F	COMBINING DOUBLE GRAVE ACCENT	036C	COMBINING LATIN SMALL LETTER R
0310	COMBINING CANDRABINDU	036D	COMBINING LATIN SMALL LETTER T
0311	COMBINING INVERTED BREVE	036E	COMBINING LATIN SMALL LETTER V
0312	COMBINING TURNED COMMA ABOVE	036F	COMBINING LATIN SMALL LETTER X
0313	COMBINING COMMA ABOVE (Psii)		
0314	COMBINING REVERSED COMMA ABOVE (Dasia)		
0315	COMBINING COMMA ABOVE RIGHT		
0316	COMBINING GRAVE ACCENT BELOW		
0317	COMBINING ACUTE ACCENT BELOW		
0318	COMBINING LEFT TACK BELOW		
0319	COMBINING RIGHT TACK BELOW		
031A	COMBINING LEFT ANGLE ABOVE		
031B	COMBINING HORN		
031C	COMBINING LEFT HALF RING BELOW		
031D	COMBINING UP TACK BELOW		
031E	COMBINING DOWN TACK BELOW		
031F	COMBINING PLUS SIGN BELOW		
0320	COMBINING MINUS SIGN BELOW		
0321	COMBINING PALATALIZED HOOK BELOW		
0322	COMBINING RETROFLEX HOOK BELOW		
0323	COMBINING DOT BELOW		
0324	COMBINING DIAERESIS BELOW		
0325	COMBINING RING BELOW		
0326	COMBINING COMMA BELOW		
0327	COMBINING CEDILLA		
0328	COMBINING OGONEK		
0329	COMBINING VERTICAL LINE BELOW		
032A	COMBINING BRIDGE BELOW		
032B	COMBINING INVERTED DOUBLE ARCH BELOW		
032C	COMBINING CARON BELOW		
032D	COMBINING CIRCUMFLEX ACCENT BELOW		
032E	COMBINING BREVE BELOW		
032F	COMBINING INVERTED BREVE BELOW		
0330	COMBINING TILDE BELOW		
0331	COMBINING MACRON BELOW		
0332	COMBINING LOW LINE		
0333	COMBINING DOUBLE LOW LINE		
0334	COMBINING TILDE OVERLAY		
0335	COMBINING SHORT STROKE OVERLAY		
0336	COMBINING LONG STROKE OVERLAY		
0337	COMBINING SHORT SOLIDUS OVERLAY		
0338	COMBINING LONG SOLIDUS OVERLAY		
0339	COMBINING RIGHT HALF RING BELOW		
033A	COMBINING INVERTED BRIDGE BELOW		
033B	COMBINING SQUARE BELOW		
033C	COMBINING SEAGULL BELOW		
033D	COMBINING X ABOVE		
033E	COMBINING VERTICAL TILDE		
033F	COMBINING DOUBLE OVERLINE		
0340	COMBINING GRAVE TONE MARK (Vietnamese)		
0341	COMBINING ACUTE TONE MARK (Vietnamese)		
0342	COMBINING GREEK PERISPOMENI		
0343	COMBINING GREEK KORONIS		
0344	COMBINING GREEK DIALYTIKA TONOS		
0345	COMBINING GREEK YPOGEGRAMMENI		
0346	COMBINING BRIDGE ABOVE		
0347	COMBINING EQUALS SIGN BELOW		
0348	COMBINING DOUBLE VERTICAL LINE BELOW		
0349	COMBINING LEFT ANGLE BELOW		
034A	COMBINING NOT TILDE ABOVE		
034B	COMBINING HOMOTHETIC ABOVE		
034C	COMBINING ALMOST EQUAL TO ABOVE		
034D	COMBINING LEFT RIGHT ARROW BELOW		
034E	COMBINING UPWARDS ARROW BELOW		
034F	COMBINING GRAPHEME JOINER		
0350	COMBINING RIGHT ARROWHEAD ABOVE		
0351	COMBINING LEFT HALF RING ABOVE		
0352	COMBINING FERMATA		
0353	COMBINING X BELOW		
0354	COMBINING LEFT ARROWHEAD BELOW		
0355	COMBINING RIGHT ARROWHEAD BELOW		
0356	COMBINING RIGHT ARROWHEAD AND UP ARROWHEAD BELOW		
0357	COMBINING RIGHT HALF RING ABOVE		
0358	(This position shall not be used)		
0359	(This position shall not be used)		
035A	(This position shall not be used)		
035B	(This position shall not be used)		
035C	(This position shall not be used)		

Group 00

Plane 00

Row 03

Table 10 - Row 03: Greek and Coptic

	037	038	039	03A	03B	03C	03D	03E	03F
0			ΐ 0390	Π 03A0	ϐ 03B0	π 03C0	β 03D0	ϣ 03E0	κ 03F0
1			Α 0391	Ρ 03A1	α 03B1	ρ 03C1	θ 03D1	ϣ 03E1	ϩ 03F1
2			Β 0392		β 03B2	ς 03C2	Υ 03D2	ϣ 03E2	Ϸ 03F2
3			Γ 0393	Σ 03A3	γ 03B3	σ 03C3	Υ 03D3	ϣ 03E3	Ϸ 03F3
4	΄ 0374	΄ 0384	Δ 0394	Τ 03A4	δ 03B4	τ 03C4	Ϸ 03D4	ϣ 03E4	Θ 03F4
5	΄ 0375	⋆ 0385	Ε 0395	Υ 03A5	ε 03B5	υ 03C5	φ 03D5	ϣ 03E5	Ε 03F5
6		À 0386	Ζ 0396	Φ 03A6	ζ 03B6	φ 03C6	ω 03D6	ϣ 03E6	ε 03F6
7		· 0387	Η 0397	Χ 03A7	η 03B7	χ 03C7	ϣ 03D7	ϣ 03E7	Ϸ 03F7
8		Έ 0388	Θ 0398	Ψ 03A8	θ 03B8	ψ 03C8	Ϸ 03D8	ϣ 03E8	Ϸ 03F8
9		Ή 0389	Ι 0399	Ω 03A9	ι 03B9	ω 03C9	Ϸ 03D9	ϣ 03E9	
A	΄ 037A	Ί 038A	Κ 039A	Ί 03AA	κ 03BA	ϊ 03CA	Σ 03DA	Χ 03EA	
B			Λ 039B	Ϸ 03AB	λ 03BB	Ϸ 03CB	ς 03DB	ϣ 03EB	
C		Ό 038C	Μ 039C	ά 03AC	μ 03BC	ό 03CC	Ϸ 03DC	Ϸ 03EC	
D			Ν 039D	έ 03AD	ν 03BD	ύ 03CD	Ϸ 03DD	Ϸ 03ED	
E	΄ 037E	Υ 038E	Ξ 039E	ή 03AE	ξ 03BE	ώ 03CE	Ϸ 03DE	Ϸ 03EE	
F		Ό 038F	Ο 039F	ί 03AF	ο 03BF		Ϸ 03DF	Ϸ 03EF	

G = 00
P = 00

Table 10 - Row 03: Greek and Coptic


























HEX	NAME	HEX	NAME
0370	(This position shall not be used)	03CD	GREEK SMALL LETTER UPSILON WITH TONOS
0371	(This position shall not be used)	03CE	GREEK SMALL LETTER OMEGA WITH TONOS
0372	(This position shall not be used)	03CF	(This position shall not be used)
0373	(This position shall not be used)	03D0	GREEK BETA SYMBOL
0374	GREEK NUMERAL SIGN (Dexia keraia)	03D1	GREEK THETA SYMBOL
0375	GREEK LOWER NUMERAL SIGN (Aristeri keraia)	03D2	GREEK UPSILON WITH HOOK SYMBOL
0376	(This position shall not be used)	03D3	GREEK UPSILON WITH ACUTE AND HOOK SYMBOL
0377	(This position shall not be used)	03D4	GREEK UPSILON WITH DIAERESIS AND HOOK SYMBOL
0378	(This position shall not be used)	03D5	GREEK PHI SYMBOL
0379	(This position shall not be used)	03D6	GREEK PI SYMBOL
037A	GREEK YPOGEGRAMMENI	03D7	GREEK KAI SYMBOL
037B	(This position shall not be used)	03D8	GREEK LETTER ARCHAIC KOPPA *
037C	(This position shall not be used)	03D9	GREEK SMALL LETTER ARCHAIC KOPPA *
037D	(This position shall not be used)	03DA	GREEK LETTER STIGMA
037E	GREEK QUESTION MARK (Erotimatio)	03DB	GREEK SMALL LETTER STIGMA
037F	(This position shall not be used)	03DC	GREEK LETTER DIGAMMA
0380	(This position shall not be used)	03DD	GREEK SMALL LETTER DIGAMMA
0381	(This position shall not be used)	03DE	GREEK LETTER KOPPA
0382	(This position shall not be used)	03DF	GREEK SMALL LETTER KOPPA
0383	(This position shall not be used)	03E0	GREEK LETTER SAMPI
0384	GREEK TONOS	03E1	GREEK SMALL LETTER SAMPI
0385	GREEK DIALYTIKA TONOS	03E2	COPTIC CAPITAL LETTER SHEI
0386	GREEK CAPITAL LETTER ALPHA WITH TONOS	03E3	COPTIC SMALL LETTER SHEI
0387	GREEK ANO TELEIA	03E4	COPTIC CAPITAL LETTER FEI
0388	GREEK CAPITAL LETTER EPSILON WITH TONOS	03E5	COPTIC SMALL LETTER FEI
0389	GREEK CAPITAL LETTER ETA WITH TONOS	03E6	COPTIC CAPITAL LETTER KHEI
038A	GREEK CAPITAL LETTER IOTA WITH TONOS	03E7	COPTIC SMALL LETTER KHEI
038B	(This position shall not be used)	03E8	COPTIC CAPITAL LETTER HORI
038C	GREEK CAPITAL LETTER OMICRON WITH TONOS	03E9	COPTIC SMALL LETTER HORI
038D	(This position shall not be used)	03EA	COPTIC CAPITAL LETTER GANGIA
038E	GREEK CAPITAL LETTER UPSILON WITH TONOS	03EB	COPTIC SMALL LETTER GANGIA
038F	GREEK CAPITAL LETTER OMEGA WITH TONOS	03EC	COPTIC CAPITAL LETTER SHIMA
0390	GREEK SMALL LETTER IOTA WITH DIALYTIKA AND TONOS	03ED	COPTIC SMALL LETTER SHIMA
0391	GREEK CAPITAL LETTER ALPHA	03EE	COPTIC CAPITAL LETTER DEI
0392	GREEK CAPITAL LETTER BETA	03EF	COPTIC SMALL LETTER DEI
0393	GREEK CAPITAL LETTER GAMMA	03F0	GREEK KAPPA SYMBOL
0394	GREEK CAPITAL LETTER DELTA	03F1	GREEK RHO SYMBOL
0395	GREEK CAPITAL LETTER EPSILON	03F2	GREEK LUNATE SIGMA SYMBOL
0396	GREEK CAPITAL LETTER ZETA	03F3	GREEK LETTER YOT
0397	GREEK CAPITAL LETTER ETA	03F4	GREEK CAPITAL THETA SYMBOL
0398	GREEK CAPITAL LETTER THETA	03F5	GREEK LUNATE EPSILON SYMBOL
0399	GREEK CAPITAL LETTER IOTA	03F6	GREEK REVERSED LUNATE EPSILON SYMBOL
039A	GREEK CAPITAL LETTER KAPPA	03F7	GREEK CAPITAL LETTER SHO
039B	GREEK CAPITAL LETTER LAMDA	03F8	GREEK SMALL LETTER SHO
039C	GREEK CAPITAL LETTER MU	03F9	(This position shall not be used)
039D	GREEK CAPITAL LETTER NU	03FA	(This position shall not be used)
039E	GREEK CAPITAL LETTER XI	03FB	(This position shall not be used)
039F	GREEK CAPITAL LETTER OMICRON	03FC	(This position shall not be used)
03A0	GREEK CAPITAL LETTER PI	03FD	(This position shall not be used)
03A1	GREEK CAPITAL LETTER RHO	03FE	(This position shall not be used)
03A2	(This position shall not be used)	03FF	(This position shall not be used)
03A3	GREEK CAPITAL LETTER SIGMA		
03A4	GREEK CAPITAL LETTER TAU		
03A5	GREEK CAPITAL LETTER UPSILON		
03A6	GREEK CAPITAL LETTER PHI		
03A7	GREEK CAPITAL LETTER CHI		
03A8	GREEK CAPITAL LETTER PSI		
03A9	GREEK CAPITAL LETTER OMEGA		
03AA	GREEK CAPITAL LETTER IOTA WITH DIALYTIKA		
03AB	GREEK CAPITAL LETTER UPSILON WITH DIALYTIKA		
03AC	GREEK SMALL LETTER ALPHA WITH TONOS		
03AD	GREEK SMALL LETTER EPSILON WITH TONOS		
03AE	GREEK SMALL LETTER ETA WITH TONOS		
03AF	GREEK SMALL LETTER IOTA WITH TONOS		
03B0	GREEK SMALL LETTER UPSILON WITH DIALYTIKA AND TONOS		
03B1	GREEK SMALL LETTER ALPHA		
03B2	GREEK SMALL LETTER BETA		
03B3	GREEK SMALL LETTER GAMMA		
03B4	GREEK SMALL LETTER DELTA		
03B5	GREEK SMALL LETTER EPSILON		
03B6	GREEK SMALL LETTER ZETA		
03B7	GREEK SMALL LETTER ETA		
03B8	GREEK SMALL LETTER THETA		
03B9	GREEK SMALL LETTER IOTA		
03BA	GREEK SMALL LETTER KAPPA		
03BB	GREEK SMALL LETTER LAMDA		
03BC	GREEK SMALL LETTER MU		
03BD	GREEK SMALL LETTER NU		
03BE	GREEK SMALL LETTER XI		
03BF	GREEK SMALL LETTER OMICRON		
03C0	GREEK SMALL LETTER PI		
03C1	GREEK SMALL LETTER RHO		
03C2	GREEK SMALL LETTER FINAL SIGMA		
03C3	GREEK SMALL LETTER SIGMA		
03C4	GREEK SMALL LETTER TAU		
03C5	GREEK SMALL LETTER UPSILON		
03C6	GREEK SMALL LETTER PHI		
03C7	GREEK SMALL LETTER CHI		
03C8	GREEK SMALL LETTER PSI		
03C9	GREEK SMALL LETTER OMEGA		
03CA	GREEK SMALL LETTER IOTA WITH DIALYTIKA		
03CB	GREEK SMALL LETTER UPSILON WITH DIALYTIKA		
03CC	GREEK SMALL LETTER OMICRON WITH TONOS		

Group 00

Plane 00

Row 03

Table 16 - Row 06: Arabic

	060	061	062	063	064	065	066	067
0	 0600	 0610		ذ 0630	- 0640	 0650	٠ 0660	١ 0670
1	 0601	 0611	ء 0621	ر 0631	ف 0641	 0651	١ 0661	آ 0671
2	 0602	 0612	آ 0622	ز 0632	ق 0642	 0652	٢ 0662	أ 0672
3	 0603	 0613	أ 0623	س 0633	ك 0643	 0653	٣ 0663	إ 0673
4		 0614	ؤ 0624	ش 0634	ل 0644	 0654	٤ 0664	ء 0674
5			إ 0625	ص 0635	م 0645	 0655	٥ 0665	أ 0675
6			ئ 0626	ض 0636	ن 0646	 0656	٦ 0666	ؤ 0676
7			ا 0627	ط 0637	ه 0647	 0657	٧ 0667	ؤ 0677
8			ب 0628	ظ 0638	و 0648	 0658	٨ 0668	ئ 0678
9			ة 0629	ع 0639	ي 0649	 0659	٩ 0669	ط 0679
A			ت 062A	غ 063A	ي 064A		٪ 066A	ث 067A
B		؛ 061B	ث 062B		 064B		ر 066B	ب 067B
C	، 060C		ج 062C		 064C		، 066C	ت 067C
D	 060D		ح 062D		 064D		★ 066D	ت 067D
E	 060E		خ 062E		 064E		ل 066E	پ 067E
F	 060F	؟ 061F	د 062F		 064F		و 066F	ث 067F

G = 00
P = 00

Table 16 - Row 06: Arabic

HEX	NAME	HEX	NAME
0600	ARABIC NUMBER SIGN	065D	(This position shall not be used)
0601	ARABIC SIGN SANAH	065E	(This position shall not be used)
0602	ARABIC FOOTNOTE MARKER	065F	(This position shall not be used)
0603	ARABIC SIGN SAFHA	0660	ARABIC-INDIC DIGIT ZERO
0604	(This position shall not be used)	0661	ARABIC-INDIC DIGIT ONE
0605	(This position shall not be used)	0662	ARABIC-INDIC DIGIT TWO
0606	(This position shall not be used)	0663	ARABIC-INDIC DIGIT THREE
0607	(This position shall not be used)	0664	ARABIC-INDIC DIGIT FOUR
0608	(This position shall not be used)	0665	ARABIC-INDIC DIGIT FIVE
0609	(This position shall not be used)	0666	ARABIC-INDIC DIGIT SIX
060A	(This position shall not be used)	0667	ARABIC-INDIC DIGIT SEVEN
060B	(This position shall not be used)	0668	ARABIC-INDIC DIGIT EIGHT
060C	ARABIC COMMA	0669	ARABIC-INDIC DIGIT NINE
060D	ARABIC DATE SEPARATOR	066A	ARABIC PERCENT SIGN
060E	ARABIC POETIC VERSE SIGN	066B	ARABIC DECIMAL SEPARATOR
060F	ARABIC SIGN MISRA	066C	ARABIC THOUSANDS SEPARATOR
0610	ARABIC SIGN SALLALLAHOU ALAYHE WASSALLAM	066D	ARABIC FIVE POINTED STAR
0611	ARABIC SIGN ALAYHE ASSALLAM	066E	ARABIC LETTER DOTLESS BEH
0612	ARABIC SIGN RAMATULLAH ALAYHE	066F	ARABIC LETTER DOTLESS QAF
0613	ARABIC SIGN RADI ALLAHOU ANHU	0670	ARABIC LETTER SUPERScript ALEF
0614	ARABIC SIGN TAKHALLUS	0671	ARABIC LETTER ALEF WASLA
0615	(This position shall not be used)	0672	ARABIC LETTER ALEF WITH WAVY HAMZA ABOVE
0616	(This position shall not be used)	0673	ARABIC LETTER ALEF WITH WAVY HAMZA BELOW
0617	(This position shall not be used)	0674	ARABIC LETTER HIGH HAMZA
0618	(This position shall not be used)	0675	ARABIC LETTER HIGH HAMZA ALEF
0619	(This position shall not be used)	0676	ARABIC LETTER HIGH HAMZA WAW
061A	(This position shall not be used)	0677	ARABIC LETTER U WITH HAMZA ABOVE
061B	ARABIC SEMICOLON	0678	ARABIC LETTER HIGH HAMZA YEH
061C	(This position shall not be used)	0679	ARABIC LETTER TTEH
061D	(This position shall not be used)	067A	ARABIC LETTER TTEHEH
061E	(This position shall not be used)	067B	ARABIC LETTER BEEH
061F	ARABIC QUESTION MARK	067C	ARABIC LETTER TEH WITH RING
0620	(This position shall not be used)	067D	ARABIC LETTER TEH WITH THREE DOTS ABOVE DOWNWARDS
0621	ARABIC LETTER HAMZA	067E	ARABIC LETTER PEH
0622	ARABIC LETTER ALEF WITH MADD A ABOVE	067F	ARABIC LETTER TEHEH
0623	ARABIC LETTER ALEF WITH HAMZA ABOVE		
0624	ARABIC LETTER WAW WITH HAMZA ABOVE		
0625	ARABIC LETTER ALEF WITH HAMZA BELOW		
0626	ARABIC LETTER YEH WITH HAMZA ABOVE		
0627	ARABIC LETTER ALEF		
0628	ARABIC LETTER BEH		
0629	ARABIC LETTER TEH MARBUTA		
062A	ARABIC LETTER TEH		
062B	ARABIC LETTER THEH		
062C	ARABIC LETTER JEEM		
062D	ARABIC LETTER HAH		
062E	ARABIC LETTER KHAH		
062F	ARABIC LETTER DAL		
0630	ARABIC LETTER THAL		
0631	ARABIC LETTER REH		
0632	ARABIC LETTER ZAIN		
0633	ARABIC LETTER SEEN		
0634	ARABIC LETTER SHEEN		
0635	ARABIC LETTER SAD		
0636	ARABIC LETTER DAD		
0637	ARABIC LETTER TAH		
0638	ARABIC LETTER ZAH		
0639	ARABIC LETTER AIN		
063A	ARABIC LETTER GHAIN		
063B	(This position shall not be used)		
063C	(This position shall not be used)		
063D	(This position shall not be used)		
063E	(This position shall not be used)		
063F	(This position shall not be used)		
0640	ARABIC TATWEEL		
0641	ARABIC LETTER FEH		
0642	ARABIC LETTER QAF		
0643	ARABIC LETTER KAF		
0644	ARABIC LETTER LAM		
0645	ARABIC LETTER MEEM		
0646	ARABIC LETTER NOON		
0647	ARABIC LETTER HEH		
0648	ARABIC LETTER WAW		
0649	ARABIC LETTER ALEF MAKSURA		
064A	ARABIC LETTER YEH		
064B	ARABIC FATHATAN		
064C	ARABIC DAMMATAN		
064D	ARABIC KASRATAN		
064E	ARABIC FATHA		
064F	ARABIC DAMMA		
0650	ARABIC KASRA		
0651	ARABIC SHADDA		
0652	ARABIC SUKUN		
0653	ARABIC MADD A ABOVE		
0654	ARABIC HAMZA ABOVE		
0655	ARABIC HAMZA BELOW		
0656	ARABIC SUBSCRIPT ALEF		
0657	ARABIC INVERTED DAMMA		
0658	ARABIC NOON-GHUNNA		
0659	ARABIC SMALL HIGH TAH		
065A	(This position shall not be used)		
065B	(This position shall not be used)		
065C	(This position shall not be used)		

Group 00

Plane 00

Row 06

Table 17 - Row 06: Arabic

















































































	068	069	06A	06B	06C	06D	06E	06F
0	پ 0680	ڈ 0690	غ 06A0	گ 06B0	ه 06C0	ې 06D0	◌ 06E0	◌ 06F0
1	خ 0681	ڑ 0691	ف 06A1	گ 06B1	ه 06C1	پ 06D1	◌ 06E1	ا 06F1
2	خ 0682	ز 0692	ب 06A2	گ 06B2	ء 06C2	ے 06D2	◌ 06E2	ب 06F2
3	ج 0683	ر 0693	ب 06A3	گ 06B3	ت 06C3	ے 06D3	◌ 06E3	ب 06F3
4	ج 0684	ر 0694	قا 06A4	گ 06B4	و 06C4	- 06D4	◌ 06E4	ب 06F4
5	خ 0685	ر 0695	پ 06A5	ل 06B5	و 06C5	ه 06D5	ر 06E5	ب 06F5
6	ج 0686	ر 0696	قا 06A6	ل 06B6	و 06C6	◌ 06D6	ے 06E6	ب 06F6
7	ج 0687	ز 0697	ف 06A7	ث 06B7	و 06C7	◌ 06D7	ے 06E7	ب 06F7
8	ڈ 0688	ڑ 0698	قا 06A8	پ 06B8	و 06C8	◌ 06D8	◌ 06E8	ب 06F8
9	د 0689	ڑ 0699	ک 06A9	ب 06B9	و 06C9	◌ 06D9	◌ 06E9	ب 06F9
A	ب 068A	ب 069A	ک 06AA	ن 06BA	ق 06CA	◌ 06DA	◌ 06EA	ب 06FA
B	ب 068B	ب 069B	ک 06AB	ن 06BB	ق 06CB	◌ 06DB	◌ 06EB	ب 06FB
C	ت 068C	ب 069C	ک 06AC	ب 06BC	ی 06CC	◌ 06DC	◌ 06EC	ب 06FC
D	د 068D	ب 069D	ک 06AD	ن 06BD	ی 06CD	◌ 06DD	◌ 06ED	ب 06FD
E	ڈ 068E	ض 069E	پ 06AE	ه 06BE	ی 06CE	◌ 06DE	د 06EE	ب 06FE
F	ڈ 068F	ظ 069F	گ 06AF	ب 06BF	ف 06CF	◌ 06DF	ر 06EF	ب 06FF

G = 00
P = 00

Table 17 - Row 06: Arabic

HEX	NAME	HEX	NAME
0680	ARABIC LETTER BEHEH	06DD	ARABIC END OF AYAH
0681	ARABIC LETTER HAH WITH HAMZA ABOVE	06DE	ARABIC START OF RUB EL HIZB
0682	ARABIC LETTER HAH WITH TWO DOTS VERTICAL ABOVE	06DF	ARABIC SMALL HIGH ROUNDED ZERO
0683	ARABIC LETTER NYEH	06E0	ARABIC SMALL HIGH UPRIGHT RECTANGULAR ZERO
0684	ARABIC LETTER DYEH	06E1	ARABIC SMALL HIGH DOTLESS HEAD OF KHAH
0685	ARABIC LETTER HAH WITH THREE DOTS ABOVE	06E2	ARABIC SMALL HIGH MEEM ISOLATED FORM
0686	ARABIC LETTER TCHEH	06E3	ARABIC SMALL LOW SEEN
0687	ARABIC LETTER TCHEHEH	06E4	ARABIC SMALL HIGH MADDA
0688	ARABIC LETTER DDAL	06E5	ARABIC SMALL WAW
0689	ARABIC LETTER DAL WITH RING	06E6	ARABIC SMALL YEH
068A	ARABIC LETTER DAL WITH DOT BELOW	06E7	ARABIC SMALL HIGH YEH
068B	ARABIC LETTER DAL WITH DOT BELOW AND SMALL TAH	06E8	ARABIC SMALL HIGH NOON
068C	ARABIC LETTER DAHAL	06E9	ARABIC PLACE OF SAJDAH
068D	ARABIC LETTER DDAHAL	06EA	ARABIC EMPTY CENTRE LOW STOP
068E	ARABIC LETTER DUL	06EB	ARABIC EMPTY CENTRE HIGH STOP
068F	ARABIC LETTER DAL WITH THREE DOTS ABOVE DOWNWARDS	06EC	ARABIC ROUNDED HIGH STOP WITH FILLED CENTRE
0690	ARABIC LETTER DAL WITH FOUR DOTS ABOVE	06ED	ARABIC SMALL LOW MEEM
0691	ARABIC LETTER RREH	06EE	ARABIC LETTER DAL WITH INVERTED V
0692	ARABIC LETTER REH WITH SMALL V	06EF	ARABIC LETTER REH WITH INVERTED V
0693	ARABIC LETTER REH WITH RING	06F0	EXTENDED ARABIC-INDIC DIGIT ZERO
0694	ARABIC LETTER REH WITH DOT BELOW	06F1	EXTENDED ARABIC-INDIC DIGIT ONE
0695	ARABIC LETTER REH WITH SMALL V BELOW	06F2	EXTENDED ARABIC-INDIC DIGIT TWO
0696	ARABIC LETTER REH WITH DOT BELOW AND DOT ABOVE	06F3	EXTENDED ARABIC-INDIC DIGIT THREE
0697	ARABIC LETTER REH WITH TWO DOTS ABOVE	06F4	EXTENDED ARABIC-INDIC DIGIT FOUR
0698	ARABIC LETTER JEH	06F5	EXTENDED ARABIC-INDIC DIGIT FIVE
0699	ARABIC LETTER REH WITH FOUR DOTS ABOVE	06F6	EXTENDED ARABIC-INDIC DIGIT SIX
069A	ARABIC LETTER SEEN WITH DOT BELOW AND DOT ABOVE	06F7	EXTENDED ARABIC-INDIC DIGIT SEVEN
069B	ARABIC LETTER SEEN WITH THREE DOTS BELOW	06F8	EXTENDED ARABIC-INDIC DIGIT EIGHT
069C	ARABIC LETTER SEEN WITH THREE DOTS BELOW AND THREE DOTS ABOVE	06F9	EXTENDED ARABIC-INDIC DIGIT NINE
069D	ARABIC LETTER SAD WITH TWO DOTS BELOW	06FA	ARABIC LETTER SHEEN WITH DOT BELOW
069E	ARABIC LETTER SAD WITH THREE DOTS ABOVE	06FB	ARABIC LETTER DAD WITH DOT BELOW
069F	ARABIC LETTER TAH WITH THREE DOTS ABOVE	06FC	ARABIC LETTER GHAIN WITH DOT BELOW
06A0	ARABIC LETTER AIN WITH THREE DOTS ABOVE	06FD	ARABIC SIGN SINDHI AMPERSAND
06A1	ARABIC LETTER DOTLESS FEH	06FE	ARABIC SIGN SINDHI POSTPOSITION MEN
06A2	ARABIC LETTER FEH WITH DOT MOVED BELOW	06FF	ARABIC LETTER HEH WITH INVERTED V
06A3	ARABIC LETTER FEH WITH DOT BELOW		
06A4	ARABIC LETTER VEH		
06A5	ARABIC LETTER FEH WITH THREE DOTS BELOW		
06A6	ARABIC LETTER PEHEH		
06A7	ARABIC LETTER QAF WITH DOT ABOVE		
06A8	ARABIC LETTER QAF WITH THREE DOTS ABOVE		
06A9	ARABIC LETTER KEHEH		
06AA	ARABIC LETTER SWASH KAF		
06AB	ARABIC LETTER KAF WITH RING		
06AC	ARABIC LETTER KAF WITH DOT ABOVE		
06AD	ARABIC LETTER NG		
06AE	ARABIC LETTER KAF WITH THREE DOTS BELOW		
06AF	ARABIC LETTER GAF *		
06B0	ARABIC LETTER GAF WITH RING		
06B1	ARABIC LETTER NGOEH		
06B2	ARABIC LETTER GAF WITH TWO DOTS BELOW		
06B3	ARABIC LETTER GUEH		
06B4	ARABIC LETTER GAF WITH THREE DOTS ABOVE		
06B5	ARABIC LETTER LAM WITH SMALL V		
06B6	ARABIC LETTER LAM WITH DOT ABOVE		
06B7	ARABIC LETTER LAM WITH THREE DOTS ABOVE		
06B8	ARABIC LETTER LAM WITH THREE DOTS BELOW		
06B9	ARABIC LETTER NOON WITH DOT BELOW		
06BA	ARABIC LETTER NOON GHUNNA		
06BB	ARABIC LETTER RNOON		
06BC	ARABIC LETTER NOON WITH RING		
06BD	ARABIC LETTER NOON WITH THREE DOTS ABOVE		
06BE	ARABIC LETTER HEH DOACHASHMEE		
06BF	ARABIC LETTER TCHEH WITH DOT ABOVE		
06C0	ARABIC LETTER HEH WITH YEH ABOVE		
06C1	ARABIC LETTER HEH GOAL		
06C2	ARABIC LETTER HEH GOAL WITH HAMZA ABOVE		
06C3	ARABIC LETTER TEH MARBUTA GOAL		
06C4	ARABIC LETTER WAW WITH RING		
06C5	ARABIC LETTER KIRGHIZ OE		
06C6	ARABIC LETTER OE		
06C7	ARABIC LETTER U		
06C8	ARABIC LETTER YU		
06C9	ARABIC LETTER KIRGHIZ YU		
06CA	ARABIC LETTER WAW WITH TWO DOTS ABOVE		
06CB	ARABIC LETTER VE		
06CC	ARABIC LETTER FARSI YEH		
06CD	ARABIC LETTER YEH WITH TAIL		
06CE	ARABIC LETTER YEH WITH SMALL V		
06CF	ARABIC LETTER WAW WITH DOT ABOVE		
06D0	ARABIC LETTER E *		
06D1	ARABIC LETTER YEH WITH THREE DOTS BELOW		
06D2	ARABIC LETTER YEH BARREE		
06D3	ARABIC LETTER YEH BARREE WITH HAMZA ABOVE		
06D4	ARABIC FULL STOP		
06D5	ARABIC LETTER AE		
06D6	ARABIC SMALL HIGH LIGATURE SAD WITH LAM WITH ALEF MAKSURA		
06D7	ARABIC SMALL HIGH LIGATURE QAF WITH LAM WITH ALEF MAKSURA		
06D8	ARABIC SMALL HIGH MEEM INITIAL FORM		
06D9	ARABIC SMALL HIGH LAM ALEF		
06DA	ARABIC SMALL HIGH JEEM		
06DB	ARABIC SMALL HIGH THREE DOTS		
06DC	ARABIC SMALL HIGH SEEN		

Table 18 - Row 07: Syriac

	070	071	072	073	074
0	 0700	 0710	 0720	 0730	 0740
1	 0701	 0711	 0721	 0731	 0741
2	 0702	 0712	 0722	 0732	 0742
3	 0703	 0713	 0723	 0733	 0743
4	 0704	 0714	 0724	 0734	 0744
5	 0705	 0715	 0725	 0735	 0745
6	 0706	 0716	 0726	 0736	 0746
7	 0707	 0717	 0727	 0737	 0747
8	 0708	 0718	 0728	 0738	 0748
9	 0709	 0719	 0729	 0739	 0749
A	 070A	 071A	 072A	 073A	 074A
B	 070B	 071B	 072B	 073B	
C	 070C	 071C	 072C	 073C	
D	 070D	 071D	 072D	 073D	 074D
E		 071E	 072E	 073E	 074E
F	 070F	 071F	 072F	 073F	 074F

G = 00
P = 00

Table 18 - Row 07: Syriac

HEX	NAME	HEX	NAME
0700	SYRIAC END OF PARAGRAPH		
0701	SYRIAC SUPRALINEAR FULL STOP		
0702	SYRIAC SUBLINEAR FULL STOP		
0703	SYRIAC SUPRALINEAR COLON		
0704	SYRIAC SUBLINEAR COLON		
0705	SYRIAC HORIZONTAL COLON		
0706	SYRIAC COLON SKEWED LEFT		
0707	SYRIAC COLON SKEWED RIGHT		
0708	SYRIAC SUPRALINEAR COLON SKEWED LEFT		
0709	SYRIAC SUBLINEAR COLON SKEWED RIGHT		
070A	SYRIAC CONTRACTION		
070B	SYRIAC HARKLEAN OBELUS		
070C	SYRIAC HARKLEAN METOBELUS		
070D	SYRIAC HARKLEAN ASTERISCUS		
070E	(This position shall not be used)		
070F	SYRIAC ABBREVIATION MARK		
0710	SYRIAC LETTER ALAPH		
0711	SYRIAC LETTER SUPERSCRIPIT ALAPH		
0712	SYRIAC LETTER BETH		
0713	SYRIAC LETTER GAMAL		
0714	SYRIAC LETTER GAMAL GARSHUNI		
0715	SYRIAC LETTER DALATH		
0716	SYRIAC LETTER DOTLESS DALATH RISH		
0717	SYRIAC LETTER HE		
0718	SYRIAC LETTER WAW		
0719	SYRIAC LETTER ZAIN		
071A	SYRIAC LETTER HETH		
071B	SYRIAC LETTER TETH		
071C	SYRIAC LETTER TETH GARSHUNI		
071D	SYRIAC LETTER YUDH		
071E	SYRIAC LETTER YUDH HE		
071F	SYRIAC LETTER KAPH		
0720	SYRIAC LETTER LAMADH		
0721	SYRIAC LETTER MIM		
0722	SYRIAC LETTER NUN		
0723	SYRIAC LETTER SEMKATH		
0724	SYRIAC LETTER FINAL SEMKATH		
0725	SYRIAC LETTER E		
0726	SYRIAC LETTER PE		
0727	SYRIAC LETTER REVERSED PE		
0728	SYRIAC LETTER SADHE		
0729	SYRIAC LETTER QAPH		
072A	SYRIAC LETTER RISH		
072B	SYRIAC LETTER SHIN		
072C	SYRIAC LETTER TAW		
072D	SYRIAC LETTER PERSIAN BHETH		
072E	SYRIAC LETTER PERSIAN GHAMAL		
072F	SYRIAC LETTER PERSIAN DHALATH		
0730	SYRIAC PTHAHA ABOVE		
0731	SYRIAC PTHAHA BELOW		
0732	SYRIAC PTHAHA DOTTED		
0733	SYRIAC ZQAPHA ABOVE		
0734	SYRIAC ZQAPHA BELOW		
0735	SYRIAC ZQAPHA DOTTED		
0736	SYRIAC RBASA ABOVE		
0737	SYRIAC RBASA BELOW		
0738	SYRIAC DOTTED ZLAMA HORIZONTAL		
0739	SYRIAC DOTTED ZLAMA ANGULAR		
073A	SYRIAC HBASA ABOVE		
073B	SYRIAC HBASA BELOW		
073C	SYRIAC HBASA-ESASA DOTTED		
073D	SYRIAC ESASA ABOVE		
073E	SYRIAC ESASA BELOW		
073F	SYRIAC RWAHA		
0740	SYRIAC FEMININE DOT		
0741	SYRIAC QUSHSHAYA		
0742	SYRIAC RUKKAKHA		
0743	SYRIAC TWO VERTICAL DOTS ABOVE		
0744	SYRIAC TWO VERTICAL DOTS BELOW		
0745	SYRIAC THREE DOTS ABOVE		
0746	SYRIAC THREE DOTS BELOW		
0747	SYRIAC OBLIQUE LINE ABOVE		
0748	SYRIAC OBLIQUE LINE BELOW		
0749	SYRIAC MUSIC		
074A	SYRIAC BARREKH		
074B	(This position shall not be used)		
074C	(This position shall not be used)		
074D	SYRIAC LETTER SOGDIAN ZHAIN		
074E	SYRIAC LETTER SOGDIAN KHAPH		
074F	SYRIAC LETTER SOGDIAN FE		

Group 00

Plane 00

Row 07

Table 20 - Row 09: Devanagari

	090	091	092	093	094	095	096	097
0		ऐ 0910	ठ 0920	र 0930	ी 0940	ॐ 0950	ऋ 0960	० 0970
1	ँ 0901	ऑ 0911	ड 0921	ऱ 0931	ु 0941	ं 0951	्लृ 0961	
2	ं 0902	ओ 0912	ढ 0922	ल 0932	ॠ 0942	ॡ 0952	ॢ 0962	
3	ः 0903	ओ 0913	ण 0923	ळ 0933	ॠ 0943	े 0953	ॢ 0963	
4	ऐ 0904	औ 0914	त 0924	ळ 0934	ॠ 0944	े 0954	। 0964	
5	अ 0905	क 0915	थ 0925	व 0935	ँ 0945		॥ 0965	
6	आ 0906	ख 0916	द 0926	श 0936	े 0946		० 0966	
7	इ 0907	ग 0917	ध 0927	ष 0937	े 0947		१ 0967	
8	ई 0908	घ 0918	न 0928	स 0938	ै 0948	ऋ 0958	२ 0968	
9	उ 0909	ङ 0919	न 0929	ह 0939	ँ 0949	ख 0959	३ 0969	
A	ऊ 090A	च 091A	प 092A		ो 094A	ग 095A	४ 096A	
B	ऋ 090B	छ 091B	फ 092B		ो 094B	ज 095B	५ 096B	
C	्लृ 090C	ज 091C	ब 092C	ं 093C	ौ 094C	ड 095C	६ 096C	
D	ँ 090D	झ 091D	भ 092D	ऽ 093D	्र 094D	ढ 095D	७ 096D	
E	ऐ 090E	ञ 091E	म 092E	ा 093E		फ़ 095E	८ 096E	
F	ए 090F	ट 091F	य 092F	ि 093F		य़ 095F	९ 096F	

G = 00
P = 00

Table 20 - Row 09: Devanagari

HEX	NAME	HEX	NAME
0900	(This position shall not be used)	095D	DEVANAGARI LETTER RHA
0901	DEVANAGARI SIGN CANDRABINDU	095E	DEVANAGARI LETTER FA
0902	DEVANAGARI SIGN ANUSVARA	095F	DEVANAGARI LETTER YYA
0903	DEVANAGARI SIGN VISARGA	0960	DEVANAGARI LETTER VOCALIC RR
0904	DEVANAGARI SHORT LETTER A	0961	DEVANAGARI LETTER VOCALIC LL
0905	DEVANAGARI LETTER A	0962	DEVANAGARI VOWEL SIGN VOCALIC L
0906	DEVANAGARI LETTER AA	0963	DEVANAGARI VOWEL SIGN VOCALIC LL
0907	DEVANAGARI LETTER I	0964	DEVANAGARI DANDA
0908	DEVANAGARI LETTER II	0965	DEVANAGARI DOUBLE DANDA
0909	DEVANAGARI LETTER U	0966	DEVANAGARI DIGIT ZERO
090A	DEVANAGARI LETTER UU	0967	DEVANAGARI DIGIT ONE
090B	DEVANAGARI LETTER VOCALIC R	0968	DEVANAGARI DIGIT TWO
090C	DEVANAGARI LETTER VOCALIC L	0969	DEVANAGARI DIGIT THREE
090D	DEVANAGARI LETTER CANDRA E	096A	DEVANAGARI DIGIT FOUR
090E	DEVANAGARI LETTER SHORT E	096B	DEVANAGARI DIGIT FIVE
090F	DEVANAGARI LETTER E	096C	DEVANAGARI DIGIT SIX
0910	DEVANAGARI LETTER AI	096D	DEVANAGARI DIGIT SEVEN
0911	DEVANAGARI LETTER CANDRA O	096E	DEVANAGARI DIGIT EIGHT
0912	DEVANAGARI LETTER SHORT O	096F	DEVANAGARI DIGIT NINE
0913	DEVANAGARI LETTER O	0970	DEVANAGARI ABBREVIATION SIGN
0914	DEVANAGARI LETTER AU	0971	(This position shall not be used)
0915	DEVANAGARI LETTER KA	0972	(This position shall not be used)
0916	DEVANAGARI LETTER KHA	0973	(This position shall not be used)
0917	DEVANAGARI LETTER GA	0974	(This position shall not be used)
0918	DEVANAGARI LETTER GHA	0975	(This position shall not be used)
0919	DEVANAGARI LETTER NGA	0976	(This position shall not be used)
091A	DEVANAGARI LETTER CA	0977	(This position shall not be used)
091B	DEVANAGARI LETTER CHA	0978	(This position shall not be used)
091C	DEVANAGARI LETTER JA	0979	(This position shall not be used)
091D	DEVANAGARI LETTER JHA	097A	(This position shall not be used)
091E	DEVANAGARI LETTER NYA	097B	(This position shall not be used)
091F	DEVANAGARI LETTER TTA	097C	(This position shall not be used)
0920	DEVANAGARI LETTER TTHA	097D	(This position shall not be used)
0921	DEVANAGARI LETTER DDA	097E	(This position shall not be used)
0922	DEVANAGARI LETTER DDHA	097F	(This position shall not be used)
0923	DEVANAGARI LETTER NNA		
0924	DEVANAGARI LETTER TA		
0925	DEVANAGARI LETTER THA		
0926	DEVANAGARI LETTER DA		
0927	DEVANAGARI LETTER DHA		
0928	DEVANAGARI LETTER NA		
0929	DEVANAGARI LETTER NNA		
092A	DEVANAGARI LETTER PA		
092B	DEVANAGARI LETTER PHA		
092C	DEVANAGARI LETTER BA		
092D	DEVANAGARI LETTER BHA		
092E	DEVANAGARI LETTER MA		
092F	DEVANAGARI LETTER YA		
0930	DEVANAGARI LETTER RA		
0931	DEVANAGARI LETTER RRA		
0932	DEVANAGARI LETTER LA		
0933	DEVANAGARI LETTER LLA		
0934	DEVANAGARI LETTER LLLA		
0935	DEVANAGARI LETTER VA		
0936	DEVANAGARI LETTER SHA		
0937	DEVANAGARI LETTER SSA		
0938	DEVANAGARI LETTER SA		
0939	DEVANAGARI LETTER HA		
093A	(This position shall not be used)		
093B	(This position shall not be used)		
093C	DEVANAGARI SIGN NUKTA		
093D	DEVANAGARI SIGN AVAGRAHA		
093E	DEVANAGARI VOWEL SIGN AA		
093F	DEVANAGARI VOWEL SIGN I		
0940	DEVANAGARI VOWEL SIGN II		
0941	DEVANAGARI VOWEL SIGN U		
0942	DEVANAGARI VOWEL SIGN UU		
0943	DEVANAGARI VOWEL SIGN VOCALIC R		
0944	DEVANAGARI VOWEL SIGN VOCALIC RR		
0945	DEVANAGARI VOWEL SIGN CANDRA E		
0946	DEVANAGARI VOWEL SIGN SHORT E		
0947	DEVANAGARI VOWEL SIGN E		
0948	DEVANAGARI VOWEL SIGN AI		
0949	DEVANAGARI VOWEL SIGN CANDRA O		
094A	DEVANAGARI VOWEL SIGN SHORT O		
094B	DEVANAGARI VOWEL SIGN O		
094C	DEVANAGARI VOWEL SIGN AU		
094D	DEVANAGARI SIGN VIRAMA		
094E	(This position shall not be used)		
094F	(This position shall not be used)		
0950	DEVANAGARI OM		
0951	DEVANAGARI STRESS SIGN UDATTA		
0952	DEVANAGARI STRESS SIGN ANUDATTA		
0953	DEVANAGARI GRAVE ACCENT		
0954	DEVANAGARI ACUTE ACCENT		
0955	(This position shall not be used)		
0956	(This position shall not be used)		
0957	(This position shall not be used)		
0958	DEVANAGARI LETTER QA		
0959	DEVANAGARI LETTER KHIHA		
095A	DEVANAGARI LETTER GHHA		
095B	DEVANAGARI LETTER ZA		
095C	DEVANAGARI LETTER DDHA		

Group 00

Plane 00

Row 09

Table 21 - Row 09: Bengali

	098	099	09A	09B	09C	09D	09E	09F
0		ঐ 0990	ঊ 09A0	ঋ 09B0	ঌ 09C0		঍ 09E0	঎ 09F0
1	ঁ 0981		ড 09A1		ঢ় 09C1		ঢ় 09E1	ঢ় 09F1
2	ৎ 0982		ঢ 09A2	ণ 09B2	ণ 09C2		ৎ 09E2	ৎ 09F2
3	ঃ 0983	ঙ 0993	ণ 09A3		ং 09C3		ং 09E3	ঙ 09F3
4		ঞ্জ 0994	ত 09A4		ৎ 09C4			ৎ 09F4
5	অ 0985	ক 0995	খ 09A5					খ 09F5
6	ত্রা 0986	থ 0996	দ 09A6	শ 09B6			০ 09E6	থ 09F6
7	ঠ 0987	গ 0997	ঘ 09A7	ষ 09B7	়ে 09C7	়া 09D7	৷ 09E7	। 09F7
8	ক্ষ 0988	য 0998	ম 09A8	স 09B8	়ৈ 09C8		৲ 09E8	৳ 09F8
9	ড় 0989	ঙ 0999		ণ 09B9			৳ 09E9	৳ 09F9
A	ঢ় 098A	চ 099A	প 09AA				৳ 09EA	৳ 09FA
B	ক্ষ 098B	ছ 099B	ফ 09AB		়ৌ 09CB		৳ 09EB	
C	৳ 098C	জ 099C	ব 09AC	় 09BC	়ৌ 09CC	ড় 09DC	ড় 09EC	
D		ঝ 099D	ভ 09AD	় 09BD	় 09CD	ঢ 09DD	ঢ 09ED	
E		ঞ 099E	ম 09AE	়া 09BE			ঢ 09EE	
F	এ 098F	ট 099F	ষ 09AF	়ি 09BF		য় 09DF	য় 09EF	

G = 00
P = 00

Table 21 - Row 09: Bengali

HEX	NAME	HEX	NAME
0980	(This position shall not be used)	09DD	BENGALI LETTER RHA
0981	BENGALI SIGN CANDRABINDU	09DE	(This position shall not be used)
0982	BENGALI SIGN ANUSVARA	09DF	BENGALI LETTER YYA
0983	BENGALI SIGN VISARGA	09E0	BENGALI LETTER VOCALIC RR
0984	(This position shall not be used)	09E1	BENGALI LETTER VOCALIC LL
0985	BENGALI LETTER A	09E2	BENGALI VOWEL SIGN VOCALIC L
0986	BENGALI LETTER AA	09E3	BENGALI VOWEL SIGN VOCALIC LL
0987	BENGALI LETTER I	09E4	(This position shall not be used)
0988	BENGALI LETTER II	09E5	(This position shall not be used)
0989	BENGALI LETTER U	09E6	BENGALI DIGIT ZERO
098A	BENGALI LETTER UU	09E7	BENGALI DIGIT ONE
098B	BENGALI LETTER VOCALIC R	09E8	BENGALI DIGIT TWO
098C	BENGALI LETTER VOCALIC L	09E9	BENGALI DIGIT THREE
098D	(This position shall not be used)	09EA	BENGALI DIGIT FOUR
098E	(This position shall not be used)	09EB	BENGALI DIGIT FIVE
098F	BENGALI LETTER E	09EC	BENGALI DIGIT SIX
0990	BENGALI LETTER AI	09ED	BENGALI DIGIT SEVEN
0991	(This position shall not be used)	09EE	BENGALI DIGIT EIGHT
0992	(This position shall not be used)	09EF	BENGALI DIGIT NINE
0993	BENGALI LETTER O	09F0	BENGALI LETTER RA WITH MIDDLE DIAGONAL (Assamese)
0994	BENGALI LETTER AU	09F1	BENGALI LETTER RA WITH LOWER DIAGONAL (Assamese)
0995	BENGALI LETTER KA	09F2	BENGALI RUPEE MARK
0996	BENGALI LETTER KHA	09F3	BENGALI RUPEE SIGN
0997	BENGALI LETTER GA	09F4	BENGALI CURRENCY NUMERATOR ONE
0998	BENGALI LETTER GHA	09F5	BENGALI CURRENCY NUMERATOR TWO
0999	BENGALI LETTER NGA	09F6	BENGALI CURRENCY NUMERATOR THREE
099A	BENGALI LETTER CA	09F7	BENGALI CURRENCY NUMERATOR FOUR
099B	BENGALI LETTER CHA	09F8	BENGALI CURRENCY NUMERATOR ONE LESS THAN THE DENOMINATOR
099C	BENGALI LETTER JA	09F9	BENGALI CURRENCY DENOMINATOR SIXTEEN
099D	BENGALI LETTER JHA	09FA	BENGALI ISSHAR
099E	BENGALI LETTER NYA	09FB	(This position shall not be used)
099F	BENGALI LETTER TTA	09FC	(This position shall not be used)
09A0	BENGALI LETTER TTHA	09FD	(This position shall not be used)
09A1	BENGALI LETTER DDA	09FE	(This position shall not be used)
09A2	BENGALI LETTER DDHA	09FF	(This position shall not be used)
09A3	BENGALI LETTER NNA		
09A4	BENGALI LETTER TA		
09A5	BENGALI LETTER THA		
09A6	BENGALI LETTER DA		
09A7	BENGALI LETTER DHA		
09A8	BENGALI LETTER NA		
09A9	(This position shall not be used)		
09AA	BENGALI LETTER PA		
09AB	BENGALI LETTER PHA		
09AC	BENGALI LETTER BA		
09AD	BENGALI LETTER BHA		
09AE	BENGALI LETTER MA		
09AF	BENGALI LETTER YA		
09B0	BENGALI LETTER RA		
09B1	(This position shall not be used)		
09B2	BENGALI LETTER LA		
09B3	(This position shall not be used)		
09B4	(This position shall not be used)		
09B5	(This position shall not be used)		
09B6	BENGALI LETTER SHA		
09B7	BENGALI LETTER SSA		
09B8	BENGALI LETTER SA		
09B9	BENGALI LETTER HA		
09BA	(This position shall not be used)		
09BB	(This position shall not be used)		
09BC	BENGALI SIGN NUKTA		
09BD	BENGALI SIGN AVAGRAHA		
09BE	BENGALI VOWEL SIGN AA		
09BF	BENGALI VOWEL SIGN I		
09C0	BENGALI VOWEL SIGN II		
09C1	BENGALI VOWEL SIGN U		
09C2	BENGALI VOWEL SIGN UU		
09C3	BENGALI VOWEL SIGN VOCALIC R		
09C4	BENGALI VOWEL SIGN VOCALIC RR		
09C5	(This position shall not be used)		
09C6	(This position shall not be used)		
09C7	BENGALI VOWEL SIGN E		
09C8	BENGALI VOWEL SIGN AI		
09C9	(This position shall not be used)		
09CA	(This position shall not be used)		
09CB	BENGALI VOWEL SIGN O		
09CC	BENGALI VOWEL SIGN AU		
09CD	BENGALI SIGN VIRAMA		
09CE	(This position shall not be used)		
09CF	(This position shall not be used)		
09D0	(This position shall not be used)		
09D1	(This position shall not be used)		
09D2	(This position shall not be used)		
09D3	(This position shall not be used)		
09D4	(This position shall not be used)		
09D5	(This position shall not be used)		
09D6	(This position shall not be used)		
09D7	BENGALI AU LENGTH MARK		
09D8	(This position shall not be used)		
09D9	(This position shall not be used)		
09DA	(This position shall not be used)		
09DB	(This position shall not be used)		
09DC	BENGALI LETTER RRA		

Group 00

Plane 00

Row 09

Table 22 - Row 0A: Gurmukhi

	0A0	0A1	0A2	0A3	0A4	0A5	0A6	0A7
0		ਐ 0A10	ਠ 0A20	ਰ 0A30	ੀ 0A40			ੰ 0A70
1	ੰ 0A01		ਡ 0A21		ੁ 0A41			ੱ 0A71
2	ਂ 0A02		ਢ 0A22	ਲ 0A32	ੁ 0A42			ੲ 0A72
3	ੰ 0A03	ਓ 0A13	ਲ 0A23	ਲ 0A33				ੳ 0A73
4		ਐ 0A14	ਤ 0A24					ੴ 0A74
5	ਅ 0A05	ਕ 0A15	ਥ 0A25	ਵ 0A35				
6	ਆ 0A06	ਖ 0A16	ਦ 0A26	ਸ਼ 0A36			ੌ 0A66	
7	ਇ 0A07	ਗ 0A17	ਧ 0A27		ੇ 0A47		ੴ 0A67	
8	ਈ 0A08	ਘ 0A18	ਨ 0A28	ਸ਼ 0A38	ੈ 0A48		ੴ 0A68	
9	ਉ 0A09	ਙ 0A19		ਹ 0A39		ਖ਼ 0A59	ੴ 0A69	
A	ੳ 0A0A	ਚ 0A1A	ਪ 0A2A			ਗ਼ 0A5A	ੴ 0A6A	
B		ਛ 0A1B	ਫ 0A2B		ੋ 0A4B	ਜ਼ 0A5B	ਪ਼ 0A6B	
C		ਜ 0A1C	ਬ 0A2C	੍ਰ 0A3C	ੌ 0A4C	ਖ਼ 0A5C	ੴ 0A6C	
D		ਝ 0A1D	ਭ 0A2D		੍ਰ 0A4D		ੴ 0A6D	
E		ਞ 0A1E	ਮ 0A2E	ਾ 0A3E		ਫ਼ 0A5E	ੴ 0A6E	
F	ੳ 0A0F	ਟ 0A1F	ਯ 0A2F	ਿ 0A3F			ੴ 0A6F	

G = 00
P = 00

Table 22 - Row 0A: Gurmukhi

HEX	NAME	HEX	NAME
0A00	(This position shall not be used)	0A5D	(This position shall not be used)
0A01	GURMUKHI SIGN ADAK BINDI	0A5E	GURMUKHI LETTER FA
0A02	GURMUKHI SIGN BINDI	0A5F	(This position shall not be used)
0A03	GURMUKHI SIGN VISARGA	0A60	(This position shall not be used)
0A04	(This position shall not be used)	0A61	(This position shall not be used)
0A05	GURMUKHI LETTER A	0A62	(This position shall not be used)
0A06	GURMUKHI LETTER AA	0A63	(This position shall not be used)
0A07	GURMUKHI LETTER I	0A64	(This position shall not be used)
0A08	GURMUKHI LETTER II	0A65	(This position shall not be used)
0A09	GURMUKHI LETTER U	0A66	GURMUKHI DIGIT ZERO
0A0A	GURMUKHI LETTER UU	0A67	GURMUKHI DIGIT ONE
0A0B	(This position shall not be used)	0A68	GURMUKHI DIGIT TWO
0A0C	(This position shall not be used)	0A69	GURMUKHI DIGIT THREE
0A0D	(This position shall not be used)	0A6A	GURMUKHI DIGIT FOUR
0A0E	(This position shall not be used)	0A6B	GURMUKHI DIGIT FIVE
0A0F	GURMUKHI LETTER EE	0A6C	GURMUKHI DIGIT SIX
0A10	GURMUKHI LETTER AI	0A6D	GURMUKHI DIGIT SEVEN
0A11	(This position shall not be used)	0A6E	GURMUKHI DIGIT EIGHT
0A12	(This position shall not be used)	0A6F	GURMUKHI DIGIT NINE
0A13	GURMUKHI LETTER OO	0A70	GURMUKHI TIPPI
0A14	GURMUKHI LETTER AU	0A71	GURMUKHI ADDAK
0A15	GURMUKHI LETTER KA	0A72	GURMUKHI IRI
0A16	GURMUKHI LETTER KHA	0A73	GURMUKHI URA
0A17	GURMUKHI LETTER GA	0A74	GURMUKHI EK ONKAR
0A18	GURMUKHI LETTER GHA	0A75	(This position shall not be used)
0A19	GURMUKHI LETTER NGA	0A76	(This position shall not be used)
0A1A	GURMUKHI LETTER CA	0A77	(This position shall not be used)
0A1B	GURMUKHI LETTER CHA	0A78	(This position shall not be used)
0A1C	GURMUKHI LETTER JA	0A79	(This position shall not be used)
0A1D	GURMUKHI LETTER JHA	0A7A	(This position shall not be used)
0A1E	GURMUKHI LETTER NYA	0A7B	(This position shall not be used)
0A1F	GURMUKHI LETTER TTA	0A7C	(This position shall not be used)
0A20	GURMUKHI LETTER TTHA	0A7D	(This position shall not be used)
0A21	GURMUKHI LETTER DDA	0A7E	(This position shall not be used)
0A22	GURMUKHI LETTER DDHA	0A7F	(This position shall not be used)
0A23	GURMUKHI LETTER NNA		
0A24	GURMUKHI LETTER TA		
0A25	GURMUKHI LETTER THA		
0A26	GURMUKHI LETTER DA		
0A27	GURMUKHI LETTER DHA		
0A28	GURMUKHI LETTER NA		
0A29	(This position shall not be used)		
0A2A	GURMUKHI LETTER PA		
0A2B	GURMUKHI LETTER PHA		
0A2C	GURMUKHI LETTER BA		
0A2D	GURMUKHI LETTER BHA		
0A2E	GURMUKHI LETTER MA		
0A2F	GURMUKHI LETTER YA		
0A30	GURMUKHI LETTER RA		
0A31	(This position shall not be used)		
0A32	GURMUKHI LETTER LA		
0A33	GURMUKHI LETTER LLA		
0A34	(This position shall not be used)		
0A35	GURMUKHI LETTER VA		
0A36	GURMUKHI LETTER SHA		
0A37	(This position shall not be used)		
0A38	GURMUKHI LETTER SA		
0A39	GURMUKHI LETTER HA		
0A3A	(This position shall not be used)		
0A3B	(This position shall not be used)		
0A3C	GURMUKHI SIGN NUKTA		
0A3D	(This position shall not be used)		
0A3E	GURMUKHI VOWEL SIGN AA		
0A3F	GURMUKHI VOWEL SIGN I		
0A40	GURMUKHI VOWEL SIGN II		
0A41	GURMUKHI VOWEL SIGN U		
0A42	GURMUKHI VOWEL SIGN UU		
0A43	(This position shall not be used)		
0A44	(This position shall not be used)		
0A45	(This position shall not be used)		
0A46	(This position shall not be used)		
0A47	GURMUKHI VOWEL SIGN EE		
0A48	GURMUKHI VOWEL SIGN AI		
0A49	(This position shall not be used)		
0A4A	(This position shall not be used)		
0A4B	GURMUKHI VOWEL SIGN OO		
0A4C	GURMUKHI VOWEL SIGN AU		
0A4D	GURMUKHI SIGN VIRAMA		
0A4E	(This position shall not be used)		
0A4F	(This position shall not be used)		
0A50	(This position shall not be used)		
0A51	(This position shall not be used)		
0A52	(This position shall not be used)		
0A53	(This position shall not be used)		
0A54	(This position shall not be used)		
0A55	(This position shall not be used)		
0A56	(This position shall not be used)		
0A57	(This position shall not be used)		
0A58	(This position shall not be used)		
0A59	GURMUKHI LETTER KHHH		
0A5A	GURMUKHI LETTER GHHA		
0A5B	GURMUKHI LETTER ZH		
0A5C	GURMUKHI LETTER RRA		

Group 00

Plane 00

Row 0A

Table 23 - Row 0A: Gujarati

	0A8	0A9	0AA	0AB	0AC	0AD	0AE	0AF
0		ૐ 0A90	ઠ 0AA0	ર 0AB0	ી 0AC0	ૐ 0AD0	ૠ 0AE0	
1	ઁ 0A81	ઑ 0A91	ડ 0AA1		ુ 0AC1		ૡ 0AE1	ૣ 0AF1
2	ં 0A82		ઢ 0AA2	લ 0AB2	ૃ 0AC2		ૢ 0AE2	
3	ઃ 0A83	ઔ 0A93	ણ 0AA3	ળ 0AB3	ૄ 0AC3		ૣ 0AE3	
4		ઔ 0A94	ત 0AA4		ૅ 0AC4			
5	અ 0A85	ક 0A95	થ 0AA5	વ 0AB5	૆ 0AC5			
6	આ 0A86	ખ 0A96	દ 0AA6	શ 0AB6			ૌ 0AE6	
7	ઈ 0A87	ગ 0A97	ધ 0AA7	પ 0AB7	ે 0AC7		્ 0AE7	
8	ઇ 0A88	ઘ 0A98	ન 0AA8	સ 0AB8	ૈ 0AC8		૎ 0AE8	
9	ઉ 0A89	ઙ 0A99		હ 0AB9	ૉ 0AC9		૏ 0AE9	
A	ઊ 0A8A	ચ 0A9A	પ 0AA9				ૐ 0AEA	
B	ઋ 0A8B	છ 0A9B	જ 0AA9		૊ 0ACB		૑ 0AEB	
C	ૠ 0A8C	જ 0A9C	ઝ 0AAC	઼ 0ABC	ો 0ACC		૒ 0AEC	
D	ઞ 0A8D	ઝ 0A9D	ઞ 0AAD	ઽ 0ABD	ૄ 0ACD		૓ 0AED	
E		ઞ 0A9E	મ 0AAE	ા 0ABE			૔ 0AEE	
F	એ 0A8F	ટ 0A9F	ય 0AAF	િ 0ABF			૕ 0AEF	

G = 00
P = 00

Table 23 - Row 0A: Gujarati

HEX	NAME	HEX	NAME
0A80	(This position shall not be used)	0ADD	(This position shall not be used)
0A81	GUJARATI SIGN CANDRABINDU	0ADE	(This position shall not be used)
0A82	GUJARATI SIGN ANUSVARA	0ADF	(This position shall not be used)
0A83	GUJARATI SIGN VISARGA	0AE0	GUJARATI LETTER VOCALIC RR
0A84	(This position shall not be used)	0AE1	GUJARATI LETTER VOCALIC LL
0A85	GUJARATI LETTER A	0AE2	GUJARATI VOWEL SIGN VOCALIC L
0A86	GUJARATI LETTER AA	0AE3	GUJARATI VOWEL SIGN VOCALIC LL
0A87	GUJARATI LETTER I	0AE4	(This position shall not be used)
0A88	GUJARATI LETTER II	0AE5	(This position shall not be used)
0A89	GUJARATI LETTER U	0AE6	GUJARATI DIGIT ZERO
0A8A	GUJARATI LETTER UU	0AE7	GUJARATI DIGIT ONE
0A8B	GUJARATI LETTER VOCALIC R	0AE8	GUJARATI DIGIT TWO
0A8C	GUJARATI LETTER VOCALIC L	0AE9	GUJARATI DIGIT THREE
0A8D	GUJARATI VOWEL CANDRA E	0AEA	GUJARATI DIGIT FOUR
0A8E	(This position shall not be used)	0AEB	GUJARATI DIGIT FIVE
0A8F	GUJARATI LETTER E	0AEC	GUJARATI DIGIT SIX
0A90	GUJARATI LETTER AI	0AED	GUJARATI DIGIT SEVEN
0A91	GUJARATI VOWEL CANDRA O	0AEE	GUJARATI DIGIT EIGHT
0A92	(This position shall not be used)	0AEF	GUJARATI DIGIT NINE
0A93	GUJARATI LETTER O	0AF0	(This position shall not be used)
0A94	GUJARATI LETTER AU	0AF1	GUJARATI RUPEE SIGN
0A95	GUJARATI LETTER KA	0AF2	(This position shall not be used)
0A96	GUJARATI LETTER KHA	0AF3	(This position shall not be used)
0A97	GUJARATI LETTER GA	0AF4	(This position shall not be used)
0A98	GUJARATI LETTER GHA	0AF5	(This position shall not be used)
0A99	GUJARATI LETTER NGA	0AF6	(This position shall not be used)
0A9A	GUJARATI LETTER CA	0AF7	(This position shall not be used)
0A9B	GUJARATI LETTER CHA	0AF8	(This position shall not be used)
0A9C	GUJARATI LETTER JA	0AF9	(This position shall not be used)
0A9D	GUJARATI LETTER JHA	0AFA	(This position shall not be used)
0A9E	GUJARATI LETTER NYA	0AFB	(This position shall not be used)
0A9F	GUJARATI LETTER TTA	0AFC	(This position shall not be used)
0AA0	GUJARATI LETTER TTHA	0AFD	(This position shall not be used)
0AA1	GUJARATI LETTER DDA	0AFE	(This position shall not be used)
0AA2	GUJARATI LETTER DDHA	0AFF	(This position shall not be used)
0AA3	GUJARATI LETTER NNA		
0AA4	GUJARATI LETTER TA		
0AA5	GUJARATI LETTER THA		
0AA6	GUJARATI LETTER DA		
0AA7	GUJARATI LETTER DHA		
0AA8	GUJARATI LETTER NA		
0AA9	(This position shall not be used)		
0AAA	GUJARATI LETTER PA		
0AAB	GUJARATI LETTER PHA		
0AAC	GUJARATI LETTER BA		
0AAD	GUJARATI LETTER BHA		
0AAE	GUJARATI LETTER MA		
0AAF	GUJARATI LETTER YA		
0AB0	GUJARATI LETTER RA		
0AB1	(This position shall not be used)		
0AB2	GUJARATI LETTER LA		
0AB3	GUJARATI LETTER LLA		
0AB4	(This position shall not be used)		
0AB5	GUJARATI LETTER VA		
0AB6	GUJARATI LETTER SHA		
0AB7	GUJARATI LETTER SSA		
0AB8	GUJARATI LETTER SA		
0AB9	GUJARATI LETTER HA		
0ABA	(This position shall not be used)		
0ABB	(This position shall not be used)		
0ABC	GUJARATI SIGN NUKTA		
0ABD	GUJARATI SIGN AVAGRAHA		
0ABE	GUJARATI VOWEL SIGN AA		
0ABF	GUJARATI VOWEL SIGN I		
0AC0	GUJARATI VOWEL SIGN II		
0AC1	GUJARATI VOWEL SIGN U		
0AC2	GUJARATI VOWEL SIGN UU		
0AC3	GUJARATI VOWEL SIGN VOCALIC R		
0AC4	GUJARATI VOWEL SIGN VOCALIC RR		
0AC5	GUJARATI VOWEL SIGN CANDRA E		
0AC6	(This position shall not be used)		
0AC7	GUJARATI VOWEL SIGN E		
0AC8	GUJARATI VOWEL SIGN AI		
0AC9	GUJARATI VOWEL SIGN CANDRA O		
0ACA	(This position shall not be used)		
0ACB	GUJARATI VOWEL SIGN O		
0ACC	GUJARATI VOWEL SIGN AU		
0ACD	GUJARATI SIGN VIRAMA		
0ACE	(This position shall not be used)		
0ACF	(This position shall not be used)		
0AD0	GUJARATI OM		
0AD1	(This position shall not be used)		
0AD2	(This position shall not be used)		
0AD3	(This position shall not be used)		
0AD4	(This position shall not be used)		
0AD5	(This position shall not be used)		
0AD6	(This position shall not be used)		
0AD7	(This position shall not be used)		
0AD8	(This position shall not be used)		
0AD9	(This position shall not be used)		
0ADA	(This position shall not be used)		
0ADB	(This position shall not be used)		
0ADC	(This position shall not be used)		

Group 00

Plane 00

Row 0A

Table 24 - Row 0B: Oriya

	OB0	OB1	OB2	OB3	OB4	OB5	OB6	OB7
0		ଐ OB10	ଠ OB20	ର OB30	଼ OB40		ଠ OB60	✓ OB70
1	ଃ OB01		ଡ OB21		ୃ OB41		ଢ OB61	
2	ଃ OB02		ଢ OB22	ଢ OB32	ୃ OB42			
3	ଃ OB03	ଌ OB13	ଣ OB23	ଢ OB33	ୃ OB43			
4		ଐ OB14	ଡ OB24					
5	ଅ OB05	କ OB15	ଧ OB25	ଝ OB35				
6	ଆ OB06	ଶ OB16	ଦ OB26	ଣ OB36		଼ OB56	ଠ OB66	
7	ଈ OB07	ଗ OB17	ଧ OB27	ଷ OB37	଼ OB47	଼ OB57	୧ OB67	
8	ଈ OB08	ଘ OB18	ନ OB28	ସ OB38	ୈ OB48		୨ OB68	
9	ଉ OB09	ଝ OB19		ଞ OB39			୩ OB69	
A	ଊ OB0A	ଞ OB1A	ପ OB2A				୪ OB6A	
B	ଋ OB0B	ଞ OB1B	ଫ OB2B		଼ OB4B		୫ OB6B	
C	ୠ OB0C	କ OB1C	ବ OB2C	଼ OB3C	ୈ OB4C	ଢ OB5C	୬ OB6C	
D		ୡ OB1D	ଭ OB2D	ଝ OB3D	ୃ OB4D	ଢ OB5D	୭ OB6D	
E		ଌ OB1E	ନ OB2E	଼ OB3E			୮ OB6E	
F	ୣ OB0F	ଂ OB1F	ସ OB2F	଼ OB3F		୩ OB5F	୯ OB6F	

G = 00
P = 00

Table 24 - Row 0B: Oriya

HEX	NAME	HEX	NAME
0B00	(This position shall not be used)	0B5D	ORIYA LETTER RHA
0B01	ORIYA SIGN CANDRABINDU	0B5E	(This position shall not be used)
0B02	ORIYA SIGN ANUSVARA	0B5F	ORIYA LETTER YYA
0B03	ORIYA SIGN VISARGA	0B60	ORIYA LETTER VOCALIC RR
0B04	(This position shall not be used)	0B61	ORIYA LETTER VOCALIC LL
0B05	ORIYA LETTER A	0B62	(This position shall not be used)
0B06	ORIYA LETTER AA	0B63	(This position shall not be used)
0B07	ORIYA LETTER I	0B64	(This position shall not be used)
0B08	ORIYA LETTER II	0B65	(This position shall not be used)
0B09	ORIYA LETTER U	0B66	ORIYA DIGIT ZERO
0B0A	ORIYA LETTER UU	0B67	ORIYA DIGIT ONE
0B0B	ORIYA LETTER VOCALIC R	0B68	ORIYA DIGIT TWO
0B0C	ORIYA LETTER VOCALIC L	0B69	ORIYA DIGIT THREE
0B0D	(This position shall not be used)	0B6A	ORIYA DIGIT FOUR
0B0E	(This position shall not be used)	0B6B	ORIYA DIGIT FIVE
0B0F	ORIYA LETTER E	0B6C	ORIYA DIGIT SIX
0B10	ORIYA LETTER AI	0B6D	ORIYA DIGIT SEVEN
0B11	(This position shall not be used)	0B6E	ORIYA DIGIT EIGHT
0B12	(This position shall not be used)	0B6F	ORIYA DIGIT NINE
0B13	ORIYA LETTER O	0B70	ORIYA ISSHAR
0B14	ORIYA LETTER AU	0B71	(This position shall not be used)
0B15	ORIYA LETTER KA	0B72	(This position shall not be used)
0B16	ORIYA LETTER KHA	0B73	(This position shall not be used)
0B17	ORIYA LETTER GA	0B74	(This position shall not be used)
0B18	ORIYA LETTER GHA	0B75	(This position shall not be used)
0B19	ORIYA LETTER NGA	0B76	(This position shall not be used)
0B1A	ORIYA LETTER CA	0B77	(This position shall not be used)
0B1B	ORIYA LETTER CHA	0B78	(This position shall not be used)
0B1C	ORIYA LETTER JA	0B79	(This position shall not be used)
0B1D	ORIYA LETTER JHA	0B7A	(This position shall not be used)
0B1E	ORIYA LETTER NYA	0B7B	(This position shall not be used)
0B1F	ORIYA LETTER TTA	0B7C	(This position shall not be used)
0B20	ORIYA LETTER TTHA	0B7D	(This position shall not be used)
0B21	ORIYA LETTER DDA	0B7E	(This position shall not be used)
0B22	ORIYA LETTER DDHA	0B7F	(This position shall not be used)
0B23	ORIYA LETTER NNA		
0B24	ORIYA LETTER TA		
0B25	ORIYA LETTER THA		
0B26	ORIYA LETTER DA		
0B27	ORIYA LETTER DHA		
0B28	ORIYA LETTER NA		
0B29	(This position shall not be used)		
0B2A	ORIYA LETTER PA		
0B2B	ORIYA LETTER PHA		
0B2C	ORIYA LETTER BA		
0B2D	ORIYA LETTER BHA		
0B2E	ORIYA LETTER MA		
0B2F	ORIYA LETTER YA		
0B30	ORIYA LETTER RA		
0B31	(This position shall not be used)		
0B32	ORIYA LETTER LA		
0B33	ORIYA LETTER LLA		
0B34	(This position shall not be used)		
0B35	ORIYA LETTER VA		
0B36	ORIYA LETTER SHA		
0B37	ORIYA LETTER SSA		
0B38	ORIYA LETTER SA		
0B39	ORIYA LETTER HA		
0B3A	(This position shall not be used)		
0B3B	(This position shall not be used)		
0B3C	ORIYA SIGN NUKTA		
0B3D	ORIYA SIGN AVAGRAHA		
0B3E	ORIYA VOWEL SIGN AA		
0B3F	ORIYA VOWEL SIGN I		
0B40	ORIYA VOWEL SIGN II		
0B41	ORIYA VOWEL SIGN U		
0B42	ORIYA VOWEL SIGN UU		
0B43	ORIYA VOWEL SIGN VOCALIC R		
0B44	(This position shall not be used)		
0B45	(This position shall not be used)		
0B46	(This position shall not be used)		
0B47	ORIYA VOWEL SIGN E		
0B48	ORIYA VOWEL SIGN AI		
0B49	(This position shall not be used)		
0B4A	(This position shall not be used)		
0B4B	ORIYA VOWEL SIGN O		
0B4C	ORIYA VOWEL SIGN AU		
0B4D	ORIYA SIGN VIRAMA		
0B4E	(This position shall not be used)		
0B4F	(This position shall not be used)		
0B50	(This position shall not be used)		
0B51	(This position shall not be used)		
0B52	(This position shall not be used)		
0B53	(This position shall not be used)		
0B54	(This position shall not be used)		
0B55	(This position shall not be used)		
0B56	ORIYA AI LENGTH MARK		
0B57	ORIYA AU LENGTH MARK		
0B58	(This position shall not be used)		
0B59	(This position shall not be used)		
0B5A	(This position shall not be used)		
0B5B	(This position shall not be used)		
0B5C	ORIYA LETTER RRA		

Group 00

Plane 00

Row 0B

Table 25 - Row 0B: Tamil

	0B8	0B9	0BA	0BB	0BC	0BD	0BE	0BF
0		ஐ 0B90		ர 0BB0	ீ 0BC0			ய 0BF0
1				ற 0BB1	ு 0BC1			ள 0BF1
2	ஃ 0B82	ஔ 0B92		ல 0BB2	ூ 0BC2			சு 0BF2
3	ஃ 0B83	ஔ 0B93	ண 0BA3	ள 0BB3				உ 0BF3
4		ஔ 0B94	த 0BA4	ழ 0BB4				ம் 0BF4
5	அ 0B85	க 0B95		வ 0BB5				ஶ 0BF5
6	ஆ 0B86				ெ 0BC6			யு 0BF6
7	இ 0B87			ஷ 0BB7	ே 0BC7	ள 0BD7	க 0BE7	ஶ 0BF7
8	ஈ 0B88		ந 0BA8	ஸ 0BB8	ை 0BC8		உ 0BE8	ஷெ 0BF8
9	உ 0B89	ங 0B99	ன 0BA9	ஹ 0BB9			ந 0BE9	ஶ 0BF9
A	ஊ 0B8A	ச 0B9A	ப 0BAA		ொ 0BCA		சு 0BEA	ஶ 0BFA
B					ோ 0BCB		ரு 0BEB	
C		ஐ 0B9C			ெள 0BCC		சு 0BEC	
D					ஃ 0BCD		எ 0BED	
E	எ 0B8E	ஞ 0B9E	ம 0BAE	ா 0BBE			அ 0BEE	
F	ஏ 0B8F	ல 0B9F	ய 0BAF	ி 0BBF			சு 0BEF	

G = 00
P = 00

Table 25 - Row 0B: Tamil

HEX	NAME	HEX	NAME
0B80	(This position shall not be used)	0BDD	(This position shall not be used)
0B81	(This position shall not be used)	0BDE	(This position shall not be used)
0B82	TAMIL SIGN ANUSVARA	0BDF	(This position shall not be used)
0B83	TAMIL SIGN VISARGA	0BE0	(This position shall not be used)
0B84	(This position shall not be used)	0BE1	(This position shall not be used)
0B85	TAMIL LETTER A	0BE2	(This position shall not be used)
0B86	TAMIL LETTER AA	0BE3	(This position shall not be used)
0B87	TAMIL LETTER I	0BE4	(This position shall not be used)
0B88	TAMIL LETTER II	0BE5	(This position shall not be used)
0B89	TAMIL LETTER U	0BE6	(This position shall not be used)
0B8A	TAMIL LETTER UU	0BE7	TAMIL DIGIT ONE
0B8B	(This position shall not be used)	0BE8	TAMIL DIGIT TWO
0B8C	(This position shall not be used)	0BE9	TAMIL DIGIT THREE
0B8D	(This position shall not be used)	0BEA	TAMIL DIGIT FOUR
0B8E	TAMIL LETTER E	0BEB	TAMIL DIGIT FIVE
0B8F	TAMIL LETTER EE	0BEC	TAMIL DIGIT SIX
0B90	TAMIL LETTER AI	0BED	TAMIL DIGIT SEVEN
0B91	(This position shall not be used)	0BEE	TAMIL DIGIT EIGHT
0B92	TAMIL LETTER O	0BEF	TAMIL DIGIT NINE
0B93	TAMIL LETTER OO	0BF0	TAMIL NUMBER TEN
0B94	TAMIL LETTER AU	0BF1	TAMIL NUMBER ONE HUNDRED
0B95	TAMIL LETTER KA	0BF2	TAMIL NUMBER ONE THOUSAND
0B96	(This position shall not be used)	0BF3	TAMIL DAY SIGN (Naal)
0B97	(This position shall not be used)	0BF4	TAMIL MONTH SIGN (Maatham)
0B98	(This position shall not be used)	0BF5	TAMIL YEAR SIGN (Varudam)
0B99	TAMIL LETTER NGA	0BF6	TAMIL DEBIT SIGN (Patru)
0B9A	TAMIL LETTER CA	0BF7	TAMIL CREDIT SIGN (Varavu)
0B9B	(This position shall not be used)	0BF8	TAMIL AS ABOVE SIGN (Merpadi)
0B9C	TAMIL LETTER JA	0BF9	TAMIL RUPEE SIGN (Rupai)
0B9D	(This position shall not be used)	0BFA	TAMIL NUMBER SIGN (Enn)
0B9E	TAMIL LETTER NYA	0BFB	(This position shall not be used)
0B9F	TAMIL LETTER TTA	0BFC	(This position shall not be used)
0BA0	(This position shall not be used)	0BFD	(This position shall not be used)
0BA1	(This position shall not be used)	0BFE	(This position shall not be used)
0BA2	(This position shall not be used)	0BFF	(This position shall not be used)
0BA3	TAMIL LETTER NNA		
0BA4	TAMIL LETTER TA		
0BA5	(This position shall not be used)		
0BA6	(This position shall not be used)		
0BA7	(This position shall not be used)		
0BA8	TAMIL LETTER NA		
0BA9	TAMIL LETTER NNNA		
0BAA	TAMIL LETTER PA		
0BAB	(This position shall not be used)		
0BAC	(This position shall not be used)		
0BAD	(This position shall not be used)		
0BAE	TAMIL LETTER MA		
0BAF	TAMIL LETTER YA		
0BB0	TAMIL LETTER RA		
0BB1	TAMIL LETTER RRA		
0BB2	TAMIL LETTER LA		
0BB3	TAMIL LETTER LLA		
0BB4	TAMIL LETTER LLLA		
0BB5	TAMIL LETTER VA		
0BB6	(This position shall not be used)		
0BB7	TAMIL LETTER SSA		
0BB8	TAMIL LETTER SA		
0BB9	TAMIL LETTER HA		
0BBA	(This position shall not be used)		
0BBB	(This position shall not be used)		
0BBC	(This position shall not be used)		
0BBD	(This position shall not be used)		
0BBE	TAMIL VOWEL SIGN AA		
0BBF	TAMIL VOWEL SIGN I		
0BC0	TAMIL VOWEL SIGN II		
0BC1	TAMIL VOWEL SIGN U		
0BC2	TAMIL VOWEL SIGN UU		
0BC3	(This position shall not be used)		
0BC4	(This position shall not be used)		
0BC5	(This position shall not be used)		
0BC6	TAMIL VOWEL SIGN E		
0BC7	TAMIL VOWEL SIGN EE		
0BC8	TAMIL VOWEL SIGN AI		
0BC9	(This position shall not be used)		
0BCA	TAMIL VOWEL SIGN O		
0BCB	TAMIL VOWEL SIGN OO		
0BCC	TAMIL VOWEL SIGN AU		
0BCD	TAMIL SIGN VIRAMA		
0BCE	(This position shall not be used)		
0BCF	(This position shall not be used)		
0BD0	(This position shall not be used)		
0BD1	(This position shall not be used)		
0BD2	(This position shall not be used)		
0BD3	(This position shall not be used)		
0BD4	(This position shall not be used)		
0BD5	(This position shall not be used)		
0BD6	(This position shall not be used)		
0BD7	TAMIL AU LENGTH MARK		
0BD8	(This position shall not be used)		
0BD9	(This position shall not be used)		
0BDA	(This position shall not be used)		
0BDB	(This position shall not be used)		
0BDC	(This position shall not be used)		

Group 00

Plane 00

Row 0B

Table 27 - Row 0C: Kannada

	0C8	0C9	0CA	0CB	0CC	0CD	0CE	0CF
0		ಬ 0C90	ಎ 0CA0	ಇ 0CB0	ಓ 0CC0		ಋ 0CE0	
1			ಊ 0CA1	ಋ 0CB1	ೠ 0CC1		ೡ 0CE1	
2	ಃ 0C82	ಒ 0C92	ಋ 0CA2	ಲ 0CB2	ೠ 0CC2			
3	ಃ 0C83	ಓ 0C93	ಋ 0CA3	ಳ 0CB3	ೠ 0CC3			
4		ಔ 0C94	ಋ 0CA4		ೠ 0CC4			
5	ಱ 0C85	ಱ 0C95	ಱ 0CA5	ಱ 0CB5		ಱ 0CD5		
6	ಱ 0C86	ಱ 0C96	ಱ 0CA6	ಱ 0CB6	ಱ 0CC6	ಱ 0CD6	ಱ 0CE6	
7	ಱ 0C87	ಱ 0C97	ಱ 0CA7	ಱ 0CB7	ಱ 0CC7		ಱ 0CE7	
8	ಱ 0C88	ಱ 0C98	ಱ 0CA8	ಱ 0CB8	ಱ 0CC8		ಱ 0CE8	
9	ಱ 0C89	ಱ 0C99		ಱ 0CB9			ಱ 0CE9	
A	ಱ 0C8A	ಱ 0C9A	ಱ 0CAA		ಱ 0CCA		ಱ 0CEA	
B	ಱ 0C8B	ಱ 0C9B	ಱ 0CAB		ಱ 0CCB		ಱ 0CEB	
C	ಱ 0C8C	ಱ 0C9C	ಱ 0CAC	ಱ 0CBC	ಱ 0CCC		ಱ 0CEC	
D		ಱ 0C9D	ಱ 0CAD	ಱ 0CBD	ಱ 0CCD		ಱ 0CED	
E	ಱ 0C8E	ಱ 0C9E	ಱ 0CAE	ಱ 0CBE		ಱ 0CDE	ಱ 0CEE	
F	ಱ 0C8F	ಱ 0C9F	ಱ 0CAF	ಱ 0CBF			ಱ 0CEF	

G = 00
P = 00

Table 27 - Row 0C: Kannada

HEX	NAME	HEX	NAME
0C80	(This position shall not be used)	0CDD	(This position shall not be used)
0C81	(This position shall not be used)	0CDE	KANNADA LETTER FA
0C82	KANNADA SIGN ANUSVARA	0CDF	(This position shall not be used)
0C83	KANNADA SIGN VISARGA	0CE0	KANNADA LETTER VOCALIC RR
0C84	(This position shall not be used)	0CE1	KANNADA LETTER VOCALIC LL
0C85	KANNADA LETTER A	0CE2	(This position shall not be used)
0C86	KANNADA LETTER AA	0CE3	(This position shall not be used)
0C87	KANNADA LETTER I	0CE4	(This position shall not be used)
0C88	KANNADA LETTER II	0CE5	(This position shall not be used)
0C89	KANNADA LETTER U	0CE6	KANNADA DIGIT ZERO
0C8A	KANNADA LETTER UU	0CE7	KANNADA DIGIT ONE
0C8B	KANNADA LETTER VOCALIC R	0CE8	KANNADA DIGIT TWO
0C8C	KANNADA LETTER VOCALIC L	0CE9	KANNADA DIGIT THREE
0C8D	(This position shall not be used)	0CEA	KANNADA DIGIT FOUR
0C8E	KANNADA LETTER E	0CEB	KANNADA DIGIT FIVE
0C8F	KANNADA LETTER EE	0CEC	KANNADA DIGIT SIX
0C90	KANNADA LETTER AI	0CED	KANNADA DIGIT SEVEN
0C91	(This position shall not be used)	0CEE	KANNADA DIGIT EIGHT
0C92	KANNADA LETTER O	0CEF	KANNADA DIGIT NINE
0C93	KANNADA LETTER OO	0CF0	(This position shall not be used)
0C94	KANNADA LETTER AU	0CF1	(This position shall not be used)
0C95	KANNADA LETTER KA	0CF2	(This position shall not be used)
0C96	KANNADA LETTER KHA	0CF3	(This position shall not be used)
0C97	KANNADA LETTER GA	0CF4	(This position shall not be used)
0C98	KANNADA LETTER GHA	0CF5	(This position shall not be used)
0C99	KANNADA LETTER NGA	0CF6	(This position shall not be used)
0C9A	KANNADA LETTER CA	0CF7	(This position shall not be used)
0C9B	KANNADA LETTER CHA	0CF8	(This position shall not be used)
0C9C	KANNADA LETTER JA	0CF9	(This position shall not be used)
0C9D	KANNADA LETTER JHA	0CFA	(This position shall not be used)
0C9E	KANNADA LETTER NYA	0CFB	(This position shall not be used)
0C9F	KANNADA LETTER TTA	0CFC	(This position shall not be used)
0CA0	KANNADA LETTER TTHA	0CFD	(This position shall not be used)
0CA1	KANNADA LETTER DDA	0CFE	(This position shall not be used)
0CA2	KANNADA LETTER DDHA	0CFF	(This position shall not be used)
0CA3	KANNADA LETTER NNA		
0CA4	KANNADA LETTER TA		
0CA5	KANNADA LETTER THA		
0CA6	KANNADA LETTER DA		
0CA7	KANNADA LETTER DHA		
0CA8	KANNADA LETTER NA		
0CA9	(This position shall not be used)		
0CAA	KANNADA LETTER PA		
0CAB	KANNADA LETTER PHA		
0CAC	KANNADA LETTER BA		
0CAD	KANNADA LETTER BHA		
0CAE	KANNADA LETTER MA		
0CAF	KANNADA LETTER YA		
0CB0	KANNADA LETTER RA		
0CB1	KANNADA LETTER RRA		
0CB2	KANNADA LETTER LA		
0CB3	KANNADA LETTER LLA		
0CB4	(This position shall not be used)		
0CB5	KANNADA LETTER VA		
0CB6	KANNADA LETTER SHA		
0CB7	KANNADA LETTER SSA		
0CB8	KANNADA LETTER SA		
0CB9	KANNADA LETTER HA		
0CBA	(This position shall not be used)		
0CBB	(This position shall not be used)		
0CBC	KANNADA SIGN NUKTA		
0CBD	KANNADA SIGN AVAGRAHA		
0CBE	KANNADA VOWEL SIGN AA		
0CBF	KANNADA VOWEL SIGN I		
0CC0	KANNADA VOWEL SIGN II		
0CC1	KANNADA VOWEL SIGN U		
0CC2	KANNADA VOWEL SIGN UU		
0CC3	KANNADA VOWEL SIGN VOCALIC R		
0CC4	KANNADA VOWEL SIGN VOCALIC RR		
0CC5	(This position shall not be used)		
0CC6	KANNADA VOWEL SIGN E		
0CC7	KANNADA VOWEL SIGN EE		
0CC8	KANNADA VOWEL SIGN AI		
0CC9	(This position shall not be used)		
0CCA	KANNADA VOWEL SIGN O		
0CCB	KANNADA VOWEL SIGN OO		
0CCC	KANNADA VOWEL SIGN AU		
0CCD	KANNADA SIGN VIRAMA		
0CCE	(This position shall not be used)		
0CCF	(This position shall not be used)		
0CD0	(This position shall not be used)		
0CD1	(This position shall not be used)		
0CD2	(This position shall not be used)		
0CD3	(This position shall not be used)		
0CD4	(This position shall not be used)		
0CD5	KANNADA LENGTH MARK		
0CD6	KANNADA AI LENGTH MARK		
0CD7	(This position shall not be used)		
0CD8	(This position shall not be used)		
0CD9	(This position shall not be used)		
0CDA	(This position shall not be used)		
0CDB	(This position shall not be used)		
0CDC	(This position shall not be used)		

Group 00

Plane 00

Row 0C

Table 52 - Row 17: Khmer

	178	179	17A	17B	17C	17D	17E	17F
0	ក 1780	ថ 1790	ហ 17A0	ព 17B0	ៀ 17C0	័ 17D0	័ 17E0	័ 17F0
1	ខ 1781	ទ 1791	ឡ 17A1	ឌ 17B1	េ 17C1	័ 17D1	័ 17E1	័ 17F1
2	គ 1782	ធ 1792	អ 17A2	ច 17B2	ែ 17C2	័ 17D2	័ 17E2	័ 17F2
3	ឃ 1783	ន 1793	អ 17A3	ឌ 17B3	ៃ 17C3	័ 17D3	័ 17E3	័ 17F3
4	ង 1784	ប 1794	អា 17A4	KIV AQ 17B4	ៅ 17C4	័ 17D4	័ 17E4	័ 17F4
5	ច 1785	ផ 1795	ត 17A5	KIV AA 17B5	ៅ 17C5	័ 17D5	័ 17E5	័ 17F5
6	អ 1786	ព 1796	ឡ 17A6	ា 17B6	័ 17C6	័ 17D6	័ 17E6	័ 17F6
7	ជ 1787	ភ 1797	ឌ 17A7	័ 17B7	័ 17C7	័ 17D7	័ 17E7	័ 17F7
8	ឃ 1788	ម 1798	ឌ 17A8	័ 17B8	័ 17C8	័ 17D8	័ 17E8	័ 17F8
9	ញ 1789	យ 1799	ឌ 17A9	័ 17B9	័ 17C9	័ 17D9	័ 17E9	័ 17F9
A	ដ 178A	រ 179A	ឌ 17AA	័ 17BA	័ 17CA	័ 17DA		
B	វ 178B	ល 179B	ប 17AB	័ 17BB	័ 17CB	័ 17DB		
C	ខ 178C	រ 179C	ប 17AC	័ 17BC	័ 17CC	័ 17DC		
D	ណ 178D	ត 179D	ព 17AD	័ 17BD	័ 17CD	័ 17DD		
E	ណ 178E	ថ 179E	ព 17AE	័ 17BE	័ 17CE			
F	ត 178F	ស 179F	ង 17AF	័ 17BF	័ 17CF			

G = 00
P = 00

Table 52 - Row 17: Khmer

HEX	NAME	HEX	NAME
1780	KHMER LETTER KA	17DD	KHMER SIGN ATTHACAN
1781	KHMER LETTER KHA	17DE	(This position shall not be used)
1782	KHMER LETTER KO	17DF	(This position shall not be used)
1783	KHMER LETTER KHO	17E0	KHMER DIGIT ZERO
1784	KHMER LETTER NGO	17E1	KHMER DIGIT ONE
1785	KHMER LETTER CA	17E2	KHMER DIGIT TWO
1786	KHMER LETTER CHA	17E3	KHMER DIGIT THREE
1787	KHMER LETTER CO	17E4	KHMER DIGIT FOUR
1788	KHMER LETTER CHO	17E5	KHMER DIGIT FIVE
1789	KHMER LETTER NYO	17E6	KHMER DIGIT SIX
178A	KHMER LETTER DA	17E7	KHMER DIGIT SEVEN
178B	KHMER LETTER TTHA	17E8	KHMER DIGIT EIGHT
178C	KHMER LETTER DO	17E9	KHMER DIGIT NINE
178D	KHMER LETTER TTHO	17EA	(This position shall not be used)
178E	KHMER LETTER NNO	17EB	(This position shall not be used)
178F	KHMER LETTER TA	17EC	(This position shall not be used)
1790	KHMER LETTER THA	17ED	(This position shall not be used)
1791	KHMER LETTER TO	17EE	(This position shall not be used)
1792	KHMER LETTER THO	17EF	(This position shall not be used)
1793	KHMER LETTER NO	17F0	KHMER SYMBOL LEK ATTAK SON
1794	KHMER LETTER BA	17F1	KHMER SYMBOL LEK ATTAK MUOY
1795	KHMER LETTER PHA	17F2	KHMER SYMBOL LEK ATTAK PII
1796	KHMER LETTER PO	17F3	KHMER SYMBOL LEK ATTAK BEI
1797	KHMER LETTER PHO	17F4	KHMER SYMBOL LEK ATTAK BUON
1798	KHMER LETTER MO	17F5	KHMER SYMBOL LEK ATTAK PRAM
1799	KHMER LETTER YO	17F6	KHMER SYMBOL LEK ATTAK PRAM-MUOY
179A	KHMER LETTER RO	17F7	KHMER SYMBOL LEK ATTAK PRAM-PII
179B	KHMER LETTER LO	17F8	KHMER SYMBOL LEK ATTAK PRAM-BEI
179C	KHMER LETTER VO	17F9	KHMER SYMBOL LEK ATTAK PRAM-BUON
179D	KHMER LETTER SHA	17FA	(This position shall not be used)
179E	KHMER LETTER SSO	17FB	(This position shall not be used)
179F	KHMER LETTER SA	17FC	(This position shall not be used)
17A0	KHMER LETTER HA	17FD	(This position shall not be used)
17A1	KHMER LETTER LA	17FE	(This position shall not be used)
17A2	KHMER LETTER QA	17FF	(This position shall not be used)
17A3	KHMER INDEPENDENT VOWEL QAA *		
17A4	KHMER INDEPENDENT VOWEL QAA *		
17A5	KHMER INDEPENDENT VOWEL QI		
17A6	KHMER INDEPENDENT VOWEL QII		
17A7	KHMER INDEPENDENT VOWEL QI		
17A8	KHMER INDEPENDENT VOWEL QUK		
17A9	KHMER INDEPENDENT VOWEL QUU		
17AA	KHMER INDEPENDENT VOWEL QULV		
17AB	KHMER INDEPENDENT VOWEL RY		
17AC	KHMER INDEPENDENT VOWEL RYY		
17AD	KHMER INDEPENDENT VOWEL LY		
17AE	KHMER INDEPENDENT VOWEL LYY		
17AF	KHMER INDEPENDENT VOWEL QE		
17B0	KHMER INDEPENDENT VOWEL QAI		
17B1	KHMER INDEPENDENT VOWEL QOO TYPE ONE		
17B2	KHMER INDEPENDENT VOWEL QOO TYPE TWO		
17B3	KHMER INDEPENDENT VOWEL QAU		
17B4	KHMER VOWEL INHERENT AQ *		
17B5	KHMER VOWEL INHERENT AA *		
17B6	KHMER VOWEL SIGN AA		
17B7	KHMER VOWEL SIGN I		
17B8	KHMER VOWEL SIGN II		
17B9	KHMER VOWEL SIGN Y		
17BA	KHMER VOWEL SIGN YY		
17BB	KHMER VOWEL SIGN U		
17BC	KHMER VOWEL SIGN UU		
17BD	KHMER VOWEL SIGN UA		
17BE	KHMER VOWEL SIGN OE		
17BF	KHMER VOWEL SIGN YA		
17C0	KHMER VOWEL SIGN IE		
17C1	KHMER VOWEL SIGN E		
17C2	KHMER VOWEL SIGN AE		
17C3	KHMER VOWEL SIGN AI		
17C4	KHMER VOWEL SIGN OO		
17C5	KHMER VOWEL SIGN AU		
17C6	KHMER SIGN NIKAHIT		
17C7	KHMER SIGN REAHMUK		
17C8	KHMER SIGN YUUKALEAPINTU		
17C9	KHMER SIGN MUUSIKATOAN		
17CA	KHMER SIGN TRIISAP		
17CB	KHMER SIGN BANTOC		
17CC	KHMER SIGN ROBAT		
17CD	KHMER SIGN TOANDAKHIAT		
17CE	KHMER SIGN KAKABAT		
17CF	KHMER SIGN AHSDA		
17D0	KHMER SIGN SAMYOK SANNYA		
17D1	KHMER SIGN VIRIAM		
17D2	KHMER SIGN COENG		
17D3	KHMER SIGN BATHAMASAT *		
17D4	KHMER SIGN KHAN		
17D5	KHMER SIGN BARIYOOSAN		
17D6	KHMER SIGN CAMNUC PII KUUH		
17D7	KHMER SIGN LEK TOO		
17D8	KHMER SIGN BEYYAL *		
17D9	KHMER SIGN PHNAEK MUAN		
17DA	KHMER SIGN KOOMJUT		
17DB	KHMER CURRENCY SYMBOL RIEL		
17DC	KHMER SIGN AVAKRAHASANYA		

Group 00

Plane 00

Row 17

Table 54 - Row 19: Limbu

	190	191	192	193	194
0	𑄀 1900	𑄁 1910	𑄂 1920	𑄃 1930	𑄄 1940
1	𑄅 1901	𑄆 1911	𑄇 1921	𑄈 1931	
2	𑄉 1902	𑄊 1912	𑄋 1922	𑄌 1932	
3	𑄍 1903	𑄎 1913	𑄏 1923	𑄐 1933	
4	𑄑 1904	𑄒 1914	𑄓 1924	𑄔 1934	𑄕 1944
5	𑄖 1905	𑄗 1915	𑄘 1925	𑄙 1935	𑄚 1945
6	𑄛 1906	𑄜 1916	𑄝 1926	𑄞 1936	𑄟 1946
7	𑄠 1907	𑄡 1917	𑄢 1927	𑄣 1937	𑄤 1947
8	𑄥 1908	𑄦 1918	𑄧 1928	𑄨 1938	𑄩 1948
9	𑄪 1909	𑄫 1919	𑄬 1929	𑄭 1939	𑄮 1949
A	𑄯 190A	𑄰 191A	𑄱 192A	𑄲 193A	𑄳 194A
B	𑄴 190B	𑄵 191B	𑄶 192B	𑄷 193B	𑄸 194B
C	𑄹 190C	𑄺 191C			𑄻 194C
D	𑄼 190D				𑄽 194D
E	𑄾 190E				𑄿 194E
F	𑅀 190F				𑅁 194F

G = 00
P = 00

Table 54 - Row 19: Limbu

HEX	NAME	HEX	NAME
1900	LIMBU VOWEL-CARRIER LETTER		
1901	LIMBU LETTER KA		
1902	LIMBU LETTER KHA		
1903	LIMBU LETTER GA		
1904	LIMBU LETTER GHA		
1905	LIMBU LETTER NGA		
1906	LIMBU LETTER CA		
1907	LIMBU LETTER CHA		
1908	LIMBU LETTER JA		
1909	LIMBU LETTER JHA		
190A	LIMBU LETTER YAN		
190B	LIMBU LETTER TA		
190C	LIMBU LETTER THA		
190D	LIMBU LETTER DA		
190E	LIMBU LETTER DHA		
190F	LIMBU LETTER NA		
1910	LIMBU LETTER PA		
1911	LIMBU LETTER PHA		
1912	LIMBU LETTER BA		
1913	LIMBU LETTER BHA		
1914	LIMBU LETTER MA		
1915	LIMBU LETTER YA		
1916	LIMBU LETTER RA		
1917	LIMBU LETTER LA		
1918	LIMBU LETTER WA		
1919	LIMBU LETTER SHA		
191A	LIMBU LETTER SSA		
191B	LIMBU LETTER SA		
191C	LIMBU LETTER HA		
191D	(This position shall not be used)		
191E	(This position shall not be used)		
191F	(This position shall not be used)		
1920	LIMBU VOWEL SIGN A		
1921	LIMBU VOWEL SIGN I		
1922	LIMBU VOWEL SIGN U		
1923	LIMBU VOWEL SIGN EE		
1924	LIMBU VOWEL SIGN AI		
1925	LIMBU VOWEL SIGN OO		
1926	LIMBU VOWEL SIGN AU		
1927	LIMBU VOWEL SIGN E		
1928	LIMBU VOWEL SIGN O		
1929	LIMBU SUBJOINED LETTER YA		
192A	LIMBU SUBJOINED LETTER RA		
192B	LIMBU SUBJOINED LETTER WA		
192C	(This position shall not be used)		
192D	(This position shall not be used)		
192E	(This position shall not be used)		
192F	(This position shall not be used)		
1930	LIMBU SMALL LETTER KA		
1931	LIMBU SMALL LETTER NGA		
1932	LIMBU SMALL LETTER ANUSVARA		
1933	LIMBU SMALL LETTER TA		
1934	LIMBU SMALL LETTER NA		
1935	LIMBU SMALL LETTER PA		
1936	LIMBU SMALL LETTER MA		
1937	LIMBU SMALL LETTER RA		
1938	LIMBU SMALL LETTER LA		
1939	LIMBU SIGN MUKPHRENG		
193A	LIMBU SIGN KEMPHRENG		
193B	LIMBU SIGN SA-I		
193C	(This position shall not be used)		
193D	(This position shall not be used)		
193E	(This position shall not be used)		
193F	(This position shall not be used)		
1940	LIMBU SIGN LOO		
1941	(This position shall not be used)		
1942	(This position shall not be used)		
1943	(This position shall not be used)		
1944	LIMBU EXCLAMATION MARK		
1945	LIMBU QUESTION MARK		
1946	LIMBU DIGIT ZERO		
1947	LIMBU DIGIT ONE		
1948	LIMBU DIGIT TWO		
1949	LIMBU DIGIT THREE		
194A	LIMBU DIGIT FOUR		
194B	LIMBU DIGIT FIVE		
194C	LIMBU DIGIT SIX		
194D	LIMBU DIGIT SEVEN		
194E	LIMBU DIGIT EIGHT		
194F	LIMBU DIGIT NINE		

Group 00

Plane 00

Row 19

Table 55 - Row 19: Tai Le

	195	196	197
0	ၵ 1950	ၶ 1960	ၷ 1970
1	ၸ 1951	ၹ 1961	ၺ 1971
2	ၻ 1952	ၼ 1962	ၽ 1972
3	ၾ 1953	ၿ 1963	ၠ 1973
4	ၡ 1954	ၢ 1964	ၣ 1974
5	ၤ 1955	ၥ 1965	
6	ၦ 1956	ၧ 1966	
7	ၨ 1957	ၩ 1967	
8	ၪ 1958	ၫ 1968	
9	ၬ 1959	ၭ 1969	
A	ၮ 195A	ၯ 196A	
B	ၱ 195B	ၲ 196B	
C	ၳ 195C	ၴ 196C	
D	ၶ 195D	ၷ 196D	
E	ၹ 195E		
F	ၺ 195F		

G = 00
P = 00

Table 55 - Row 19: Tai Le

HEX	NAME	HEX	NAME
1950	TAI LE LETTER KA		
1951	TAI LE LETTER XA		
1952	TAI LE LETTER NGA		
1953	TAI LE LETTER TSA		
1954	TAI LE LETTER SA		
1955	TAI LE LETTER YA		
1956	TAI LE LETTER TA		
1957	TAI LE LETTER THA		
1958	TAI LE LETTER LA		
1959	TAI LE LETTER PA		
195A	TAI LE LETTER PHA		
195B	TAI LE LETTER MA		
195C	TAI LE LETTER FA		
195D	TAI LE LETTER VA		
195E	TAI LE LETTER HA		
195F	TAI LE LETTER QA		
1960	TAI LE LETTER KHA		
1961	TAI LE LETTER TSHA		
1962	TAI LE LETTER NA		
1963	TAI LE LETTER A		
1964	TAI LE LETTER I		
1965	TAI LE LETTER EE		
1966	TAI LE LETTER EH		
1967	TAI LE LETTER U		
1968	TAI LE LETTER OO		
1969	TAI LE LETTER O		
196A	TAI LE LETTER UE		
196B	TAI LE LETTER E		
196C	TAI LE LETTER AUE		
196D	TAI LE LETTER AI		
196E	(This position shall not be used)		
196F	(This position shall not be used)		
1970	TAI LE LETTER TONE-2		
1971	TAI LE LETTER TONE-3		
1972	TAI LE LETTER TONE-4		
1973	TAI LE LETTER TONE-5		
1974	TAI LE LETTER TONE-6		
1975	(This position shall not be used)		
1976	(This position shall not be used)		
1977	(This position shall not be used)		
1978	(This position shall not be used)		
1979	(This position shall not be used)		
197A	(This position shall not be used)		
197B	(This position shall not be used)		
197C	(This position shall not be used)		
197D	(This position shall not be used)		
197E	(This position shall not be used)		
197F	(This position shall not be used)		

Group 00

Plane 00

Row 19

Table 56 - Row 19: Khmer Symbols

	19E	19F
0	០ 19E0	៨ 19F0
1	១ 19E1	១ 19F1
2	២ 19E2	២ 19F2
3	៣ 19E3	៣ 19F3
4	៤ 19E4	៤ 19F4
5	៥ 19E5	៥ 19F5
6	៦ 19E6	៦ 19F6
7	៧ 19E7	៧ 19F7
8	៨ 19E8	៨ 19F8
9	៩ 19E9	៩ 19F9
A	១០ 19EA	១០ 19FA
B	១១ 19EB	១១ 19FB
C	១២ 19EC	១២ 19FC
D	១៣ 19ED	១៣ 19FD
E	១៤ 19EE	១៤ 19FE
F	១៥ 19EF	១៥ 19FF

G = 00
P = 00

Table 56 - Row 19: Khmer Symbols

HEX	NAME	HEX	NAME
19E0	KHMER SYMBOL PATHAMASAT		
19E1	KHMER SYMBOL MUOY KOET		
19E2	KHMER SYMBOL PII KOET		
19E3	KHMER SYMBOL BEI KOET		
19E4	KHMER SYMBOL BUON KOET		
19E5	KHMER SYMBOL PRAM KOET		
19E6	KHMER SYMBOL PRAM-MUOY KOET		
19E7	KHMER SYMBOL PRAM-PII KOET		
19E8	KHMER SYMBOL PRAM-BEI KOET		
19E9	KHMER SYMBOL PRAM-BUON KOET		
19EA	KHMER SYMBOL DAP KOET		
19EB	KHMER SYMBOL DAP-MUOY KOET		
19EC	KHMER SYMBOL DAP-PII KOET		
19ED	KHMER SYMBOL DAP-BEI KOET		
19EE	KHMER SYMBOL DAP-BUON KOET		
19EF	KHMER SYMBOL DAP-PRAM KOET		
19F0	KHMER SYMBOL TUTEYASAT		
19F1	KHMER SYMBOL MUOY ROC		
19F2	KHMER SYMBOL PII ROC		
19F3	KHMER SYMBOL BEI ROC		
19F4	KHMER SYMBOL BUON ROC		
19F5	KHMER SYMBOL PRAM ROC		
19F6	KHMER SYMBOL PRAM-MUOY ROC		
19F7	KHMER SYMBOL PRAM-PII ROC		
19F8	KHMER SYMBOL PRAM-BEI ROC		
19F9	KHMER SYMBOL PRAM-BUON ROC		
19FA	KHMER SYMBOL DAP ROC		
19FB	KHMER SYMBOL DAP-MUOY ROC		
19FC	KHMER SYMBOL DAP-PII ROC		
19FD	KHMER SYMBOL DAP-BEI ROC		
19FE	KHMER SYMBOL DAP-BUON ROC		
19FF	KHMER SYMBOL DAP-PRAM ROC		

Group 00

Plane 00

Row 19

Table 57 - Row 1D: Phonetic Extensions

	1D0	1D1	1D2	1D3	1D4	1D5	1D6	1D7
0	À 1D00	Á 1D10	Â 1D20	Ä 1D30	Å 1D40	ä 1D50	å 1D60	
1	Æ 1D01	Ö 1D11	Ŵ 1D21	È 1D31	Ū 1D41	ŋ 1D51	χ 1D61	
2	æ 1D02	ö 1D12	Ẁ 1D22	Ɛ 1D32	Ū 1D42	o 1D52	i 1D62	
3	Ɔ 1D03	ø 1D13	Ʒ 1D23	Ɔ 1D33	ɑ 1D43	ɔ 1D53	ɹ 1D63	
4	Ɔ 1D04	œ 1D14	Ʒ 1D24	Ɔ 1D34	ɑ 1D44	ɔ 1D54	u 1D64	
5	Ɔ 1D05	ɔ 1D15	Ʒ 1D25	Ɔ 1D35	ɑ 1D45	ɔ 1D55	v 1D65	
6	Ɔ 1D06	ɔ 1D16	Ɔ 1D26	Ɔ 1D36	æ 1D46	p 1D56	β 1D66	
7	Ɔ 1D07	ɔ 1D17	Ɔ 1D27	Ɔ 1D37	b 1D47	t 1D57	γ 1D67	
8	Ɔ 1D08	Ɔ 1D18	Ɔ 1D28	Ɔ 1D38	d 1D48	u 1D58	ø 1D68	
9	Ɔ 1D09	Ɔ 1D19	Ɔ 1D29	Ɔ 1D39	e 1D49	ɔ 1D59	φ 1D69	
A	Ɔ 1D0A	Ɔ 1D1A	Ɔ 1D2A	Ɔ 1D3A	ə 1D4A	ɔ 1D5A	χ 1D6A	
B	Ɔ 1D0B	Ɔ 1D1B	Ɔ 1D2B	Ɔ 1D3B	ε 1D4B	v 1D5B		
C	Ɔ 1D0C	Ɔ 1D1C	Ɔ 1D2C	Ɔ 1D3C	ɜ 1D4C	ɔ 1D5C		
D	Ɔ 1D0D	Ɔ 1D1D	Ɔ 1D2D	Ɔ 1D3D	g 1D4D	β 1D5D		
E	Ɔ 1D0E	Ɔ 1D1E	Ɔ 1D2E	Ɔ 1D3E	ı 1D4E	γ 1D5E		
F	Ɔ 1D0F	Ɔ 1D1F	Ɔ 1D2F	Ɔ 1D3F	k 1D4F	δ 1D5F		

G = 00
P = 00

Table 57 - Row 1D: Phonetic Extensions




















































HEX	NAME	HEX	NAME
1D00	LATIN LETTER SMALL CAPITAL A	1D5D	MODIFIER LETTER SMALL BETA
1D01	LATIN LETTER SMALL CAPITAL AE	1D5E	MODIFIER LETTER SMALL GREEK GAMMA
1D02	LATIN SMALL LETTER TURNED AE	1D5F	MODIFIER LETTER SMALL DELTA
1D03	LATIN LETTER SMALL CAPITAL BARRED B	1D60	MODIFIER LETTER SMALL GREEK PHI
1D04	LATIN LETTER SMALL CAPITAL C	1D61	MODIFIER LETTER SMALL CHI
1D05	LATIN LETTER SMALL CAPITAL D	1D62	LATIN SUBSCRIPT SMALL LETTER I
1D06	LATIN LETTER SMALL CAPITAL ETH	1D63	LATIN SUBSCRIPT SMALL LETTER R
1D07	LATIN LETTER SMALL CAPITAL E	1D64	LATIN SUBSCRIPT SMALL LETTER U
1D08	LATIN SMALL LETTER TURNED OPEN E	1D65	LATIN SUBSCRIPT SMALL LETTER V
1D09	LATIN SMALL LETTER TURNED I	1D66	GREEK SUBSCRIPT SMALL LETTER BETA
1D0A	LATIN LETTER SMALL CAPITAL J	1D67	GREEK SUBSCRIPT SMALL LETTER GAMMA
1D0B	LATIN LETTER SMALL CAPITAL K	1D68	GREEK SUBSCRIPT SMALL LETTER RHO
1D0C	LATIN LETTER SMALL CAPITAL L WITH STROKE	1D69	GREEK SUBSCRIPT SMALL LETTER PHI
1D0D	LATIN LETTER SMALL CAPITAL M	1D6A	GREEK SUBSCRIPT SMALL LETTER CHI
1D0E	LATIN LETTER SMALL CAPITAL REVERSED N	1D6B	(This position shall not be used)
1D0F	LATIN LETTER SMALL CAPITAL O	1D6C	(This position shall not be used)
1D10	LATIN LETTER SMALL CAPITAL OPEN O	1D6D	(This position shall not be used)
1D11	LATIN SMALL LETTER SIDEWAYS O	1D6E	(This position shall not be used)
1D12	LATIN SMALL LETTER SIDEWAYS OPEN O	1D6F	(This position shall not be used)
1D13	LATIN SMALL LETTER SIDEWAYS O WITH STROKE	1D70	(This position shall not be used)
1D14	LATIN SMALL LETTER TURNED OE	1D71	(This position shall not be used)
1D15	LATIN LETTER SMALL CAPITAL OU	1D72	(This position shall not be used)
1D16	LATIN SMALL LETTER TOP HALF O	1D73	(This position shall not be used)
1D17	LATIN SMALL LETTER BOTTOM HALF O	1D74	(This position shall not be used)
1D18	LATIN LETTER SMALL CAPITAL P	1D75	(This position shall not be used)
1D19	LATIN LETTER SMALL CAPITAL REVERSED R	1D76	(This position shall not be used)
1D1A	LATIN LETTER SMALL CAPITAL TURNED R	1D77	(This position shall not be used)
1D1B	LATIN LETTER SMALL CAPITAL T	1D78	(This position shall not be used)
1D1C	LATIN LETTER SMALL CAPITAL U	1D79	(This position shall not be used)
1D1D	LATIN SMALL LETTER SIDEWAYS U	1D7A	(This position shall not be used)
1D1E	LATIN SMALL LETTER SIDEWAYS DIAERESIZED U	1D7B	(This position shall not be used)
1D1F	LATIN SMALL LETTER SIDEWAYS TURNED M	1D7C	(This position shall not be used)
1D20	LATIN LETTER SMALL CAPITAL V	1D7D	(This position shall not be used)
1D21	LATIN LETTER SMALL CAPITAL W	1D7E	(This position shall not be used)
1D22	LATIN LETTER SMALL CAPITAL Z	1D7F	(This position shall not be used)
1D23	LATIN LETTER SMALL CAPITAL EZH		
1D24	LATIN LETTER VOICED LARYNGEAL SPIRANT		
1D25	LATIN LETTER AIN		
1D26	GREEK LETTER SMALL CAPITAL GAMMA		
1D27	GREEK LETTER SMALL CAPITAL LAMDA		
1D28	GREEK LETTER SMALL CAPITAL PI		
1D29	GREEK LETTER SMALL CAPITAL RHO		
1D2A	GREEK LETTER SMALL CAPITAL PSI		
1D2B	CYRILLIC LETTER SMALL CAPITAL EL		
1D2C	MODIFIER LETTER CAPITAL A		
1D2D	MODIFIER LETTER CAPITAL AE		
1D2E	MODIFIER LETTER CAPITAL B		
1D2F	MODIFIER LETTER CAPITAL BARRED B		
1D30	MODIFIER LETTER CAPITAL D		
1D31	MODIFIER LETTER CAPITAL E		
1D32	MODIFIER LETTER CAPITAL REVERSED E		
1D33	MODIFIER LETTER CAPITAL G		
1D34	MODIFIER LETTER CAPITAL H		
1D35	MODIFIER LETTER CAPITAL I		
1D36	MODIFIER LETTER CAPITAL J		
1D37	MODIFIER LETTER CAPITAL K		
1D38	MODIFIER LETTER CAPITAL L		
1D39	MODIFIER LETTER CAPITAL M		
1D3A	MODIFIER LETTER CAPITAL N		
1D3B	MODIFIER LETTER CAPITAL REVERSED N		
1D3C	MODIFIER LETTER CAPITAL O		
1D3D	MODIFIER LETTER CAPITAL OU		
1D3E	MODIFIER LETTER CAPITAL P		
1D3F	MODIFIER LETTER CAPITAL R		
1D40	MODIFIER LETTER CAPITAL T		
1D41	MODIFIER LETTER CAPITAL U		
1D42	MODIFIER LETTER CAPITAL W		
1D43	MODIFIER LETTER SMALL A		
1D44	MODIFIER LETTER SMALL TURNED A		
1D45	MODIFIER LETTER SMALL ALPHA		
1D46	MODIFIER LETTER SMALL TURNED AE		
1D47	MODIFIER LETTER SMALL B		
1D48	MODIFIER LETTER SMALL D		
1D49	MODIFIER LETTER SMALL E		
1D4A	MODIFIER LETTER SMALL SCHWA		
1D4B	MODIFIER LETTER SMALL OPEN E		
1D4C	MODIFIER LETTER SMALL TURNED OPEN E		
1D4D	MODIFIER LETTER SMALL G		
1D4E	MODIFIER LETTER SMALL TURNED I		
1D4F	MODIFIER LETTER SMALL K		
1D50	MODIFIER LETTER SMALL M		
1D51	MODIFIER LETTER SMALL ENG		
1D52	MODIFIER LETTER SMALL O		
1D53	MODIFIER LETTER SMALL OPEN O		
1D54	MODIFIER LETTER SMALL TOP HALF O		
1D55	MODIFIER LETTER SMALL BOTTOM HALF O		
1D56	MODIFIER LETTER SMALL P		
1D57	MODIFIER LETTER SMALL T		
1D58	MODIFIER LETTER SMALL U		
1D59	MODIFIER LETTER SMALL SIDEWAYS U		
1D5A	MODIFIER LETTER SMALL TURNED M		
1D5B	MODIFIER LETTER SMALL V		
1D5C	MODIFIER LETTER SMALL AIN		

Group 00

Plane 00

Row 1D

Table 62 - Row 20: General Punctuation

	200	201	202	203	204	205	206
0	 2000	— 2010	† 2020	‰ 2030	◡ 2040	◐ 2050	 2060
1	 2001	 2011	‡ 2021	‱ 2031	∕ 2041	* 2051	 2061
2	 2002	— 2012	● 2022	' 2032	* 2042	% 2052	 2062
3	 2003	— 2013	▶ 2023	" 2033	■ 2043	~ 2053	 2063
4	 2004	— 2014	• 2024	” 2034	/ 2044	⌒ 2054	
5	 2005	— 2015	•• 2025	\ 2035	[2045		
6	 2006	 2016	••• 2026	“ 2036	}] 2046		
7	 2007	= 2017	• 2027	”” 2037	?? 2047	””” 2057	
8	 2008	‘ 2018	 2028	^ 2038	?! 2048		
9	 2009	, 2019	 2029	< 2039	!? 2049		
A	 200A	, 201A	 202A	> 203A	7 204A		 206A
B	 200B	‘ 201B	 202B	⊗ 203B	¶ 204B		 206B
C	 200C	“ 201C	 202C	!! 203C	◐ 204C		 206C
D	 200D	” 201D	 202D	!? 203D	◑ 204D		 206D
E	 200E	”” 201E	 202E	— 203E	* 204E		 206E
F	 200F	““ 201F	 202F	◡ 203F	• 204F	 205F	 206F

G = 00
P = 00

Table 62 - Row 20: General Punctuation

HEX	NAME	HEX	NAME
2000	EN QUAD	205D	(This position shall not be used)
2001	EM QUAD	205E	(This position shall not be used)
2002	EN SPACE	205F	MEDIUM MATHEMATICAL SPACE
2003	EM SPACE	2060	WORD JOINER
2004	THREE-PER-EM SPACE	2061	FUNCTION APPLICATION
2005	FOUR-PER-EM SPACE	2062	INVISIBLE TIMES
2006	SIX-PER-EM SPACE	2063	INVISIBLE SEPARATOR
2007	FIGURE SPACE	2064	(This position shall not be used)
2008	PUNCTUATION SPACE	2065	(This position shall not be used)
2009	THIN SPACE	2066	(This position shall not be used)
200A	HAIR SPACE	2067	(This position shall not be used)
200B	ZERO WIDTH SPACE	2068	(This position shall not be used)
200C	ZERO WIDTH NON-JOINER	2069	(This position shall not be used)
200D	ZERO WIDTH JOINER	206A	INHIBIT SYMMETRIC SWAPPING
200E	LEFT-TO-RIGHT MARK	206B	ACTIVATE SYMMETRIC SWAPPING
200F	RIGHT-TO-LEFT MARK	206C	INHIBIT ARABIC FORM SHAPING
2010	HYPHEN	206D	ACTIVATE ARABIC FORM SHAPING
2011	NON-BREAKING HYPHEN	206E	NATIONAL DIGIT SHAPES
2012	FIGURE DASH	206F	NOMINAL DIGIT SHAPES
2013	EN DASH		
2014	EM DASH		
2015	HORIZONTAL BAR		
2016	DOUBLE VERTICAL LINE		
2017	DOUBLE LOW LINE		
2018	LEFT SINGLE QUOTATION MARK		
2019	RIGHT SINGLE QUOTATION MARK		
201A	SINGLE LOW-9 QUOTATION MARK		
201B	SINGLE HIGH-REVERSED-9 QUOTATION MARK		
201C	LEFT DOUBLE QUOTATION MARK		
201D	RIGHT DOUBLE QUOTATION MARK		
201E	DOUBLE LOW-9 QUOTATION MARK		
201F	DOUBLE HIGH-REVERSED-9 QUOTATION MARK		
2020	DAGGER		
2021	DOUBLE DAGGER		
2022	BULLET		
2023	TRIANGULAR BULLET		
2024	ONE DOT LEADER		
2025	TWO DOT LEADER		
2026	HORIZONTAL ELLIPSIS		
2027	HYPHENATION POINT		
2028	LINE SEPARATOR		
2029	PARAGRAPH SEPARATOR		
202A	LEFT-TO-RIGHT EMBEDDING		
202B	RIGHT-TO-LEFT EMBEDDING		
202C	POP DIRECTIONAL FORMATTING		
202D	LEFT-TO-RIGHT OVERRIDE		
202E	RIGHT-TO-LEFT OVERRIDE		
202F	NARROW NO-BREAK SPACE		
2030	PER MILLE SIGN		
2031	PER TEN THOUSAND SIGN		
2032	PRIME		
2033	DOUBLE PRIME		
2034	TRIPLE PRIME		
2035	REVERSED PRIME		
2036	REVERSED DOUBLE PRIME		
2037	REVERSED TRIPLE PRIME		
2038	CARET		
2039	SINGLE LEFT-POINTING ANGLE QUOTATION MARK		
203A	SINGLE RIGHT-POINTING ANGLE QUOTATION MARK		
203B	REFERENCE MARK		
203C	DOUBLE EXCLAMATION MARK		
203D	INTERROBANG		
203E	OVERLINE		
203F	UNDERTIE (Eotikon)		
2040	CHARACTER TIE		
2041	CARET INSERTION POINT		
2042	ASTERISM		
2043	HYPHEN BULLET		
2044	FRACTION SLASH		
2045	LEFT SQUARE BRACKET WITH QUILL		
2046	RIGHT SQUARE BRACKET WITH QUILL		
2047	DOUBLE QUESTION MARK		
2048	QUESTION EXCLAMATION MARK		
2049	EXCLAMATION QUESTION MARK		
204A	TIRONIAN SIGN ET		
204B	REVERSED PILCROW SIGN		
204C	BLACK LEFTWARDS BULLET		
204D	BLACK RIGHTWARDS BULLET		
204E	LOW ASTERISK		
204F	REVERSED SEMICOLON		
2050	CLOSE UP		
2051	TWO ASTERISKS ALIGNED VERTICALLY		
2052	COMMERCIAL MINUS SIGN		
2053	SWUNG DASH		
2054	INVERTED UNDERTIE		
2055	(This position shall not be used)		
2056	(This position shall not be used)		
2057	QUADRUPLE PRIME		
2058	(This position shall not be used)		
2059	(This position shall not be used)		
205A	(This position shall not be used)		
205B	(This position shall not be used)		
205C	(This position shall not be used)		

Group 00

Plane 00

Row 20

Table 66 - Row 21: Letterlike Symbols

	210	211	212	213	214
0	<i>a/c</i> 2100	<i>J</i> 2110	SM 2120	<i>E</i> 2130	Σ 2140
1	<i>a/s</i> 2101	<i>J</i> 2111	TEL 2121	<i>F</i> 2131	<i>G</i> 2141
2	<i>C</i> 2102	<i>L</i> 2112	TM 2122	<i>H</i> 2132	<i>I</i> 2142
3	$^{\circ}\text{C}$ 2103	<i>l</i> 2113	<i>V</i> 2123	<i>M</i> 2133	<i>J</i> 2143
4	<i>¢</i> 2104	<i>W</i> 2114	<i>Z</i> 2124	<i>o</i> 2134	<i>Y</i> 2144
5	<i>%</i> 2105	<i>N</i> 2115	<i>z</i> 2125	<i>X</i> 2135	<i>D</i> 2145
6	<i>%u</i> 2106	<i>N_o</i> 2116	Ω 2126	<i>U</i> 2136	<i>d</i> 2146
7	<i>E</i> 2107	<i>®</i> 2117	<i>U</i> 2127	<i>Y</i> 2137	<i>e</i> 2147
8	<i>Ð</i> 2108	<i>ø</i> 2118	<i>z</i> 2128	<i>T</i> 2138	<i>i</i> 2148
9	$^{\circ}\text{F}$ 2109	<i>P</i> 2119	<i>ı</i> 2129	<i>i</i> 2139	<i>j</i> 2149
A	<i>g</i> 210A	<i>Q</i> 211A	<i>K</i> 212A	<i>O</i> 213A	<i>Þ</i> 214A
B	<i>H</i> 210B	<i>R</i> 211B	<i>Å</i> 212B	FAX 213B	<i>ø</i> 214B
C	<i>h</i> 210C	<i>R</i> 211C	<i>B</i> 212C		
D	<i>H</i> 210D	<i>R</i> 211D	<i>C</i> 212D	<i>Y</i> 213D	
E	<i>h</i> 210E	<i>R</i> 211E	<i>e</i> 212E	<i>T</i> 213E	
F	<i>h</i> 210F	<i>R</i> 211F	<i>e</i> 212F	<i>U</i> 213F	

G = 00
P = 00

Table 66 - Row 21: Letterlike Symbols

















































































HEX	NAME	HEX	NAME
2100	ACCOUNT OF		
2101	ADDRESSED TO THE SUBJECT		
2102	DOUBLE-STRUCK CAPITAL C		
2103	DEGREE CELSIUS		
2104	CENTRE LINE SYMBOL		
2105	CARE OF		
2106	CADA UNA		
2107	EULER CONSTANT		
2108	SCRUPLE		
2109	DEGREE FAHRENHEIT		
210A	SCRIPT SMALL G		
210B	SCRIPT CAPITAL H		
210C	BLACK-LETTER CAPITAL H		
210D	DOUBLE-STRUCK CAPITAL H		
210E	PLANCK CONSTANT		
210F	PLANCK CONSTANT OVER TWO PI		
2110	SCRIPT CAPITAL I		
2111	BLACK-LETTER CAPITAL I		
2112	SCRIPT CAPITAL L		
2113	SCRIPT SMALL L		
2114	L B BAR SYMBOL		
2115	DOUBLE-STRUCK CAPITAL N		
2116	NUMERO SIGN		
2117	SOUND RECORDING COPYRIGHT		
2118	SCRIPT CAPITAL P		
2119	DOUBLE-STRUCK CAPITAL P		
211A	DOUBLE-STRUCK CAPITAL Q		
211B	SCRIPT CAPITAL R		
211C	BLACK-LETTER CAPITAL R		
211D	DOUBLE-STRUCK CAPITAL R		
211E	PRESCRIPTION TAKE		
211F	RESPONSE		
2120	SERVICE MARK		
2121	TELEPHONE SIGN		
2122	TRADE MARK SIGN		
2123	VERSICLE		
2124	DOUBLE-STRUCK CAPITAL Z		
2125	OUNCE SIGN		
2126	OHM SIGN		
2127	INVERTED OHM SIGN		
2128	BLACK-LETTER CAPITAL Z		
2129	TURNED GREEK SMALL LETTER IOTA		
212A	KELVIN SIGN		
212B	ANGSTROM SIGN		
212C	SCRIPT CAPITAL B		
212D	BLACK-LETTER CAPITAL C		
212E	ESTIMATED SYMBOL		
212F	SCRIPT SMALL E		
2130	SCRIPT CAPITAL E		
2131	SCRIPT CAPITAL F		
2132	TURNED CAPITAL F		
2133	SCRIPT CAPITAL M		
2134	SCRIPT SMALL O		
2135	ALEF SYMBOL		
2136	BET SYMBOL		
2137	GIMEL SYMBOL		
2138	DALET SYMBOL		
2139	INFORMATION SOURCE		
213A	ROTATED CAPITAL Q		
213B	FACSIMILE SIGN		
213C	(This position shall not be used)		
213D	DOUBLE-STRUCK SMALL GAMMA		
213E	DOUBLE-STRUCK CAPITAL GAMMA		
213F	DOUBLE-STRUCK CAPITAL PI		
2140	DOUBLE-STRUCK N-ARY SUMMATION		
2141	TURNED SANS-SERIF CAPITAL G		
2142	TURNED SANS-SERIF CAPITAL L		
2143	REVERSED SANS-SERIF CAPITAL L		
2144	TURNED SANS-SERIF CAPITAL Y		
2145	DOUBLE-STRUCK ITALIC CAPITAL D		
2146	DOUBLE-STRUCK ITALIC SMALL D		
2147	DOUBLE-STRUCK ITALIC SMALL E		
2148	DOUBLE-STRUCK ITALIC SMALL I		
2149	DOUBLE-STRUCK ITALIC SMALL J		
214A	PROPERTY LINE		
214B	TURNED AMPERSAND		
214C	(This position shall not be used)		
214D	(This position shall not be used)		
214E	(This position shall not be used)		
214F	(This position shall not be used)		

Group 00

Plane 00

Row 21

Table 72 - Row 23: Miscellaneous Technical

	238	239	23A	23B	23C	23D	23E	23F
0	 2380	 2390	 23A0	 23B0	 23C0			
1	 2381	 2391	 23A1	 23B1	 23C1			
2	 2382	 2392	 23A2	 23B2	 23C2			
3	 2383	 2393	 23A3	 23B3	 23C3			
4	 2384	 2394	 23A4	 23B4	 23C4			
5	 2385	 2395	 23A5	 23B5	 23C5			
6	 2386	 2396	 23A6	 23B6	 23C6			
7	 2387	 2397	 23A7	 23B7	 23C7			
8	 2388	 2398	 23A8	 23B8	 23C8			
9	 2389	 2399	 23A9	 23B9	 23C9			
A	 238A	 239A	 23AA	 23BA	 23CA			
B	 238B	 239B	 23AB	 23BB	 23CB			
C	 238C	 239C	 23AC	 23BC	 23CC			
D	 238D	 239D	 23AD	 23BD	 23CD			
E	 238E	 239E	 23AE	 23BE	 23CE			
F	 238F	 239F	 23AF	 23BF	 23CF			

G = 00
P = 00

Table 72 - Row 23: Miscellaneous Technical

HEX	NAME	HEX	NAME
2380	INSERTION SYMBOL	23DD	(This position shall not be used)
2381	CONTINUOUS UNDERLINE SYMBOL	23DE	(This position shall not be used)
2382	DISCONTINUOUS UNDERLINE SYMBOL	23DF	(This position shall not be used)
2383	EMPHASIS SYMBOL	23E0	(This position shall not be used)
2384	COMPOSITION SYMBOL	23E1	(This position shall not be used)
2385	WHITE SQUARE WITH CENTRE VERTICAL LINE	23E2	(This position shall not be used)
2386	ENTER SYMBOL	23E3	(This position shall not be used)
2387	ALTERNATIVE KEY SYMBOL	23E4	(This position shall not be used)
2388	HELM SYMBOL	23E5	(This position shall not be used)
2389	CIRCLED HORIZONTAL BAR WITH NOTCH (pause)	23E6	(This position shall not be used)
238A	CIRCLED TRIANGLE DOWN (break)	23E7	(This position shall not be used)
238B	BROKEN CIRCLE WITH NORTHWEST ARROW (escape)	23E8	(This position shall not be used)
238C	UNDO SYMBOL	23E9	(This position shall not be used)
238D	MONOSTABLE SYMBOL	23EA	(This position shall not be used)
238E	HYSTERESIS SYMBOL	23EB	(This position shall not be used)
238F	OPEN-CIRCUIT-OUTPUT H-TYPE SYMBOL	23EC	(This position shall not be used)
2390	OPEN-CIRCUIT-OUTPUT L-TYPE SYMBOL	23ED	(This position shall not be used)
2391	PASSIVE-PULL-DOWN-OUTPUT SYMBOL	23EE	(This position shall not be used)
2392	PASSIVE-PULL-UP-OUTPUT SYMBOL	23EF	(This position shall not be used)
2393	DIRECT CURRENT SYMBOL FORM TWO	23F0	(This position shall not be used)
2394	SOFTWARE-FUNCTION SYMBOL	23F1	(This position shall not be used)
2395	APL FUNCTIONAL SYMBOL QUAD	23F2	(This position shall not be used)
2396	DECIMAL SEPARATOR KEY SYMBOL	23F3	(This position shall not be used)
2397	PREVIOUS PAGE	23F4	(This position shall not be used)
2398	NEXT PAGE	23F5	(This position shall not be used)
2399	PRINT SCREEN SYMBOL	23F6	(This position shall not be used)
239A	CLEAR SCREEN SYMBOL	23F7	(This position shall not be used)
239B	LEFT PARENTHESIS UPPER HOOK	23F8	(This position shall not be used)
239C	LEFT PARENTHESIS EXTENSION	23F9	(This position shall not be used)
239D	LEFT PARENTHESIS LOWER HOOK	23FA	(This position shall not be used)
239E	RIGHT PARENTHESIS UPPER HOOK	23FB	(This position shall not be used)
239F	RIGHT PARENTHESIS EXTENSION	23FC	(This position shall not be used)
23A0	RIGHT PARENTHESIS LOWER HOOK	23FD	(This position shall not be used)
23A1	LEFT SQUARE BRACKET UPPER CORNER	23FE	(This position shall not be used)
23A2	LEFT SQUARE BRACKET EXTENSION	23FF	(This position shall not be used)
23A3	LEFT SQUARE BRACKET LOWER CORNER		
23A4	RIGHT SQUARE BRACKET UPPER CORNER		
23A5	RIGHT SQUARE BRACKET EXTENSION		
23A6	RIGHT SQUARE BRACKET LOWER CORNER		
23A7	LEFT CURLY BRACKET UPPER HOOK		
23A8	LEFT CURLY BRACKET MIDDLE PIECE		
23A9	LEFT CURLY BRACKET LOWER HOOK		
23AA	CURLY BRACKET EXTENSION		
23AB	RIGHT CURLY BRACKET UPPER HOOK		
23AC	RIGHT CURLY BRACKET MIDDLE PIECE		
23AD	RIGHT CURLY BRACKET LOWER HOOK		
23AE	INTEGRAL EXTENSION		
23AF	HORIZONTAL LINE EXTENSION		
23B0	UPPER LEFT OR LOWER RIGHT CURLY BRACKET SECTION		
23B1	UPPER RIGHT OR LOWER LEFT CURLY BRACKET SECTION		
23B2	SUMMATION TOP		
23B3	SUMMATION BOTTOM		
23B4	TOP SQUARE BRACKET		
23B5	BOTTOM SQUARE BRACKET		
23B6	BOTTOM SQUARE BRACKET OVER TOP SQUARE BRACKET		
23B7	RADICAL SYMBOL BOTTOM		
23B8	LEFT VERTICAL BOX LINE		
23B9	RIGHT VERTICAL BOX LINE		
23BA	HORIZONTAL SCAN LINE-1		
23BB	HORIZONTAL SCAN LINE-3		
23BC	HORIZONTAL SCAN LINE-7		
23BD	HORIZONTAL SCAN LINE-9		
23BE	DENTISTRY SYMBOL LIGHT VERTICAL AND TOP RIGHT		
23BF	DENTISTRY SYMBOL LIGHT VERTICAL AND BOTTOM RIGHT		
23C0	DENTISTRY SYMBOL LIGHT VERTICAL WITH CIRCLE		
23C1	DENTISTRY SYMBOL LIGHT DOWN AND HORIZONTAL WITH CIRCLE		
23C2	DENTISTRY SYMBOL LIGHT UP AND HORIZONTAL WITH CIRCLE		
23C3	DENTISTRY SYMBOL LIGHT VERTICAL WITH TRIANGLE		
23C4	DENTISTRY SYMBOL LIGHT DOWN AND HORIZONTAL WITH TRIANGLE		
23C5	DENTISTRY SYMBOL LIGHT UP AND HORIZONTAL WITH TRIANGLE		
23C6	DENTISTRY SYMBOL LIGHT VERTICAL AND WAVE		
23C7	DENTISTRY SYMBOL LIGHT DOWN AND HORIZONTAL WITH WAVE		
23C8	DENTISTRY SYMBOL LIGHT UP AND HORIZONTAL WITH WAVE		
23C9	DENTISTRY SYMBOL LIGHT DOWN AND HORIZONTAL		
23CA	DENTISTRY SYMBOL LIGHT UP AND HORIZONTAL		
23CB	DENTISTRY SYMBOL LIGHT VERTICAL AND TOP LEFT		
23CC	DENTISTRY SYMBOL LIGHT VERTICAL AND BOTTOM LEFT		
23CD	SQUARE FOOT		
23CE	RETURN SYMBOL		
23CF	EJECT SYMBOL		
23D0	(This position shall not be used)		
23D1	(This position shall not be used)		
23D2	(This position shall not be used)		
23D3	(This position shall not be used)		
23D4	(This position shall not be used)		
23D5	(This position shall not be used)		
23D6	(This position shall not be used)		
23D7	(This position shall not be used)		
23D8	(This position shall not be used)		
23D9	(This position shall not be used)		
23DA	(This position shall not be used)		
23DB	(This position shall not be used)		
23DC	(This position shall not be used)		

Table 75 - Row 24: Enclosed Alphanumerics

	246	247	248	249	24A	24B	24C	24D	24E	24F
0	① 2460	⑰ 2470	(13) 2480	9. 2490	(e) 24A0	(u) 24B0	Ⓚ 24C0	ⓐ 24D0	Ⓠ 24E0	⑯ 24F0
1	② 2461	⑱ 2471	(14) 2481	10. 2491	(f) 24A1	(v) 24B1	Ⓛ 24C1	ⓑ 24D1	Ⓡ 24E1	⑰ 24F1
2	③ 2462	⑲ 2472	(15) 2482	11. 2492	(g) 24A2	(w) 24B2	Ⓜ 24C2	ⓒ 24D2	Ⓢ 24E2	⑱ 24F2
3	④ 2463	⑳ 2473	(16) 2483	12. 2493	(h) 24A3	(x) 24B3	Ⓝ 24C3	ⓓ 24D3	Ⓣ 24E3	⑲ 24F3
4	⑤ 2464	(1) 2474	(17) 2484	13. 2494	(i) 24A4	(y) 24B4	Ⓞ 24C4	ⓔ 24D4	Ⓤ 24E4	⑳ 24F4
5	⑥ 2465	(2) 2475	(18) 2485	14. 2495	(j) 24A5	(z) 24B5	Ⓟ 24C5	ⓕ 24D5	Ⓡ 24E5	① 24F5
6	⑦ 2466	(3) 2476	(19) 2486	15. 2496	(k) 24A6	Ⓐ 24B6	Ⓠ 24C6	ⓖ 24D6	Ⓢ 24E6	② 24F6
7	⑧ 2467	(4) 2477	(20) 2487	16. 2497	(l) 24A7	Ⓑ 24B7	Ⓡ 24C7	ⓗ 24D7	Ⓣ 24E7	③ 24F7
8	⑨ 2468	(5) 2478	1. 2488	17. 2498	(m) 24A8	Ⓒ 24B8	Ⓢ 24C8	Ⓤ 24D8	Ⓢ 24E8	④ 24F8
9	⑩ 2469	(6) 2479	2. 2489	18. 2499	(n) 24A9	Ⓓ 24B9	Ⓣ 24C9	Ⓥ 24D9	Ⓢ 24E9	⑤ 24F9
A	⑪ 246A	(7) 247A	3. 248A	19. 249A	(o) 24AA	Ⓔ 24BA	Ⓤ 24CA	Ⓚ 24DA	Ⓞ 24EA	⑥ 24FA
B	⑫ 246B	(8) 247B	4. 248B	20. 249B	(p) 24AB	Ⓕ 24BB	Ⓡ 24CB	Ⓛ 24DB	⑪ 24EB	⑦ 24FB
C	⑬ 246C	(9) 247C	5. 248C	(a) 249C	(q) 24AC	Ⓖ 24BC	Ⓢ 24CC	Ⓜ 24DC	⑫ 24EC	⑧ 24FC
D	⑭ 246D	(10) 247D	6. 248D	(b) 249D	(r) 24AD	Ⓖ 24BD	Ⓝ 24CD	Ⓝ 24DD	⑬ 24ED	⑨ 24FD
E	⑮ 246E	(11) 247E	7. 248E	(c) 249E	(s) 24AE	Ⓘ 24BE	Ⓢ 24CE	Ⓞ 24DE	⑭ 24EE	⑩ 24FE
F	⑯ 246F	(12) 247F	8. 248F	(d) 249F	(t) 24AF	Ⓙ 24BF	Ⓢ 24CF	Ⓟ 24DF	⑮ 24EF	⑰ 24FF

G = 00
P = 00

Table 75 - Row 24: Enclosed Alphanumerics

HEX	NAME	HEX	NAME
2460	CIRCLED DIGIT ONE	24BD	CIRCLED LATIN CAPITAL LETTER H
2461	CIRCLED DIGIT TWO	24BE	CIRCLED LATIN CAPITAL LETTER I
2462	CIRCLED DIGIT THREE	24BF	CIRCLED LATIN CAPITAL LETTER J
2463	CIRCLED DIGIT FOUR	24C0	CIRCLED LATIN CAPITAL LETTER K
2464	CIRCLED DIGIT FIVE	24C1	CIRCLED LATIN CAPITAL LETTER L
2465	CIRCLED DIGIT SIX	24C2	CIRCLED LATIN CAPITAL LETTER M
2466	CIRCLED DIGIT SEVEN	24C3	CIRCLED LATIN CAPITAL LETTER N
2467	CIRCLED DIGIT EIGHT	24C4	CIRCLED LATIN CAPITAL LETTER O
2468	CIRCLED DIGIT NINE	24C5	CIRCLED LATIN CAPITAL LETTER P
2469	CIRCLED NUMBER TEN	24C6	CIRCLED LATIN CAPITAL LETTER Q
246A	CIRCLED NUMBER ELEVEN	24C7	CIRCLED LATIN CAPITAL LETTER R
246B	CIRCLED NUMBER TWELVE	24C8	CIRCLED LATIN CAPITAL LETTER S
246C	CIRCLED NUMBER THIRTEEN	24C9	CIRCLED LATIN CAPITAL LETTER T
246D	CIRCLED NUMBER FOURTEEN	24CA	CIRCLED LATIN CAPITAL LETTER U
246E	CIRCLED NUMBER FIFTEEN	24CB	CIRCLED LATIN CAPITAL LETTER V
246F	CIRCLED NUMBER SIXTEEN	24CC	CIRCLED LATIN CAPITAL LETTER W
2470	CIRCLED NUMBER SEVENTEEN	24CD	CIRCLED LATIN CAPITAL LETTER X
2471	CIRCLED NUMBER EIGHTEEN	24CE	CIRCLED LATIN CAPITAL LETTER Y
2472	CIRCLED NUMBER NINETEEN	24CF	CIRCLED LATIN CAPITAL LETTER Z
2473	CIRCLED NUMBER TWENTY	24D0	CIRCLED LATIN SMALL LETTER A
2474	PARENTHESIZED DIGIT ONE	24D1	CIRCLED LATIN SMALL LETTER B
2475	PARENTHESIZED DIGIT TWO	24D2	CIRCLED LATIN SMALL LETTER C
2476	PARENTHESIZED DIGIT THREE	24D3	CIRCLED LATIN SMALL LETTER D
2477	PARENTHESIZED DIGIT FOUR	24D4	CIRCLED LATIN SMALL LETTER E
2478	PARENTHESIZED DIGIT FIVE	24D5	CIRCLED LATIN SMALL LETTER F
2479	PARENTHESIZED DIGIT SIX	24D6	CIRCLED LATIN SMALL LETTER G
247A	PARENTHESIZED DIGIT SEVEN	24D7	CIRCLED LATIN SMALL LETTER H
247B	PARENTHESIZED DIGIT EIGHT	24D8	CIRCLED LATIN SMALL LETTER I
247C	PARENTHESIZED DIGIT NINE	24D9	CIRCLED LATIN SMALL LETTER J
247D	PARENTHESIZED NUMBER TEN	24DA	CIRCLED LATIN SMALL LETTER K
247E	PARENTHESIZED NUMBER ELEVEN	24DB	CIRCLED LATIN SMALL LETTER L
247F	PARENTHESIZED NUMBER TWELVE	24DC	CIRCLED LATIN SMALL LETTER M
2480	PARENTHESIZED NUMBER THIRTEEN	24DD	CIRCLED LATIN SMALL LETTER N
2481	PARENTHESIZED NUMBER FOURTEEN	24DE	CIRCLED LATIN SMALL LETTER O
2482	PARENTHESIZED NUMBER FIFTEEN	24DF	CIRCLED LATIN SMALL LETTER P
2483	PARENTHESIZED NUMBER SIXTEEN	24E0	CIRCLED LATIN SMALL LETTER Q
2484	PARENTHESIZED NUMBER SEVENTEEN	24E1	CIRCLED LATIN SMALL LETTER R
2485	PARENTHESIZED NUMBER EIGHTEEN	24E2	CIRCLED LATIN SMALL LETTER S
2486	PARENTHESIZED NUMBER NINETEEN	24E3	CIRCLED LATIN SMALL LETTER T
2487	PARENTHESIZED NUMBER TWENTY	24E4	CIRCLED LATIN SMALL LETTER U
2488	DIGIT ONE FULL STOP	24E5	CIRCLED LATIN SMALL LETTER V
2489	DIGIT TWO FULL STOP	24E6	CIRCLED LATIN SMALL LETTER W
248A	DIGIT THREE FULL STOP	24E7	CIRCLED LATIN SMALL LETTER X
248B	DIGIT FOUR FULL STOP	24E8	CIRCLED LATIN SMALL LETTER Y
248C	DIGIT FIVE FULL STOP	24E9	CIRCLED LATIN SMALL LETTER Z
248D	DIGIT SIX FULL STOP	24EA	CIRCLED DIGIT ZERO
248E	DIGIT SEVEN FULL STOP	24EB	NEGATIVE CIRCLED NUMBER ELEVEN
248F	DIGIT EIGHT FULL STOP	24EC	NEGATIVE CIRCLED NUMBER TWELVE
2490	DIGIT NINE FULL STOP	24ED	NEGATIVE CIRCLED NUMBER THIRTEEN
2491	NUMBER TEN FULL STOP	24EE	NEGATIVE CIRCLED NUMBER FOURTEEN
2492	NUMBER ELEVEN FULL STOP	24EF	NEGATIVE CIRCLED NUMBER FIFTEEN
2493	NUMBER TWELVE FULL STOP	24F0	NEGATIVE CIRCLED NUMBER SIXTEEN
2494	NUMBER THIRTEEN FULL STOP	24F1	NEGATIVE CIRCLED NUMBER SEVENTEEN
2495	NUMBER FOURTEEN FULL STOP	24F2	NEGATIVE CIRCLED NUMBER EIGHTEEN
2496	NUMBER FIFTEEN FULL STOP	24F3	NEGATIVE CIRCLED NUMBER NINETEEN
2497	NUMBER SIXTEEN FULL STOP	24F4	NEGATIVE CIRCLED NUMBER TWENTY
2498	NUMBER SEVENTEEN FULL STOP	24F5	DOUBLE CIRCLED DIGIT ONE
2499	NUMBER EIGHTEEN FULL STOP	24F6	DOUBLE CIRCLED DIGIT TWO
249A	NUMBER NINETEEN FULL STOP	24F7	DOUBLE CIRCLED DIGIT THREE
249B	NUMBER TWENTY FULL STOP	24F8	DOUBLE CIRCLED DIGIT FOUR
249C	PARENTHESIZED LATIN SMALL LETTER A	24F9	DOUBLE CIRCLED DIGIT FIVE
249D	PARENTHESIZED LATIN SMALL LETTER B	24FA	DOUBLE CIRCLED DIGIT SIX
249E	PARENTHESIZED LATIN SMALL LETTER C	24FB	DOUBLE CIRCLED DIGIT SEVEN
249F	PARENTHESIZED LATIN SMALL LETTER D	24FC	DOUBLE CIRCLED DIGIT EIGHT
24A0	PARENTHESIZED LATIN SMALL LETTER E	24FD	DOUBLE CIRCLED DIGIT NINE
24A1	PARENTHESIZED LATIN SMALL LETTER F	24FE	DOUBLE CIRCLED NUMBER TEN
24A2	PARENTHESIZED LATIN SMALL LETTER G	24FF	NEGATIVE CIRCLED DIGIT ZERO
24A3	PARENTHESIZED LATIN SMALL LETTER H		
24A4	PARENTHESIZED LATIN SMALL LETTER I		
24A5	PARENTHESIZED LATIN SMALL LETTER J		
24A6	PARENTHESIZED LATIN SMALL LETTER K		
24A7	PARENTHESIZED LATIN SMALL LETTER L		
24A8	PARENTHESIZED LATIN SMALL LETTER M		
24A9	PARENTHESIZED LATIN SMALL LETTER N		
24AA	PARENTHESIZED LATIN SMALL LETTER O		
24AB	PARENTHESIZED LATIN SMALL LETTER P		
24AC	PARENTHESIZED LATIN SMALL LETTER Q		
24AD	PARENTHESIZED LATIN SMALL LETTER R		
24AE	PARENTHESIZED LATIN SMALL LETTER S		
24AF	PARENTHESIZED LATIN SMALL LETTER T		
24B0	PARENTHESIZED LATIN SMALL LETTER U		
24B1	PARENTHESIZED LATIN SMALL LETTER V		
24B2	PARENTHESIZED LATIN SMALL LETTER W		
24B3	PARENTHESIZED LATIN SMALL LETTER X		
24B4	PARENTHESIZED LATIN SMALL LETTER Y		
24B5	PARENTHESIZED LATIN SMALL LETTER Z		
24B6	CIRCLED LATIN CAPITAL LETTER A		
24B7	CIRCLED LATIN CAPITAL LETTER B		
24B8	CIRCLED LATIN CAPITAL LETTER C		
24B9	CIRCLED LATIN CAPITAL LETTER D		
24BA	CIRCLED LATIN CAPITAL LETTER E		
24BB	CIRCLED LATIN CAPITAL LETTER F		
24BC	CIRCLED LATIN CAPITAL LETTER G		

Table 79 - Row 26: Miscellaneous Symbols

	260	261	262	263	264	265	266	267
0	2600	2610	2620	2630	2640	2650	2660	2670
1	2601	2611	2621	2631	2641	2651	2661	2671
2	2602	2612	2622	2632	2642	2652	2662	2672
3	2603	2613	2623	2633	2643	2653	2663	2673
4	2604	2614	2624	2634	2644	2654	2664	2674
5	2605	2615	2625	2635	2645	2655	2665	2675
6	2606	2616	2626	2636	2646	2656	2666	2676
7	2607	2617	2627	2637	2647	2657	2667	2677
8	2608	2618	2628	2638	2648	2658	2668	2678
9	2609	2619	2629	2639	2649	2659	2669	2679
A	260A	261A	262A	263A	264A	265A	266A	267A
B	260B	261B	262B	263B	264B	265B	266B	267B
C	260C	261C	262C	263C	264C	265C	266C	267C
D	260D	261D	262D	263D	264D	265D	266D	267D
E	260E	261E	262E	263E	264E	265E	266E	267E
F	260F	261F	262F	263F	264F	265F	266F	267F

G = 00
P = 00

Table 79 - Row 26: Miscellaneous Symbols





















HEX	NAME	HEX	NAME
2600	BLACK SUN WITH RAYS	265D	BLACK CHESS BISHOP
2601	CLOUD	265E	BLACK CHESS KNIGHT
2602	UMBRELLA	265F	BLACK CHESS PAWN
2603	SNOWMAN	2660	BLACK SPADE SUIT
2604	COMET	2661	WHITE HEART SUIT
2605	BLACK STAR	2662	WHITE DIAMOND SUIT
2606	WHITE STAR	2663	BLACK CLUB SUIT
2607	LIGHTNING	2664	WHITE SPADE SUIT
2608	THUNDERSTORM	2665	BLACK HEART SUIT
2609	SUN	2666	BLACK DIAMOND SUIT
260A	ASCENDING NODE	2667	WHITE CLUB SUIT
260B	DESCENDING NODE	2668	HOT SPRINGS
260C	CONJUNCTION	2669	QUARTER NOTE
260D	OPPOSITION	266A	EIGHTH NOTE
260E	BLACK TELEPHONE	266B	BEAMED EIGHTH NOTES
260F	WHITE TELEPHONE	266C	BEAMED SIXTEENTH NOTES
2610	BALLOT BOX	266D	MUSIC FLAT SIGN
2611	BALLOT BOX WITH CHECK	266E	MUSIC NATURAL SIGN
2612	BALLOT BOX WITH X	266F	MUSIC SHARP SIGN
2613	SALTIRE	2670	WEST SYRIAC CROSS
2614	UMBRELLA WITH RAIN DROPS	2671	EAST SYRIAC CROSS
2615	HOT BEVERAGE	2672	UNIVERSAL RECYCLING SYMBOL
2616	WHITE SHOJI PIECE	2673	RECYCLING SYMBOL FOR TYPE-1 PLASTICS (pete)
2617	BLACK SHOJI PIECE	2674	RECYCLING SYMBOL FOR TYPE-2 PLASTICS (hdpe)
2618	(This position shall not be used)	2675	RECYCLING SYMBOL FOR TYPE-3 PLASTICS (pvc)
2619	REVERSED ROTATED FLORAL HEART BULLET	2676	RECYCLING SYMBOL FOR TYPE-4 PLASTICS (ldpe)
261A	BLACK LEFT POINTING INDEX	2677	RECYCLING SYMBOL FOR TYPE-5 PLASTICS (pp)
261B	BLACK RIGHT POINTING INDEX	2678	RECYCLING SYMBOL FOR TYPE-6 PLASTICS (ps)
261C	WHITE LEFT POINTING INDEX	2679	RECYCLING SYMBOL FOR TYPE-7 PLASTICS (other)
261D	WHITE UP POINTING INDEX	267A	RECYCLING SYMBOL FOR GENERIC MATERIALS
261E	WHITE RIGHT POINTING INDEX	267B	BLACK UNIVERSAL RECYCLING SYMBOL
261F	WHITE DOWN POINTING INDEX	267C	RECYCLED PAPER SYMBOL
2620	SKULL AND CROSSBONES	267D	PARTIALLY-RECYCLED PAPER SYMBOL
2621	CAUTION SIGN	267E	(This position shall not be used)
2622	RADIOACTIVE SIGN	267F	(This position shall not be used)
2623	BIOHAZARD SIGN		
2624	CADUCEUS		
2625	ANKH		
2626	ORTHODOX CROSS		
2627	CHI RHO		
2628	CROSS OF LORRAINE		
2629	CROSS OF JERUSALEM		
262A	STAR AND CRESCENT		
262B	FARSI SYMBOL		
262C	ADI SHAKTI		
262D	HAMMER AND SICKLE		
262E	PEACE SYMBOL		
262F	YIN YANG		
2630	TRIGRAM FOR HEAVEN		
2631	TRIGRAM FOR LAKE		
2632	TRIGRAM FOR FIRE		
2633	TRIGRAM FOR THUNDER		
2634	TRIGRAM FOR WIND		
2635	TRIGRAM FOR WATER		
2636	TRIGRAM FOR MOUNTAIN		
2637	TRIGRAM FOR EARTH		
2638	WHEEL OF DHARMA		
2639	WHITE FROWNING FACE		
263A	WHITE SMILING FACE		
263B	BLACK SMILING FACE		
263C	WHITE SUN WITH RAYS		
263D	FIRST QUARTER MOON		
263E	LAST QUARTER MOON		
263F	MERCURY		
2640	FEMALE SIGN		
2641	EARTH		
2642	MALE SIGN		
2643	JUPITER		
2644	SATURN		
2645	URANUS		
2646	NEPTUNE		
2647	PLUTO		
2648	ARIES		
2649	TAURUS		
264A	GEMINI		
264B	CANCER		
264C	LEO		
264D	VIRGO		
264E	LIBRA		
264F	SCORPIUS		
2650	SAGITTARIUS		
2651	CAPRICORN		
2652	AQUARIUS		
2653	PISCES		
2654	WHITE CHESS KING		
2655	WHITE CHESS QUEEN		
2656	WHITE CHESS ROOK		
2657	WHITE CHESS BISHOP		
2658	WHITE CHESS KNIGHT		
2659	WHITE CHESS PAWN		
265A	BLACK CHESS KING		
265B	BLACK CHESS QUEEN		
265C	BLACK CHESS ROOK		

Group 00

Plane 00

Row 26

Table 80 - Row 26: Miscellaneous Symbols

	268	269	26A	26B	26C	26D	26E	26F
0	 2680	 2690	 26A0					
1	 2681	 2691	 26A1					
2	 2682							
3	 2683							
4	 2684							
5	 2685							
6	 2686							
7	 2687							
8	 2688							
9	 2689							
A	 268A							
B	 268B							
C	 268C							
D	 268D							
E	 268E							
F	 268F							

G = 00
P = 00

Table 80 - Row 26: Miscellaneous Symbols















HEX	NAME	HEX	NAME
2680	DIE FACE-1	26DD	(This position shall not be used)
2681	DIE FACE-2	26DE	(This position shall not be used)
2682	DIE FACE-3	26DF	(This position shall not be used)
2683	DIE FACE-4	26E0	(This position shall not be used)
2684	DIE FACE-5	26E1	(This position shall not be used)
2685	DIE FACE-6	26E2	(This position shall not be used)
2686	WHITE CIRCLE WITH DOT RIGHT	26E3	(This position shall not be used)
2687	WHITE CIRCLE WITH TWO DOTS	26E4	(This position shall not be used)
2688	BLACK CIRCLE WITH WHITE DOT RIGHT	26E5	(This position shall not be used)
2689	BLACK CIRCLE WITH TWO WHITE DOTS	26E6	(This position shall not be used)
268A	MONOGRAM FOR YANG	26E7	(This position shall not be used)
268B	MONOGRAM FOR YING	26E8	(This position shall not be used)
268C	DIGRAM FOR GREATER YANG	26E9	(This position shall not be used)
268D	DIGRAM FOR LESSER YIN	26EA	(This position shall not be used)
268E	DIGRAM FOR LESSER YANG	26EB	(This position shall not be used)
268F	DIGRAM FOR GREATER YIN	26EC	(This position shall not be used)
2690	WHITE FLAG	26ED	(This position shall not be used)
2691	BLACK FLAG	26EE	(This position shall not be used)
2692	(This position shall not be used)	26EF	(This position shall not be used)
2693	(This position shall not be used)	26F0	(This position shall not be used)
2694	(This position shall not be used)	26F1	(This position shall not be used)
2695	(This position shall not be used)	26F2	(This position shall not be used)
2696	(This position shall not be used)	26F3	(This position shall not be used)
2697	(This position shall not be used)	26F4	(This position shall not be used)
2698	(This position shall not be used)	26F5	(This position shall not be used)
2699	(This position shall not be used)	26F6	(This position shall not be used)
269A	(This position shall not be used)	26F7	(This position shall not be used)
269B	(This position shall not be used)	26F8	(This position shall not be used)
269C	(This position shall not be used)	26F9	(This position shall not be used)
269D	(This position shall not be used)	26FA	(This position shall not be used)
269E	(This position shall not be used)	26FB	(This position shall not be used)
269F	(This position shall not be used)	26FC	(This position shall not be used)
26A0	WARNING SIGN	26FD	(This position shall not be used)
26A1	HIGH VOLTAGE SIGN	26FE	(This position shall not be used)
26A2	(This position shall not be used)	26FF	(This position shall not be used)
26A3	(This position shall not be used)		
26A4	(This position shall not be used)		
26A5	(This position shall not be used)		
26A6	(This position shall not be used)		
26A7	(This position shall not be used)		
26A8	(This position shall not be used)		
26A9	(This position shall not be used)		
26AA	(This position shall not be used)		
26AB	(This position shall not be used)		
26AC	(This position shall not be used)		
26AD	(This position shall not be used)		
26AE	(This position shall not be used)		
26AF	(This position shall not be used)		
26B0	(This position shall not be used)		
26B1	(This position shall not be used)		
26B2	(This position shall not be used)		
26B3	(This position shall not be used)		
26B4	(This position shall not be used)		
26B5	(This position shall not be used)		
26B6	(This position shall not be used)		
26B7	(This position shall not be used)		
26B8	(This position shall not be used)		
26B9	(This position shall not be used)		
26BA	(This position shall not be used)		
26BB	(This position shall not be used)		
26BC	(This position shall not be used)		
26BD	(This position shall not be used)		
26BE	(This position shall not be used)		
26BF	(This position shall not be used)		
26C0	(This position shall not be used)		
26C1	(This position shall not be used)		
26C2	(This position shall not be used)		
26C3	(This position shall not be used)		
26C4	(This position shall not be used)		
26C5	(This position shall not be used)		
26C6	(This position shall not be used)		
26C7	(This position shall not be used)		
26C8	(This position shall not be used)		
26C9	(This position shall not be used)		
26CA	(This position shall not be used)		
26CB	(This position shall not be used)		
26CC	(This position shall not be used)		
26CD	(This position shall not be used)		
26CE	(This position shall not be used)		
26CF	(This position shall not be used)		
26D0	(This position shall not be used)		
26D1	(This position shall not be used)		
26D2	(This position shall not be used)		
26D3	(This position shall not be used)		
26D4	(This position shall not be used)		
26D5	(This position shall not be used)		
26D6	(This position shall not be used)		
26D7	(This position shall not be used)		
26D8	(This position shall not be used)		
26D9	(This position shall not be used)		
26DA	(This position shall not be used)		
26DB	(This position shall not be used)		
26DC	(This position shall not be used)		

Group 00

Plane 00

Row 26

Table 91 - Row 2B: Miscellaneous Symbols and Arrows

	2B0	2B1	2B2	2B3	2B4	2B5	2B6	2B7
0	 2B00							
1	 2B01							
2	 2B02							
3	 2B03							
4	 2B04							
5	 2B05							
6	 2B06							
7	 2B07							
8	 2B08							
9	 2B09							
A	 2B0A							
B	 2B0B							
C	 2B0C							
D	 2B0D							
E								
F								

G = 00
P = 00

Table 91 - Row 2B: Miscellaneous Symbols and Arrows

HEX	NAME	HEX	NAME
2B00	NORTH EAST WHITE ARROW	2B5D	(This position shall not be used)
2B01	NORTH WEST WHITE ARROW	2B5E	(This position shall not be used)
2B02	SOUTH EAST WHITE ARROW	2B5F	(This position shall not be used)
2B03	SOUTH WEST WHITE ARROW	2B60	(This position shall not be used)
2B04	LEFT RIGHT WHITE ARROW	2B61	(This position shall not be used)
2B05	LEFTWARDS BLACK ARROW	2B62	(This position shall not be used)
2B06	UPWARDS BLACK ARROW	2B63	(This position shall not be used)
2B07	DOWNWARDS BLACK ARROW	2B64	(This position shall not be used)
2B08	NORTH EAST BLACK ARROW	2B65	(This position shall not be used)
2B09	NORTH WEST BLACK ARROW	2B66	(This position shall not be used)
2B0A	SOUTH EAST BLACK ARROW	2B67	(This position shall not be used)
2B0B	SOUTH WEST BLACK ARROW	2B68	(This position shall not be used)
2B0C	LEFT RIGHT BLACK ARROW	2B69	(This position shall not be used)
2B0D	UP DOWN BLACK ARROW	2B6A	(This position shall not be used)
2B0E	(This position shall not be used)	2B6B	(This position shall not be used)
2B0F	(This position shall not be used)	2B6C	(This position shall not be used)
2B10	(This position shall not be used)	2B6D	(This position shall not be used)
2B11	(This position shall not be used)	2B6E	(This position shall not be used)
2B12	(This position shall not be used)	2B6F	(This position shall not be used)
2B13	(This position shall not be used)	2B70	(This position shall not be used)
2B14	(This position shall not be used)	2B71	(This position shall not be used)
2B15	(This position shall not be used)	2B72	(This position shall not be used)
2B16	(This position shall not be used)	2B73	(This position shall not be used)
2B17	(This position shall not be used)	2B74	(This position shall not be used)
2B18	(This position shall not be used)	2B75	(This position shall not be used)
2B19	(This position shall not be used)	2B76	(This position shall not be used)
2B1A	(This position shall not be used)	2B77	(This position shall not be used)
2B1B	(This position shall not be used)	2B78	(This position shall not be used)
2B1C	(This position shall not be used)	2B79	(This position shall not be used)
2B1D	(This position shall not be used)	2B7A	(This position shall not be used)
2B1E	(This position shall not be used)	2B7B	(This position shall not be used)
2B1F	(This position shall not be used)	2B7C	(This position shall not be used)
2B20	(This position shall not be used)	2B7D	(This position shall not be used)
2B21	(This position shall not be used)	2B7E	(This position shall not be used)
2B22	(This position shall not be used)	2B7F	(This position shall not be used)
2B23	(This position shall not be used)		
2B24	(This position shall not be used)		
2B25	(This position shall not be used)		
2B26	(This position shall not be used)		
2B27	(This position shall not be used)		
2B28	(This position shall not be used)		
2B29	(This position shall not be used)		
2B2A	(This position shall not be used)		
2B2B	(This position shall not be used)		
2B2C	(This position shall not be used)		
2B2D	(This position shall not be used)		
2B2E	(This position shall not be used)		
2B2F	(This position shall not be used)		
2B30	(This position shall not be used)		
2B31	(This position shall not be used)		
2B32	(This position shall not be used)		
2B33	(This position shall not be used)		
2B34	(This position shall not be used)		
2B35	(This position shall not be used)		
2B36	(This position shall not be used)		
2B37	(This position shall not be used)		
2B38	(This position shall not be used)		
2B39	(This position shall not be used)		
2B3A	(This position shall not be used)		
2B3B	(This position shall not be used)		
2B3C	(This position shall not be used)		
2B3D	(This position shall not be used)		
2B3E	(This position shall not be used)		
2B3F	(This position shall not be used)		
2B40	(This position shall not be used)		
2B41	(This position shall not be used)		
2B42	(This position shall not be used)		
2B43	(This position shall not be used)		
2B44	(This position shall not be used)		
2B45	(This position shall not be used)		
2B46	(This position shall not be used)		
2B47	(This position shall not be used)		
2B48	(This position shall not be used)		
2B49	(This position shall not be used)		
2B4A	(This position shall not be used)		
2B4B	(This position shall not be used)		
2B4C	(This position shall not be used)		
2B4D	(This position shall not be used)		
2B4E	(This position shall not be used)		
2B4F	(This position shall not be used)		
2B50	(This position shall not be used)		
2B51	(This position shall not be used)		
2B52	(This position shall not be used)		
2B53	(This position shall not be used)		
2B54	(This position shall not be used)		
2B55	(This position shall not be used)		
2B56	(This position shall not be used)		
2B57	(This position shall not be used)		
2B58	(This position shall not be used)		
2B59	(This position shall not be used)		
2B5A	(This position shall not be used)		
2B5B	(This position shall not be used)		
2B5C	(This position shall not be used)		

Group 00

Plane 00

Row 2B

Table 104 - Row 32: Enclosed CJK Letters and Months

	320	321	322	323	324	325	326	327
0	(ㄱ) 3200	(다) 3210	(一) 3220	(日) 3230	(祭) 3240	PTE 3250	(ㄱ) 3260	(다) 3270
1	(ㄴ) 3201	(라) 3211	(二) 3221	(株) 3231	(休) 3241	(㉑) 3251	(ㄴ) 3261	(라) 3271
2	(ㄷ) 3202	(마) 3212	(三) 3222	(有) 3232	(自) 3242	(㉒) 3252	(ㄷ) 3262	(마) 3272
3	(ㄹ) 3203	(바) 3213	(四) 3223	(社) 3233	(至) 3243	(㉓) 3253	(ㄹ) 3263	(바) 3273
4	(ㄴ) 3204	(사) 3214	(五) 3224	(名) 3234		(㉔) 3254	(ㄴ) 3264	(사) 3274
5	(ㄷ) 3205	(아) 3215	(六) 3225	(特) 3235		(㉕) 3255	(ㄷ) 3265	(아) 3275
6	(ㄷ) 3206	(자) 3216	(七) 3226	(財) 3236		(㉖) 3256	(ㄷ) 3266	(자) 3276
7	(ㅇ) 3207	(차) 3217	(八) 3227	(祝) 3237		(㉗) 3257	(ㅇ) 3267	(차) 3277
8	(ㅈ) 3208	(카) 3218	(九) 3228	(勞) 3238		(㉘) 3258	(ㅈ) 3268	(카) 3278
9	(ㅊ) 3209	(타) 3219	(十) 3229	(代) 3239		(㉙) 3259	(ㅊ) 3269	(타) 3279
A	(ㅋ) 320A	(파) 321A	(月) 322A	(呼) 323A		(㉚) 325A	(ㅋ) 326A	(파) 327A
B	(ㅌ) 320B	(하) 321B	(火) 322B	(学) 323B		(㉛) 325B	(ㅌ) 326B	(하) 327B
C	(ㄹ) 320C	(주) 321C	(水) 322C	(監) 323C		(㉜) 325C	(ㄹ) 326C	참고 327C
D	(ㅎ) 320D	오전 321D	(木) 322D	(企) 323D		(㉝) 325D	(ㅎ) 326D	주의 327D
E	(가) 320E	오후 321E	(金) 322E	(資) 323E		(㉞) 325E	(가) 326E	
F	(나) 320F		(土) 322F	(協) 323F		(㉟) 325F	(나) 326F	ㄱ 327F

G = 00
P = 00

Table 104 - Row 32: Enclosed CJK Letters and Months

HEX	NAME	HEX	NAME
3200	PARENTHESIZED HANGUL KIYEOK	325D	CIRCLED NUMBER THIRTY THREE
3201	PARENTHESIZED HANGUL NIEUN	325E	CIRCLED NUMBER THIRTY FOUR
3202	PARENTHESIZED HANGUL TKEUT	325F	CIRCLED NUMBER THIRTY FIVE
3203	PARENTHESIZED HANGUL RIEUL	3260	CIRCLED HANGUL KIYEOK
3204	PARENTHESIZED HANGUL MIEUM	3261	CIRCLED HANGUL NIEUN
3205	PARENTHESIZED HANGUL PIEUP	3262	CIRCLED HANGUL TKEUT
3206	PARENTHESIZED HANGUL SIOS	3263	CIRCLED HANGUL RIEUL
3207	PARENTHESIZED HANGUL IEUNG	3264	CIRCLED HANGUL MIEUM
3208	PARENTHESIZED HANGUL CIEUC	3265	CIRCLED HANGUL PIEUP
3209	PARENTHESIZED HANGUL CHIEUCH	3266	CIRCLED HANGUL SIOS
320A	PARENTHESIZED HANGUL KHIEUKH	3267	CIRCLED HANGUL IEUNG
320B	PARENTHESIZED HANGUL THIEUTH	3268	CIRCLED HANGUL CIEUC
320C	PARENTHESIZED HANGUL PHIEUPH	3269	CIRCLED HANGUL CHIEUCH
320D	PARENTHESIZED HANGUL HIEUH	326A	CIRCLED HANGUL KHIEUKH
320E	PARENTHESIZED HANGUL KIYEOK A	326B	CIRCLED HANGUL THIEUTH
320F	PARENTHESIZED HANGUL NIEUN A	326C	CIRCLED HANGUL PHIEUPH
3210	PARENTHESIZED HANGUL TKEUT A	326D	CIRCLED HANGUL HIEUH
3211	PARENTHESIZED HANGUL RIEUL A	326E	CIRCLED HANGUL KIYEOK A
3212	PARENTHESIZED HANGUL MIEUM A	326F	CIRCLED HANGUL NIEUN A
3213	PARENTHESIZED HANGUL PIEUP A	3270	CIRCLED HANGUL TKEUT A
3214	PARENTHESIZED HANGUL SIOS A	3271	CIRCLED HANGUL RIEUL A
3215	PARENTHESIZED HANGUL IEUNG A	3272	CIRCLED HANGUL MIEUM A
3216	PARENTHESIZED HANGUL CIEUC A	3273	CIRCLED HANGUL PIEUP A
3217	PARENTHESIZED HANGUL CHIEUCH A	3274	CIRCLED HANGUL SIOS A
3218	PARENTHESIZED HANGUL KHIEUKH A	3275	CIRCLED HANGUL IEUNG A
3219	PARENTHESIZED HANGUL THIEUTH A	3276	CIRCLED HANGUL CIEUC A
321A	PARENTHESIZED HANGUL PHIEUPH A	3277	CIRCLED HANGUL CHIEUCH A
321B	PARENTHESIZED HANGUL HIEUH A	3278	CIRCLED HANGUL KHIEUKH A
321C	PARENTHESIZED HANGUL CIEUC U	3279	CIRCLED HANGUL THIEUTH A
321D	PARENTHESIZED KOREAN CHARACTER OJEON	327A	CIRCLED HANGUL PHIEUPH A
321E	PARENTHESIZED KOREAN CHARACTER O HU	327B	CIRCLED HANGUL HIEUH A
321F	(This position shall not be used)	327C	CIRLED KOREAN CHARACTER CHAMKO
3220	PARENTHESIZED IDEOGRAPH ONE	327D	CIRLED KOREAN CHARACTER JUEUI
3221	PARENTHESIZED IDEOGRAPH TWO	327E	(This position shall not be used)
3222	PARENTHESIZED IDEOGRAPH THREE	327F	KOREAN STANDARD SYMBOL
3223	PARENTHESIZED IDEOGRAPH FOUR		
3224	PARENTHESIZED IDEOGRAPH FIVE		
3225	PARENTHESIZED IDEOGRAPH SIX		
3226	PARENTHESIZED IDEOGRAPH SEVEN		
3227	PARENTHESIZED IDEOGRAPH EIGHT		
3228	PARENTHESIZED IDEOGRAPH NINE		
3229	PARENTHESIZED IDEOGRAPH TEN		
322A	PARENTHESIZED IDEOGRAPH MOON		
322B	PARENTHESIZED IDEOGRAPH FIRE		
322C	PARENTHESIZED IDEOGRAPH WATER		
322D	PARENTHESIZED IDEOGRAPH WOOD		
322E	PARENTHESIZED IDEOGRAPH METAL		
322F	PARENTHESIZED IDEOGRAPH EARTH		
3230	PARENTHESIZED IDEOGRAPH SUN		
3231	PARENTHESIZED IDEOGRAPH STOCK		
3232	PARENTHESIZED IDEOGRAPH HAVE		
3233	PARENTHESIZED IDEOGRAPH SOCIETY		
3234	PARENTHESIZED IDEOGRAPH NAME		
3235	PARENTHESIZED IDEOGRAPH SPECIAL		
3236	PARENTHESIZED IDEOGRAPH FINANCIAL		
3237	PARENTHESIZED IDEOGRAPH CONGRATULATION		
3238	PARENTHESIZED IDEOGRAPH LABOR		
3239	PARENTHESIZED IDEOGRAPH REPRESENT		
323A	PARENTHESIZED IDEOGRAPH CALL		
323B	PARENTHESIZED IDEOGRAPH STUDY		
323C	PARENTHESIZED IDEOGRAPH SUPERVISE		
323D	PARENTHESIZED IDEOGRAPH ENTERPRISE		
323E	PARENTHESIZED IDEOGRAPH RESOURCE		
323F	PARENTHESIZED IDEOGRAPH ALLIANCE		
3240	PARENTHESIZED IDEOGRAPH FESTIVAL		
3241	PARENTHESIZED IDEOGRAPH REST		
3242	PARENTHESIZED IDEOGRAPH SELF		
3243	PARENTHESIZED IDEOGRAPH REACH		
3244	(This position shall not be used)		
3245	(This position shall not be used)		
3246	(This position shall not be used)		
3247	(This position shall not be used)		
3248	(This position shall not be used)		
3249	(This position shall not be used)		
324A	(This position shall not be used)		
324B	(This position shall not be used)		
324C	(This position shall not be used)		
324D	(This position shall not be used)		
324E	(This position shall not be used)		
324F	(This position shall not be used)		
3250	PARTNERSHIP SIGN		
3251	CIRCLED NUMBER TWENTY ONE		
3252	CIRCLED NUMBER TWENTY TWO		
3253	CIRCLED NUMBER TWENTY THREE		
3254	CIRCLED NUMBER TWENTY FOUR		
3255	CIRCLED NUMBER TWENTY FIVE		
3256	CIRCLED NUMBER TWENTY SIX		
3257	CIRCLED NUMBER TWENTY SEVEN		
3258	CIRCLED NUMBER TWENTY EIGHT		
3259	CIRCLED NUMBER TWENTY NINE		
325A	CIRCLED NUMBER THIRTY		
325B	CIRCLED NUMBER THIRTY ONE		
325C	CIRCLED NUMBER THIRTY TWO		

Table 105 - Row 32: Enclosed CJK Letters and Months

	328	329	32A	32B	32C	32D	32E	32F
0	一 3280	日 3290	項 32A0	夜 32B0	1月 32C0	ア 32D0	チ 32E0	ム 32F0
1	二 3281	株 3291	休 32A1	36 32B1	2月 32C1	イ 32D1	ツ 32E1	メ 32F1
2	三 3282	有 3292	写 32A2	37 32B2	3月 32C2	ウ 32D2	テ 32E2	モ 32F2
3	四 3283	社 3293	正 32A3	38 32B3	4月 32C3	エ 32D3	ト 32E3	ヤ 32F3
4	五 3284	名 3294	上 32A4	39 32B4	5月 32C4	オ 32D4	ナ 32E4	ユ 32F4
5	六 3285	特 3295	中 32A5	40 32B5	6月 32C5	カ 32D5	ニ 32E5	ヨ 32F5
6	七 3286	財 3296	下 32A6	41 32B6	7月 32C6	キ 32D6	ヌ 32E6	ラ 32F6
7	八 3287	祝 3297	左 32A7	42 32B7	8月 32C7	ク 32D7	ネ 32E7	リ 32F7
8	九 3288	労 3298	右 32A8	43 32B8	9月 32C8	ケ 32D8	ノ 32E8	ル 32F8
9	十 3289	秘 3299	医 32A9	44 32B9	10月 32C9	コ 32D9	ハ 32E9	レ 32F9
A	月 328A	男 329A	宗 32AA	45 32BA	11月 32CA	サ 32DA	ヒ 32EA	ロ 32FA
B	火 328B	女 329B	学 32AB	46 32BB	12月 32CB	シ 32DB	フ 32EB	ワ 32FB
C	水 328C	適 329C	監 32AC	47 32BC	Hg 32CC	ス 32DC	ヘ 32EC	井 32FC
D	木 328D	優 329D	企 32AD	48 32BD	erg 32CD	セ 32DD	ホ 32ED	エ 32FD
E	金 328E	印 329E	資 32AE	49 32BE	eV 32CE	ソ 32DE	マ 32EE	ヲ 32FE
F	土 328F	注 329F	協 32AF	50 32BF	LTD 32CF	夕 32DF	ミ 32EF	

G = 00
P = 00

Table 105 - Row 32: Enclosed CJK Letters and Months

HEX	NAME	HEX	NAME
3280	CIRCLED IDEOGRAPH ONE	32DD	CIRCLED KATAKANA SE
3281	CIRCLED IDEOGRAPH TWO	32DE	CIRCLED KATAKANA SO
3282	CIRCLED IDEOGRAPH THREE	32DF	CIRCLED KATAKANA TA
3283	CIRCLED IDEOGRAPH FOUR	32E0	CIRCLED KATAKANA TI
3284	CIRCLED IDEOGRAPH FIVE	32E1	CIRCLED KATAKANA TU
3285	CIRCLED IDEOGRAPH SIX	32E2	CIRCLED KATAKANA TE
3286	CIRCLED IDEOGRAPH SEVEN	32E3	CIRCLED KATAKANA TO
3287	CIRCLED IDEOGRAPH EIGHT	32E4	CIRCLED KATAKANA NA
3288	CIRCLED IDEOGRAPH NINE	32E5	CIRCLED KATAKANA NI
3289	CIRCLED IDEOGRAPH TEN	32E6	CIRCLED KATAKANA NU
328A	CIRCLED IDEOGRAPH MOON	32E7	CIRCLED KATAKANA NE
328B	CIRCLED IDEOGRAPH FIRE	32E8	CIRCLED KATAKANA NO
328C	CIRCLED IDEOGRAPH WATER	32E9	CIRCLED KATAKANA HA
328D	CIRCLED IDEOGRAPH WOOD	32EA	CIRCLED KATAKANA HI
328E	CIRCLED IDEOGRAPH METAL	32EB	CIRCLED KATAKANA HU
328F	CIRCLED IDEOGRAPH EARTH	32EC	CIRCLED KATAKANA HE
3290	CIRCLED IDEOGRAPH SUN	32ED	CIRCLED KATAKANA HO
3291	CIRCLED IDEOGRAPH STOCK	32EE	CIRCLED KATAKANA MA
3292	CIRCLED IDEOGRAPH HAVE	32EF	CIRCLED KATAKANA MI
3293	CIRCLED IDEOGRAPH SOCIETY	32F0	CIRCLED KATAKANA MU
3294	CIRCLED IDEOGRAPH NAME	32F1	CIRCLED KATAKANA ME
3295	CIRCLED IDEOGRAPH SPECIAL	32F2	CIRCLED KATAKANA MO
3296	CIRCLED IDEOGRAPH FINANCIAL	32F3	CIRCLED KATAKANA YA
3297	CIRCLED IDEOGRAPH CONGRATULATION	32F4	CIRCLED KATAKANA YU
3298	CIRCLED IDEOGRAPH LABOR	32F5	CIRCLED KATAKANA YO
3299	CIRCLED IDEOGRAPH SECRET	32F6	CIRCLED KATAKANA RA
329A	CIRCLED IDEOGRAPH MALE	32F7	CIRCLED KATAKANA RI
329B	CIRCLED IDEOGRAPH FEMALE	32F8	CIRCLED KATAKANA RU
329C	CIRCLED IDEOGRAPH SUITABLE	32F9	CIRCLED KATAKANA RE
329D	CIRCLED IDEOGRAPH EXCELLENT	32FA	CIRCLED KATAKANA RO
329E	CIRCLED IDEOGRAPH PRINT	32FB	CIRCLED KATAKANA WA
329F	CIRCLED IDEOGRAPH ATTENTION	32FC	CIRCLED KATAKANA WI
32A0	CIRCLED IDEOGRAPH ITEM	32FD	CIRCLED KATAKANA WE
32A1	CIRCLED IDEOGRAPH REST	32FE	CIRCLED KATAKANA WO
32A2	CIRCLED IDEOGRAPH COPY	32FF	(This position shall not be used)
32A3	CIRCLED IDEOGRAPH CORRECT		
32A4	CIRCLED IDEOGRAPH HIGH		
32A5	CIRCLED IDEOGRAPH CENTRE		
32A6	CIRCLED IDEOGRAPH LOW		
32A7	CIRCLED IDEOGRAPH LEFT		
32A8	CIRCLED IDEOGRAPH RIGHT		
32A9	CIRCLED IDEOGRAPH MEDICINE		
32AA	CIRCLED IDEOGRAPH RELIGION		
32AB	CIRCLED IDEOGRAPH STUDY		
32AC	CIRCLED IDEOGRAPH SUPERVISE		
32AD	CIRCLED IDEOGRAPH ENTERPRISE		
32AE	CIRCLED IDEOGRAPH RESOURCE		
32AF	CIRCLED IDEOGRAPH ALLIANCE		
32B0	CIRCLED IDEOGRAPH NIGHT		
32B1	CIRCLED NUMBER THIRTY SIX		
32B2	CIRCLED NUMBER THIRTY SEVEN		
32B3	CIRCLED NUMBER THIRTY EIGHT		
32B4	CIRCLED NUMBER THIRTY NINE		
32B5	CIRCLED NUMBER FORTY		
32B6	CIRCLED NUMBER FORTY ONE		
32B7	CIRCLED NUMBER FORTY TWO		
32B8	CIRCLED NUMBER FORTY THREE		
32B9	CIRCLED NUMBER FORTY FOUR		
32BA	CIRCLED NUMBER FORTY FIVE		
32BB	CIRCLED NUMBER FORTY SIX		
32BC	CIRCLED NUMBER FORTY SEVEN		
32BD	CIRCLED NUMBER FORTY EIGHT		
32BE	CIRCLED NUMBER FORTY NINE		
32BF	CIRCLED NUMBER FIFTY		
32C0	IDEOGRAPHIC TELEGRAPH SYMBOL FOR JANUARY		
32C1	IDEOGRAPHIC TELEGRAPH SYMBOL FOR FEBRUARY		
32C2	IDEOGRAPHIC TELEGRAPH SYMBOL FOR MARCH		
32C3	IDEOGRAPHIC TELEGRAPH SYMBOL FOR APRIL		
32C4	IDEOGRAPHIC TELEGRAPH SYMBOL FOR MAY		
32C5	IDEOGRAPHIC TELEGRAPH SYMBOL FOR JUNE		
32C6	IDEOGRAPHIC TELEGRAPH SYMBOL FOR JULY		
32C7	IDEOGRAPHIC TELEGRAPH SYMBOL FOR AUGUST		
32C8	IDEOGRAPHIC TELEGRAPH SYMBOL FOR SEPTEMBER		
32C9	IDEOGRAPHIC TELEGRAPH SYMBOL FOR OCTOBER		
32CA	IDEOGRAPHIC TELEGRAPH SYMBOL FOR NOVEMBER		
32CB	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DECEMBER		
32CC	SQUARE HG		
32CD	SQUARE ERG		
32CE	SQUARE EV		
32CF	LIMITED LIABILITY SIGN		
32D0	CIRCLED KATAKANA A		
32D1	CIRCLED KATAKANA I		
32D2	CIRCLED KATAKANA U		
32D3	CIRCLED KATAKANA E		
32D4	CIRCLED KATAKANA O		
32D5	CIRCLED KATAKANA KA		
32D6	CIRCLED KATAKANA KI		
32D7	CIRCLED KATAKANA KU		
32D8	CIRCLED KATAKANA KE		
32D9	CIRCLED KATAKANA KO		
32DA	CIRCLED KATAKANA SA		
32DB	CIRCLED KATAKANA SI		
32DC	CIRCLED KATAKANA SU		

Table 106 - Row 33: CJK Compatibility

	330	331	332	333	334	335	336	337
0	アパート 3300	ギガ 3310	サンチーム 3320	ピコ 3330	ポンド 3340	ユアン 3350	8点 3360	24点 3370
1	アルファ 3301	ギニー 3311	シリリング 3321	ビル 3331	ホール 3341	リットル 3351	9点 3361	hPa 3371
2	アンペア 3302	キュリー 3312	センチ 3322	ファラッド 3332	ホン 3342	リラ 3352	10点 3362	da 3372
3	アール 3303	ギルダー 3313	セント 3323	フィート 3333	マイクロ 3343	ルピー 3353	11点 3363	AU 3373
4	インゲ 3304	キロ 3314	ダース 3324	ブッセル 3334	マイル 3344	ルーブル 3354	12点 3364	bar 3374
5	インチ 3305	キログラム 3315	デシ 3325	フラン 3335	マツハ 3345	レム 3355	13点 3365	oV 3375
6	ウオン 3306	キロメートル 3316	ドル 3326	ヘクタール 3336	マルク 3346	レントゲン 3356	14点 3366	pc 3376
7	エスケード 3307	キロワット 3317	トン 3327	ペソ 3337	マンション 3347	ワット 3357	15点 3367	dm 3377
8	エーカー 3308	グラム 3318	ナノ 3328	ペニヒ 3338	ミクロン 3348	0点 3358	16点 3368	dm ² 3378
9	オンス 3309	グラムトン 3319	ノット 3329	ヘルツ 3339	ミリ 3349	1点 3359	17点 3369	dm ³ 3379
A	オーム 330A	クルゼイロ 331A	ハイツ 332A	ペンス 333A	ミリバール 334A	2点 335A	18点 336A	IU 337A
B	カイリ 330B	クローネ 331B	パーセント 332B	ページ 333B	メガ 334B	3点 335B	19点 336B	平成 337B
C	カラット 330C	ケース 331C	パーツ 332C	ベータ 333C	メガトン 334C	4点 335C	20点 336C	昭和 337C
D	カロリー 330D	コルナ 331D	バーレル 332D	ポイント 333D	メートル 334D	5点 335D	21点 336D	大正 337D
E	ガロン 330E	コーポ 331E	ピアストル 332E	ボルト 333E	ヤード 334E	6点 335E	22点 336E	明治 337E
F	ガンマ 330F	サイクル 331F	ピクル 332F	ホン 333F	ヤール 334F	7点 335F	23点 336F	株式会社 337F

G = 00
P = 00

Table 106 - Row 33: CJK Compatibility

HEX	NAME	HEX	NAME
3300	SQUARE APAATO	335D	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR FIVE
3301	SQUARE ARUHUA	335E	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR SIX
3302	SQUARE ANPEA	335F	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR SEVEN
3303	SQUARE AARU	3360	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR EIGHT
3304	SQUARE ININGU	3361	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR NINE
3305	SQUARE INTI	3362	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TEN
3306	SQUARE UON	3363	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR ELEVEN
3307	SQUARE ESUKUUDO	3364	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWELVE
3308	SQUARE EEKAA	3365	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR THIRTEEN
3309	SQUARE ONSU	3366	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR FOURTEEN
330A	SQUARE OOMU	3367	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR FIFTEEN
330B	SQUARE KAIRI	3368	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR SIXTEEN
330C	SQUARE KARATTO	3369	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR SEVENTEEN
330D	SQUARE KARORII	336A	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR EIGHTEEN
330E	SQUARE GARON	336B	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR NINETEEN
330F	SQUARE GANMA	336C	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWENTY
3310	SQUARE GIGA	336D	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWENTY-ONE
3311	SQUARE GINII	336E	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWENTY-TWO
3312	SQUARE KYURII	336F	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWENTY-THREE
3313	SQUARE GIRUDAA	3370	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWENTY-FOUR
3314	SQUARE KIRO	3371	SQUARE HPA
3315	SQUARE KIROGURAMU	3372	SQUARE DA
3316	SQUARE KIROMEETORU	3373	SQUARE AU
3317	SQUARE KIROWATTO	3374	SQUARE BAR
3318	SQUARE GURAMU	3375	SQUARE OV
3319	SQUARE GURAMUTON	3376	SQUARE PC
331A	SQUARE KURUZEIRO	3377	SQUARE DM
331B	SQUARE KUROONE	3378	SQUARE DM SQUARED
331C	SQUARE KEESU	3379	SQUARE DM CUBED
331D	SQUARE KORUNA	337A	SQUARE IU
331E	SQUARE KOOPO	337B	SQUARE ERA NAME HEISEI
331F	SQUARE SAIKURU	337C	SQUARE ERA NAME SYOUWA
3320	SQUARE SANTIMU	337D	SQUARE ERA NAME TAISYOU
3321	SQUARE SIRINGU	337E	SQUARE ERA NAME MEIZI
3322	SQUARE SENTI	337F	SQUARE CORPORATION
3323	SQUARE SENTO		
3324	SQUARE DAASU		
3325	SQUARE DESI		
3326	SQUARE DORU		
3327	SQUARE TON		
3328	SQUARE NANO		
3329	SQUARE NOTTO		
332A	SQUARE HAITU		
332B	SQUARE PAASENTO		
332C	SQUARE PAATU		
332D	SQUARE BAARERU		
332E	SQUARE PIASUTORU		
332F	SQUARE PIKURU		
3330	SQUARE PIKO		
3331	SQUARE BIRU		
3332	SQUARE HUARADDO		
3333	SQUARE HUIITO		
3334	SQUARE BUSSYERU		
3335	SQUARE HURAN		
3336	SQUARE HEKUTAARU		
3337	SQUARE PESO		
3338	SQUARE PENIHI		
3339	SQUARE HERUTU		
333A	SQUARE PENSU		
333B	SQUARE PEEZI		
333C	SQUARE BEETA		
333D	SQUARE POINTO		
333E	SQUARE BORUTO		
333F	SQUARE HON		
3340	SQUARE PONDO		
3341	SQUARE HOORU		
3342	SQUARE HOON		
3343	SQUARE MAIKURO		
3344	SQUARE MAIRU		
3345	SQUARE MAHHA		
3346	SQUARE MARUKU		
3347	SQUARE MANSYON		
3348	SQUARE MIKURON		
3349	SQUARE MIRI		
334A	SQUARE MIRIBAARU		
334B	SQUARE MEGA		
334C	SQUARE MEGATON		
334D	SQUARE MEETORU		
334E	SQUARE YAADO		
334F	SQUARE YAARU		
3350	SQUARE YUAN		
3351	SQUARE RITTORU		
3352	SQUARE RIRA		
3353	SQUARE RUPII		
3354	SQUARE RUUBURU		
3355	SQUARE REMU		
3356	SQUARE RENTOGEN		
3357	SQUARE WATTO		
3358	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR ZERO		
3359	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR ONE		
335A	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR TWO		
335B	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR THREE		
335C	IDEOGRAPHIC TELEGRAPH SYMBOL FOR HOUR FOUR		

Group 00

Plane 00

Row 33

Table 107 - Row 33: CJK Compatibility

	338	339	33A	33B	33C	33D	33E	33F
0	pA 3380	Hz 3390	cm ² 33A0	ps 33B0	kΩ 33C0	lm 33D0	1日 33E0	17日 33F0
1	nA 3381	kHz 3391	m ² 33A1	ns 33B1	MΩ 33C1	ln 33D1	2日 33E1	18日 33F1
2	μA 3382	MHz 3392	km ² 33A2	μs 33B2	a.m. 33C2	log 33D2	3日 33E2	19日 33F2
3	mA 3383	GHz 3393	mm ³ 33A3	ms 33B3	Bq 33C3	lx 33D3	4日 33E3	20日 33F3
4	kA 3384	THz 3394	cm ³ 33A4	pV 33B4	cc 33C4	mb 33D4	5日 33E4	21日 33F4
5	KB 3385	μl 3395	m ³ 33A5	nV 33B5	cd 33C5	mil 33D5	6日 33E5	22日 33F5
6	MB 3386	Me 3396	km ³ 33A6	μV 33B6	C/kg 33C6	mol 33D6	7日 33E6	23日 33F6
7	GB 3387	dℓ 3397	m/s 33A7	mV 33B7	Co. 33C7	pH 33D7	8日 33E7	24日 33F7
8	cal 3388	kl 3398	m/s ² 33A8	kV 33B8	dB 33C8	p.m. 33D8	9日 33E8	25日 33F8
9	kcal 3389	fm 3399	Pa 33A9	MV 33B9	Gy 33C9	PPM 33D9	10日 33E9	26日 33F9
A	pF 338A	nm 339A	kPa 33AA	pW 33BA	ha 33CA	PR 33DA	11日 33EA	27日 33FA
B	nF 338B	μm 339B	MPa 33AB	nW 33BB	HP 33CB	sr 33DB	12日 33EB	28日 33FB
C	μF 338C	mm 339C	GPa 33AC	μW 33BC	in 33CC	Sv 33DC	13日 33EC	29日 33FC
D	μg 338D	cm 339D	rad 33AD	mW 33BD	K.K. 33CD	Wb 33DD	14日 33ED	30日 33FD
E	mg 338E	km 339E	rad/s 33AE	kW 33BE	KM 33CE	V/m 33DE	15日 33EE	31日 33FE
F	kg 338F	mm ² 339F	rad/s ² 33AF	MW 33BF	kt 33CF	A/m 33DF	16日 33EF	gal 33FF

G = 00
P = 00

Table 107 - Row 33: CJK Compatibility

































































HEX	NAME	HEX	NAME
3380	SQUARE PA AMPS	33DD	SQUARE WB
3381	SQUARE NA	33DE	SQUARE V OVER M
3382	SQUARE MU A	33DF	SQUARE A OVER M
3383	SQUARE MA	33E0	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY ONE
3384	SQUARE KA	33E1	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWO
3385	SQUARE KB	33E2	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY THREE
3386	SQUARE MB	33E3	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY FOUR
3387	SQUARE GB	33E4	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY FIVE
3388	SQUARE CAL	33E5	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY SIX
3389	SQUARE KCAL	33E6	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY SEVEN
338A	SQUARE PF	33E7	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY EIGHT
338B	SQUARE NF	33E8	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY NINE
338C	SQUARE MU F	33E9	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TEN
338D	SQUARE MU G	33EA	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY ELEVEN
338E	SQUARE MG	33EB	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWELVE
338F	SQUARE KG	33EC	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY THIRTEEN
3390	SQUARE HZ	33ED	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY FOURTEEN
3391	SQUARE KHZ	33EE	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY FIFTEEN
3392	SQUARE MHZ	33EF	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY SIXTEEN
3393	SQUARE GHZ	33F0	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY SEVENTEEN
3394	SQUARE THZ	33F1	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY EIGHTEEN
3395	SQUARE MU L	33F2	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY NINETEEN
3396	SQUARE ML	33F3	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY
3397	SQUARE DL	33F4	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-ONE
3398	SQUARE KL	33F5	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-TWO
3399	SQUARE FM	33F6	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-THREE
339A	SQUARE NM	33F7	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-FOUR
339B	SQUARE MU M	33F8	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-FIVE
339C	SQUARE MM	33F9	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-SIX
339D	SQUARE CM	33FA	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-SEVEN
339E	SQUARE KM	33FB	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-EIGHT
339F	SQUARE MM SQUARED	33FC	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY TWENTY-NINE
33A0	SQUARE CM SQUARED	33FD	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY THIRTY
33A1	SQUARE M SQUARED	33FE	IDEOGRAPHIC TELEGRAPH SYMBOL FOR DAY THIRTY-ONE
33A2	SQUARE KM SQUARED	33FF	SQUARE GAL
33A3	SQUARE MM CUBED		
33A4	SQUARE CM CUBED		
33A5	SQUARE M CUBED		
33A6	SQUARE KM CUBED		
33A7	SQUARE M OVER S		
33A8	SQUARE M OVER S SQUARED		
33A9	SQUARE PA		
33AA	SQUARE KPA		
33AB	SQUARE MPA		
33AC	SQUARE GPA		
33AD	SQUARE RAD		
33AE	SQUARE RAD OVER S		
33AF	SQUARE RAD OVER S SQUARED		
33B0	SQUARE PS		
33B1	SQUARE NS		
33B2	SQUARE MU S		
33B3	SQUARE MS		
33B4	SQUARE PV		
33B5	SQUARE NV		
33B6	SQUARE MU V		
33B7	SQUARE MV		
33B8	SQUARE KV		
33B9	SQUARE MV MEGA		
33BA	SQUARE PW		
33BB	SQUARE NW		
33BC	SQUARE MU W		
33BD	SQUARE MW		
33BE	SQUARE KW		
33BF	SQUARE MW MEGA		
33C0	SQUARE K OHM		
33C1	SQUARE M OHM		
33C2	SQUARE AM		
33C3	SQUARE BQ		
33C4	SQUARE CC		
33C5	SQUARE CD		
33C6	SQUARE C OVER KG		
33C7	SQUARE CO		
33C8	SQUARE DB		
33C9	SQUARE GY		
33CA	SQUARE HA		
33CB	SQUARE HP		
33CC	SQUARE IN		
33CD	SQUARE KK		
33CE	SQUARE KM CAPITAL		
33CF	SQUARE KT		
33D0	SQUARE LM		
33D1	SQUARE LN		
33D2	SQUARE LOG		
33D3	SQUARE LX		
33D4	SQUARE MB SMALL		
33D5	SQUARE ML		
33D6	SQUARE MOL		
33D7	SQUARE PH		
33D8	SQUARE PM		
33D9	SQUARE PPM		
33DA	SQUARE PR		
33DB	SQUARE SR		
33DC	SQUARE SV		

Group 00

Plane 00

Row 33

Table 108 - Row 4D: Yijing Hexagram Symbols

	4DC	4DD	4DE	4DF
0	 4DC0	 4DD0	 4DE0	 4DF0
1	 4DC1	 4DD1	 4DE1	 4DF1
2	 4DC2	 4DD2	 4DE2	 4DF2
3	 4DC3	 4DD3	 4DE3	 4DF3
4	 4DC4	 4DD4	 4DE4	 4DF4
5	 4DC5	 4DD5	 4DE5	 4DF5
6	 4DC6	 4DD6	 4DE6	 4DF6
7	 4DC7	 4DD7	 4DE7	 4DF7
8	 4DC8	 4DD8	 4DE8	 4DF8
9	 4DC9	 4DD9	 4DE9	 4DF9
A	 4DCA	 4DDA	 4DEA	 4DFA
B	 4DCB	 4ddb	 4DEB	 4DFB
C	 4DCC	 4DDC	 4DEC	 4DFC
D	 4DCD	 4DDD	 4DED	 4DFD
E	 4DCE	 4DDE	 4DEE	 4DFE
F	 4DCF	 4DDF	 4DEF	 4DFE

G = 00
P = 00

Table 108 - Row 4D: Yijing Hexagram Symbols

HEX	NAME	HEX	NAME
4DC0	HEXAGRAM FOR THE CREATIVE HEAVEN		
4DC1	HEXAGRAM FOR THE RECEPTIVE EARTH		
4DC2	HEXAGRAM FOR DIFFICULTY AT THE BEGINNING		
4DC3	HEXAGRAM FOR YOUTHFUL FOLLY		
4DC4	HEXAGRAM FOR WAITING		
4DC5	HEXAGRAM FOR CONFLICT		
4DC6	HEXAGRAM FOR THE ARMY		
4DC7	HEXAGRAM FOR HOLDING TOGETHER		
4DC8	HEXAGRAM FOR SMALL TAMING		
4DC9	HEXAGRAM FOR TREADING		
4DCA	HEXAGRAM FOR PEACE		
4DCB	HEXAGRAM FOR STANDSTILL		
4DCC	HEXAGRAM FOR FELLOWSHIP		
4DCD	HEXAGRAM FOR GREAT POSSESSION		
4DCE	HEXAGRAM FOR MODESTY		
4DCF	HEXAGRAM FOR ENTHUSIASM		
4DD0	HEXAGRAM FOR FOLLOWING		
4DD1	HEXAGRAM FOR WORK ON THE DECAYED		
4DD2	HEXAGRAM FOR APPROACH		
4DD3	HEXAGRAM FOR CONTEMPLATION		
4DD4	HEXAGRAM FOR BITING THROUGH		
4DD5	HEXAGRAM FOR GRACE		
4DD6	HEXAGRAM FOR SPLITTING APART		
4DD7	HEXAGRAM FOR RETURN		
4DD8	HEXAGRAM FOR INNOCENCE		
4DD9	HEXAGRAM FOR GREAT TAMING		
4DDA	HEXAGRAM FOR MOUTH CORNERS		
4ddb	HEXAGRAM FOR GREAT PREPONDERANCE		
4DDC	HEXAGRAM FOR THE ABYSMAL WATER		
4DDD	HEXAGRAM FOR THE CLINGING FIRE		
4DDE	HEXAGRAM FOR INFLUENCE		
4DDF	HEXAGRAM FOR DURATION		
4DE0	HEXAGRAM FOR RETREAT		
4DE1	HEXAGRAM FOR GREAT POWER		
4DE2	HEXAGRAM FOR PROGRESS		
4DE3	HEXAGRAM FOR DARKENING OF THE LIGHT		
4DE4	HEXAGRAM FOR THE FAMILY		
4DE5	HEXAGRAM FOR OPPOSITION		
4DE6	HEXAGRAM FOR OBSTRUCTION		
4DE7	HEXAGRAM FOR DELIVERANCE		
4DE8	HEXAGRAM FOR DECREASE		
4DE9	HEXAGRAM FOR INCREASE		
4DEA	HEXAGRAM FOR BREAKTHROUGH		
4DEB	HEXAGRAM FOR COMING TO MEET		
4DEC	HEXAGRAM FOR GATHERING TOGETHER		
4DED	HEXAGRAM FOR PUSHING UPWARD		
4DEE	HEXAGRAM FOR OPPRESSION		
4DEF	HEXAGRAM FOR THE WELL		
4DF0	HEXAGRAM FOR REVOLUTION		
4DF1	HEXAGRAM FOR THE CAULDRON		
4DF2	HEXAGRAM FOR THE AROUSING THUNDER		
4DF3	HEXAGRAM FOR THE KEEPING STILL MOUNTAIN		
4DF4	HEXAGRAM FOR DEVELOPMENT		
4DF5	HEXAGRAM FOR THE MARRYING MAIDEN		
4DF6	HEXAGRAM FOR ABUNDANCE		
4DF7	HEXAGRAM FOR THE WANDERER		
4DF8	HEXAGRAM FOR THE GENTLE WIND		
4DF9	HEXAGRAM FOR THE JOYOUS LAKE		
4DFA	HEXAGRAM FOR DISPERSION		
4DFB	HEXAGRAM FOR LIMITATION		
4DFC	HEXAGRAM FOR INNER TRUTH		
4DFD	HEXAGRAM FOR SMALL PREPONDERANCE		
4DFE	HEXAGRAM FOR AFTER COMPLETION		
4DFF	HEXAGRAM FOR BEFORE COMPLETION		

Group 00

Plane 00

Row 4D

Table 151 - Row FA: CJK Compatibility Ideographs

	FA6	FA7	FA8	FA9	FAA	FAB	FAC	FAD	FAE	FAF
0	褐 FA60	並 FA70	奄 FA80	慊 FA90	沛 FAA0	瘟 FAB0	鉞 FAC0	贈 FAD0	龐 FAE0	
1	視 FA61	况 FA71	奔 FA81	懲 FA91	流 FAA1	益 FAB1	者 FAC1	輸 FAD1	龜 FAE1	
2	謁 FA62	全 FA72	婢 FA82	戴 FA92	淫 FAA2	盛 FAB2	荒 FAC2	遲 FAD2	慙 FAE2	
3	謹 FA63	俐 FA73	嫵 FA83	掄 FA93	滋 FAA3	直 FAB3	華 FAC3	醜 FAD3	憊 FAE3	
4	賓 FA64	充 FA74	廩 FA84	掄 FA94	漠 FAA4	眈 FAB4	蝮 FAC4	銷 FAD4	梳 FAE4	
5	贈 FA65	冀 FA75	廩 FA85	搜 FA95	澗 FAA5	眈 FAB5	襁 FAC5	鉞 FAD5	狎 FAE5	
6	亼 FA66	勇 FA76	彩 FA86	擗 FA96	灰 FAA6	着 FAB6	覆 FAC6	鋤 FAD6	瞭 FAE6	
7	逸 FA67	勺 FA77	徭 FA87	敖 FA97	煮 FAA7	映 FAB7	視 FAC7	階 FAD7	簡 FAE7	
8	難 FA68	喝 FA78	愉 FA88	晴 FA98	瞧 FAA8	碩 FAB8	調 FAC8	難 FAD8	豨 FAE8	
9	響 FA69	啣 FA79	惘 FA89	朗 FA99	爵 FAA9	褻 FAB9	諸 FAC9	靖 FAD9	赳 FAE9	
A	頻 FA6A	喙 FA7A	慎 FA8A	望 FA9A	犯 FAAA	泮 FABA	請 FACA	鞞 FADA		
B		喙 FA7B	愈 FA8B	杖 FA9B	猪 FAAB	節 FABB	謁 FACB	響 FADB		
C		嘆 FA7C	慈 FA8C	栾 FA9C	瑱 FAAC	粪 FABC	諾 FACC	頤 FADC		
D		器 FA7D	慌 FA8D	榔 FA9D	瓷 FAAD	條 FABD	諭 FACD	頻 FADD		
E		塚 FA7E	憎 FA8E	反 FA9E	画 FAAE	練 FABE	謹 FACE	鬢 FADE		
F		墳 FA7F	傲 FA8F	殺 FA9F	瘰 FAAF	紕 FABF	變 FACF	鯁 FADF		

G = 00
P = 00

Table 151 - Row FA: CJK Compatibility Ideographs

HEX	NAME	HEX	NAME
FA60	CJK COMPATIBILITY IDEOGRAPH-FA60	FABD	CJK COMPATIBILITY IDEOGRAPH-FABD
FA61	CJK COMPATIBILITY IDEOGRAPH-FA61	FABE	CJK COMPATIBILITY IDEOGRAPH-FABE
FA62	CJK COMPATIBILITY IDEOGRAPH-FA62	FABF	CJK COMPATIBILITY IDEOGRAPH-FABF
FA63	CJK COMPATIBILITY IDEOGRAPH-FA63	FAC0	CJK COMPATIBILITY IDEOGRAPH-FAC0
FA64	CJK COMPATIBILITY IDEOGRAPH-FA64	FAC1	CJK COMPATIBILITY IDEOGRAPH-FAC1
FA65	CJK COMPATIBILITY IDEOGRAPH-FA65	FAC2	CJK COMPATIBILITY IDEOGRAPH-FAC2
FA66	CJK COMPATIBILITY IDEOGRAPH-FA66	FAC3	CJK COMPATIBILITY IDEOGRAPH-FAC3
FA67	CJK COMPATIBILITY IDEOGRAPH-FA67	FAC4	CJK COMPATIBILITY IDEOGRAPH-FAC4
FA68	CJK COMPATIBILITY IDEOGRAPH-FA68	FAC5	CJK COMPATIBILITY IDEOGRAPH-FAC5
FA69	CJK COMPATIBILITY IDEOGRAPH-FA69	FAC6	CJK COMPATIBILITY IDEOGRAPH-FAC6
FA6A	CJK COMPATIBILITY IDEOGRAPH-FA6A	FAC7	CJK COMPATIBILITY IDEOGRAPH-FAC7
FA6B	(This position shall not be used)	FAC8	CJK COMPATIBILITY IDEOGRAPH-FAC8
FA6C	(This position shall not be used)	FAC9	CJK COMPATIBILITY IDEOGRAPH-FAC9
FA6D	(This position shall not be used)	FACA	CJK COMPATIBILITY IDEOGRAPH-FACA
FA6E	(This position shall not be used)	FACB	CJK COMPATIBILITY IDEOGRAPH-FACB
FA6F	(This position shall not be used)	FACC	CJK COMPATIBILITY IDEOGRAPH-FACC
FA70	CJK COMPATIBILITY IDEOGRAPH-FA70	FACD	CJK COMPATIBILITY IDEOGRAPH-FACD
FA71	CJK COMPATIBILITY IDEOGRAPH-FA71	FACE	CJK COMPATIBILITY IDEOGRAPH-FACE
FA72	CJK COMPATIBILITY IDEOGRAPH-FA72	FACF	CJK COMPATIBILITY IDEOGRAPH-FACF
FA73	CJK COMPATIBILITY IDEOGRAPH-FA73	FAD0	CJK COMPATIBILITY IDEOGRAPH-FAD0
FA74	CJK COMPATIBILITY IDEOGRAPH-FA74	FAD1	CJK COMPATIBILITY IDEOGRAPH-FAD1
FA75	CJK COMPATIBILITY IDEOGRAPH-FA75	FAD2	CJK COMPATIBILITY IDEOGRAPH-FAD2
FA76	CJK COMPATIBILITY IDEOGRAPH-FA76	FAD3	CJK COMPATIBILITY IDEOGRAPH-FAD3
FA77	CJK COMPATIBILITY IDEOGRAPH-FA77	FAD4	CJK COMPATIBILITY IDEOGRAPH-FAD4
FA78	CJK COMPATIBILITY IDEOGRAPH-FA78	FAD5	CJK COMPATIBILITY IDEOGRAPH-FAD5
FA79	CJK COMPATIBILITY IDEOGRAPH-FA79	FAD6	CJK COMPATIBILITY IDEOGRAPH-FAD6
FA7A	CJK COMPATIBILITY IDEOGRAPH-FA7A	FAD7	CJK COMPATIBILITY IDEOGRAPH-FAD7
FA7B	CJK COMPATIBILITY IDEOGRAPH-FA7B	FAD8	CJK COMPATIBILITY IDEOGRAPH-FAD8
FA7C	CJK COMPATIBILITY IDEOGRAPH-FA7C	FAD9	CJK COMPATIBILITY IDEOGRAPH-FAD9
FA7D	CJK COMPATIBILITY IDEOGRAPH-FA7D	FADA	CJK COMPATIBILITY IDEOGRAPH-FADA
FA7E	CJK COMPATIBILITY IDEOGRAPH-FA7E	FADB	CJK COMPATIBILITY IDEOGRAPH-FADB
FA7F	CJK COMPATIBILITY IDEOGRAPH-FA7F	FADC	CJK COMPATIBILITY IDEOGRAPH-FADC
FA80	CJK COMPATIBILITY IDEOGRAPH-FA80	FADD	CJK COMPATIBILITY IDEOGRAPH-FADD
FA81	CJK COMPATIBILITY IDEOGRAPH-FA81	FADE	CJK COMPATIBILITY IDEOGRAPH-FADE
FA82	CJK COMPATIBILITY IDEOGRAPH-FA82	FADF	CJK COMPATIBILITY IDEOGRAPH-FADF
FA83	CJK COMPATIBILITY IDEOGRAPH-FA83	FAE0	CJK COMPATIBILITY IDEOGRAPH-FAE0
FA84	CJK COMPATIBILITY IDEOGRAPH-FA84	FAE1	CJK COMPATIBILITY IDEOGRAPH-FAE1
FA85	CJK COMPATIBILITY IDEOGRAPH-FA85	FAE2	CJK COMPATIBILITY IDEOGRAPH-FAE2
FA86	CJK COMPATIBILITY IDEOGRAPH-FA86	FAE3	CJK COMPATIBILITY IDEOGRAPH-FAE3
FA87	CJK COMPATIBILITY IDEOGRAPH-FA87	FAE4	CJK COMPATIBILITY IDEOGRAPH-FAE4
FA88	CJK COMPATIBILITY IDEOGRAPH-FA88	FAE5	CJK COMPATIBILITY IDEOGRAPH-FAE5
FA89	CJK COMPATIBILITY IDEOGRAPH-FA89	FAE6	CJK COMPATIBILITY IDEOGRAPH-FAE6
FA8A	CJK COMPATIBILITY IDEOGRAPH-FA8A	FAE7	CJK COMPATIBILITY IDEOGRAPH-FAE7
FA8B	CJK COMPATIBILITY IDEOGRAPH-FA8B	FAE8	CJK COMPATIBILITY IDEOGRAPH-FAE8
FA8C	CJK COMPATIBILITY IDEOGRAPH-FA8C	FAE9	CJK COMPATIBILITY IDEOGRAPH-FAE9
FA8D	CJK COMPATIBILITY IDEOGRAPH-FA8D	FAEA	(This position shall not be used)
FA8E	CJK COMPATIBILITY IDEOGRAPH-FA8E	FAEB	(This position shall not be used)
FA8F	CJK COMPATIBILITY IDEOGRAPH-FA8F	FAEC	(This position shall not be used)
FA90	CJK COMPATIBILITY IDEOGRAPH-FA90	FAED	(This position shall not be used)
FA91	CJK COMPATIBILITY IDEOGRAPH-FA91	FAEE	(This position shall not be used)
FA92	CJK COMPATIBILITY IDEOGRAPH-FA92	FAEF	(This position shall not be used)
FA93	CJK COMPATIBILITY IDEOGRAPH-FA93	FAF0	(This position shall not be used)
FA94	CJK COMPATIBILITY IDEOGRAPH-FA94	FAF1	(This position shall not be used)
FA95	CJK COMPATIBILITY IDEOGRAPH-FA95	FAF2	(This position shall not be used)
FA96	CJK COMPATIBILITY IDEOGRAPH-FA96	FAF3	(This position shall not be used)
FA97	CJK COMPATIBILITY IDEOGRAPH-FA97	FAF4	(This position shall not be used)
FA98	CJK COMPATIBILITY IDEOGRAPH-FA98	FAF5	(This position shall not be used)
FA99	CJK COMPATIBILITY IDEOGRAPH-FA99	FAF6	(This position shall not be used)
FA9A	CJK COMPATIBILITY IDEOGRAPH-FA9A	FAF7	(This position shall not be used)
FA9B	CJK COMPATIBILITY IDEOGRAPH-FA9B	FAF8	(This position shall not be used)
FA9C	CJK COMPATIBILITY IDEOGRAPH-FA9C	FAF9	(This position shall not be used)
FA9D	CJK COMPATIBILITY IDEOGRAPH-FA9D	FAFA	(This position shall not be used)
FA9E	CJK COMPATIBILITY IDEOGRAPH-FA9E	FAFB	(This position shall not be used)
FA9F	CJK COMPATIBILITY IDEOGRAPH-FA9F	FAFC	(This position shall not be used)
FAA0	CJK COMPATIBILITY IDEOGRAPH-FAA0	FAFD	(This position shall not be used)
FAA1	CJK COMPATIBILITY IDEOGRAPH-FAA1	FAFE	(This position shall not be used)
FAA2	CJK COMPATIBILITY IDEOGRAPH-FAA2	FAFF	(This position shall not be used)
FAA3	CJK COMPATIBILITY IDEOGRAPH-FAA3		
FAA4	CJK COMPATIBILITY IDEOGRAPH-FAA4		
FAA5	CJK COMPATIBILITY IDEOGRAPH-FAA5		
FAA6	CJK COMPATIBILITY IDEOGRAPH-FAA6		
FAA7	CJK COMPATIBILITY IDEOGRAPH-FAA7		
FAA8	CJK COMPATIBILITY IDEOGRAPH-FAA8		
FAA9	CJK COMPATIBILITY IDEOGRAPH-FAA9		
FAAA	CJK COMPATIBILITY IDEOGRAPH-FAAA		
FAAB	CJK COMPATIBILITY IDEOGRAPH-FAAB		
FAAC	CJK COMPATIBILITY IDEOGRAPH-FAAC		
FAAD	CJK COMPATIBILITY IDEOGRAPH-FAAD		
FAAE	CJK COMPATIBILITY IDEOGRAPH-FAAE		
FAAF	CJK COMPATIBILITY IDEOGRAPH-FAAF		
FAB0	CJK COMPATIBILITY IDEOGRAPH-FAB0		
FAB1	CJK COMPATIBILITY IDEOGRAPH-FAB1		
FAB2	CJK COMPATIBILITY IDEOGRAPH-FAB2		
FAB3	CJK COMPATIBILITY IDEOGRAPH-FAB3		
FAB4	CJK COMPATIBILITY IDEOGRAPH-FAB4		
FAB5	CJK COMPATIBILITY IDEOGRAPH-FAB5		
FAB6	CJK COMPATIBILITY IDEOGRAPH-FAB6		
FAB7	CJK COMPATIBILITY IDEOGRAPH-FAB7		
FAB8	CJK COMPATIBILITY IDEOGRAPH-FAB8		
FAB9	CJK COMPATIBILITY IDEOGRAPH-FAB9		
FABA	CJK COMPATIBILITY IDEOGRAPH-FABA		
FABB	CJK COMPATIBILITY IDEOGRAPH-FABB		
FABC	CJK COMPATIBILITY IDEOGRAPH-FABC		

Group 00

Plane 00

Row FA

Table 156 - Row FD: Arabic Presentation Forms-A

	FD6	FD7	FD8	FD9	FDA	FDB	FDC	FDD	FDE	FD F
0	صَلَاة FD60	بَلَاة FD70	سَلَاة FD80		نَلَاة FDA0	يَلَاة FDB0	فَلَاة FDC0			صَلَاة FDF0
1	قَلَاة FD61	رَلَاة FD71	زَلَاة FD81		طَلَاة FDA1	ثَلَاة FDB1	دَلَاة FDC1			قَلَاة FDF1
2	هَلَاة FD62	وَلَاة FD72	زَلَاة FD82	نَلَاة FD92	يَلَاة FDA2	فَلَاة FDB2	فَلَاة FDC2			اللَّه FDF2
3	هَلَاة FD63	وَلَاة FD73	زَلَاة FD83	نَلَاة FD93	يَلَاة FDA3	فَلَاة FDB3	فَلَاة FDC3			اَكْبَر FDF3
4	مَلَاة FD64	بَلَاة FD74	نَلَاة FD84	هَلَاة FD94	وَلَاة FDA4	زَلَاة FDB4	دَلَاة FDC4			مُحَمَّد FDF4
5	سَلَاة FD65	جَلَاة FD75	سَلَاة FD85	بَلَاة FD95	يَلَاة FDA5	فَلَاة FDB5	فَلَاة FDC5			صَلَم FDF5
6	هَلَاة FD66	وَلَاة FD76	زَلَاة FD86	نَلَاة FD96	يَلَاة FDA6	فَلَاة FDB6	فَلَاة FDC6			رَسُول FDF6
7	سَلَاة FD67	بَلَاة FD77	نَلَاة FD87	هَلَاة FD97	وَلَاة FDA7	زَلَاة FDB7	دَلَاة FDC7			عَلِيه FDF7
8	بَلَاة FD68	وَلَاة FD78	نَلَاة FD88	هَلَاة FD98	وَلَاة FDA8	نَلَاة FDB8				وَسَلَم FDF8
9	يَلَاة FD69	هَلَاة FD79	نَلَاة FD89	وَلَاة FD99	يَلَاة FDA9	فَلَاة FDB9				صَلِي FDF9
A	رَلَاة FD6A	يَلَاة FD7A	بَلَاة FD8A	يَلَاة FD9A	وَلَاة FDAA	نَلَاة FDBA				صَلَّى اللّٰهُ عَلَيْهِ وَسَلَّمَ FDF A
B	بَلَاة FD6B	وَلَاة FD7B	يَلَاة FD8B	وَلَاة FD9B	يَلَاة FDA B	هَلَاة FDB B				جَلَّال FDF B
C	هَلَاة FD6C	سَلَاة FD7C	نَلَاة FD8C	تَلَاة FD9C	يَلَاة FDA C	نَلَاة FDB C				رِيَال FDF C
D	هَلَاة FD6D	بَلَاة FD7D	نَلَاة FD8D	تَلَاة FD9D	وَلَاة FDA D	نَلَاة FDB D				بِاللَّيْلِ وَالنَّجْمِ الْمُتَرَاوِعِ FDF D
E	وَلَاة FD6E	رَلَاة FD7E	نَلَاة FD8E	يَلَاة FD9E	يَلَاة FDA E	يَلَاة FDB E				
F	سَلَاة FD6F	هَلَاة FD7F	بَلَاة FD8F	يَلَاة FD9F	يَلَاة FDA F	يَلَاة FDB F				

G = 00
P = 00

Table 156 - Row FD: Arabic Presentation Forms-A

































HEX	NAME	HEX	NAME
FD60	ARABIC LIGATURE SEEN WITH MEEM WITH HAH INITIAL FORM	FDBD	ARABIC LIGATURE NOON WITH JEEM WITH HAH FINAL FORM
FD61	ARABIC LIGATURE SEEN WITH MEEM WITH JEEM INITIAL FORM	FDBE	ARABIC LIGATURE JEEM WITH HAH WITH YEH FINAL FORM
FD62	ARABIC LIGATURE SEEN WITH MEEM WITH MEEM FINAL FORM	FDBF	ARABIC LIGATURE HAH WITH JEEM WITH YEH FINAL FORM
FD63	ARABIC LIGATURE SEEN WITH MEEM WITH MEEM INITIAL FORM	FDC0	ARABIC LIGATURE MEEM WITH JEEM WITH YEH FINAL FORM
FD64	ARABIC LIGATURE SAD WITH HAH WITH HAH FINAL FORM	FDC1	ARABIC LIGATURE FEH WITH MEEM WITH YEH FINAL FORM
FD65	ARABIC LIGATURE SAD WITH HAH WITH HAH INITIAL FORM	FDC2	ARABIC LIGATURE BEH WITH HAH WITH YEH FINAL FORM
FD66	ARABIC LIGATURE SAD WITH MEEM WITH MEEM FINAL FORM	FDC3	ARABIC LIGATURE KAF WITH MEEM WITH MEEM INITIAL FORM
FD67	ARABIC LIGATURE SHEEN WITH HAH WITH MEEM FINAL FORM	FDC4	ARABIC LIGATURE AIN WITH JEEM WITH MEEM INITIAL FORM
FD68	ARABIC LIGATURE SHEEN WITH HAH WITH MEEM INITIAL FORM	FDC5	ARABIC LIGATURE SAD WITH MEEM WITH MEEM INITIAL FORM
FD69	ARABIC LIGATURE SHEEN WITH MEEM WITH YEH FINAL FORM	FDC6	ARABIC LIGATURE SEEN WITH KHAH WITH YEH FINAL FORM
FD6A	ARABIC LIGATURE SHEEN WITH MEEM WITH KHAH FINAL FORM	FDC7	ARABIC LIGATURE NOON WITH JEEM WITH YEH FINAL FORM
FD6B	ARABIC LIGATURE SHEEN WITH MEEM WITH KHAH INITIAL FORM	FDC8	(This position shall not be used)
FD6C	ARABIC LIGATURE SHEEN WITH MEEM WITH MEEM FINAL FORM	FDC9	(This position shall not be used)
FD6D	ARABIC LIGATURE SHEEN WITH MEEM WITH MEEM INITIAL FORM	FDCA	(This position shall not be used)
FD6E	ARABIC LIGATURE DAD WITH HAH WITH ALEF MAKSURA FINAL FORM	FDCB	(This position shall not be used)
FD6F	ARABIC LIGATURE DAD WITH KHAH WITH MEEM FINAL FORM	FDCD	(This position shall not be used)
FD70	ARABIC LIGATURE DAD WITH KHAH WITH MEEM INITIAL FORM	FDCD	(This position shall not be used)
FD71	ARABIC LIGATURE TAH WITH MEEM WITH HAH FINAL FORM	FDCD	(This position shall not be used)
FD72	ARABIC LIGATURE TAH WITH MEEM WITH HAH INITIAL FORM	FDCD	(This position shall not be used)
FD73	ARABIC LIGATURE TAH WITH MEEM WITH MEEM INITIAL FORM	FDCD	(This position shall not be used)
FD74	ARABIC LIGATURE TAH WITH MEEM WITH YEH FINAL FORM	FDD0	(This position is permanently reserved)
FD75	ARABIC LIGATURE AIN WITH JEEM WITH MEEM FINAL FORM	FDD1	(This position is permanently reserved)
FD76	ARABIC LIGATURE AIN WITH MEEM WITH MEEM FINAL FORM	FDD2	(This position is permanently reserved)
FD77	ARABIC LIGATURE AIN WITH MEEM WITH MEEM INITIAL FORM	FDD3	(This position is permanently reserved)
FD78	ARABIC LIGATURE AIN WITH MEEM WITH ALEF MAKSURA FINAL FORM	FDD4	(This position is permanently reserved)
FD79	ARABIC LIGATURE GHAIN WITH MEEM WITH MEEM FINAL FORM	FDD5	(This position is permanently reserved)
FD7A	ARABIC LIGATURE GHAIN WITH MEEM WITH YEH FINAL FORM	FDD6	(This position is permanently reserved)
FD7B	ARABIC LIGATURE GHAIN WITH MEEM WITH ALEF MAKSURA FINAL FORM	FDD7	(This position is permanently reserved)
FD7C	ARABIC LIGATURE FEH WITH KHAH WITH MEEM FINAL FORM	FDD8	(This position is permanently reserved)
FD7D	ARABIC LIGATURE FEH WITH KHAH WITH MEEM INITIAL FORM	FDD9	(This position is permanently reserved)
FD7E	ARABIC LIGATURE QAF WITH MEEM WITH HAH FINAL FORM	FDDA	(This position is permanently reserved)
FD7F	ARABIC LIGATURE QAF WITH MEEM WITH MEEM FINAL FORM	FDDB	(This position is permanently reserved)
FD80	ARABIC LIGATURE LAM WITH HAH WITH MEEM FINAL FORM	FDDC	(This position is permanently reserved)
FD81	ARABIC LIGATURE LAM WITH HAH WITH YEH FINAL FORM	FDDD	(This position is permanently reserved)
FD82	ARABIC LIGATURE LAM WITH HAH WITH ALEF MAKSURA FINAL FORM	FDDE	(This position is permanently reserved)
FD83	ARABIC LIGATURE LAM WITH JEEM WITH JEEM INITIAL FORM	FDDF	(This position is permanently reserved)
FD84	ARABIC LIGATURE LAM WITH JEEM WITH JEEM FINAL FORM	FDE0	(This position is permanently reserved)
FD85	ARABIC LIGATURE LAM WITH KHAH WITH MEEM FINAL FORM	FDE1	(This position is permanently reserved)
FD86	ARABIC LIGATURE LAM WITH KHAH WITH MEEM INITIAL FORM	FDE2	(This position is permanently reserved)
FD87	ARABIC LIGATURE LAM WITH MEEM WITH HAH FINAL FORM	FDE3	(This position is permanently reserved)
FD88	ARABIC LIGATURE LAM WITH MEEM WITH HAH INITIAL FORM	FDE4	(This position is permanently reserved)
FD89	ARABIC LIGATURE MEEM WITH HAH WITH JEEM INITIAL FORM	FDE5	(This position is permanently reserved)
FD8A	ARABIC LIGATURE MEEM WITH HAH WITH MEEM INITIAL FORM	FDE6	(This position is permanently reserved)
FD8B	ARABIC LIGATURE MEEM WITH HAH WITH YEH FINAL FORM	FDE7	(This position is permanently reserved)
FD8C	ARABIC LIGATURE MEEM WITH JEEM WITH HAH INITIAL FORM	FDE8	(This position is permanently reserved)
FD8D	ARABIC LIGATURE MEEM WITH JEEM WITH MEEM INITIAL FORM	FDE9	(This position is permanently reserved)
FD8E	ARABIC LIGATURE MEEM WITH KHAH WITH JEEM INITIAL FORM	FDEA	(This position is permanently reserved)
FD8F	ARABIC LIGATURE MEEM WITH KHAH WITH MEEM INITIAL FORM	FDEB	(This position is permanently reserved)
FD90	(This position shall not be used)	FDEC	(This position is permanently reserved)
FD91	(This position shall not be used)	FDED	(This position is permanently reserved)
FD92	ARABIC LIGATURE MEEM WITH JEEM WITH KHAH INITIAL FORM	FDEE	(This position is permanently reserved)
FD93	ARABIC LIGATURE HEH WITH MEEM WITH JEEM INITIAL FORM	FDEF	(This position is permanently reserved)
FD94	ARABIC LIGATURE HEH WITH MEEM WITH MEEM INITIAL FORM	FDF0	ARABIC LIGATURE SALLA USED AS KORANIC STOP SIGN ISOLATED FORM
FD95	ARABIC LIGATURE NOON WITH HAH WITH MEEM INITIAL FORM	FDF1	ARABIC LIGATURE QALA USED AS KORANIC STOP SIGN ISOLATED FORM
FD96	ARABIC LIGATURE NOON WITH HAH WITH ALEF MAKSURA FINAL FORM	FDF2	ARABIC LIGATURE ALLAH ISOLATED FORM
FD97	ARABIC LIGATURE NOON WITH JEEM WITH MEEM FINAL FORM	FDF3	ARABIC LIGATURE AKBAR ISOLATED FORM
FD98	ARABIC LIGATURE NOON WITH MEEM WITH MEEM INITIAL FORM	FDF4	ARABIC LIGATURE MOHAMMAD ISOLATED FORM
FD99	ARABIC LIGATURE NOON WITH JEEM WITH ALEF MAKSURA FINAL FORM	FDF5	ARABIC LIGATURE SALAM ISOLATED FORM
FD9A	ARABIC LIGATURE NOON WITH MEEM WITH YEH FINAL FORM	FDF6	ARABIC LIGATURE RASOUL ISOLATED FORM
FD9B	ARABIC LIGATURE NOON WITH MEEM WITH ALEF MAKSURA FINAL FORM	FDF7	ARABIC LIGATURE ALAYHE ISOLATED FORM
FD9C	ARABIC LIGATURE YEH WITH MEEM WITH MEEM FINAL FORM	FDF8	ARABIC LIGATURE WASALLAM ISOLATED FORM
FD9D	ARABIC LIGATURE YEH WITH MEEM WITH MEEM INITIAL FORM	FDF9	ARABIC LIGATURE SALLA ISOLATED FORM
FD9E	ARABIC LIGATURE BEH WITH KHAH WITH YEH FINAL FORM	FDDA	ARABIC LIGATURE SALLALLAHOU ALAYHE WASALLAM
FD9F	ARABIC LIGATURE TEH WITH JEEM WITH YEH FINAL FORM	FDFB	ARABIC LIGATURE JALLAJALALOUHOU
FDA0	ARABIC LIGATURE TEH WITH JEEM WITH ALEF MAKSURA FINAL FORM	FDFC	RIAL SIGN
FDA1	ARABIC LIGATURE TEH WITH KHAH WITH YEH FINAL FORM	FDDF	ARABIC LIGATURE BISMILLAH ARRABHMAN ARRABHIM
FDA2	ARABIC LIGATURE TEH WITH KHAH WITH ALEF MAKSURA FINAL FORM	FDFE	(This position shall not be used)
FDA3	ARABIC LIGATURE TEH WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDA4	ARABIC LIGATURE TEH WITH MEEM WITH ALEF MAKSURA FINAL FORM	FDFE	(This position shall not be used)
FDA5	ARABIC LIGATURE JEEM WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDA6	ARABIC LIGATURE JEEM WITH HAH WITH ALEF MAKSURA FINAL FORM	FDFE	(This position shall not be used)
FDA7	ARABIC LIGATURE JEEM WITH MEEM WITH ALEF MAKSURA FINAL FORM	FDFE	(This position shall not be used)
FDA8	ARABIC LIGATURE SEEN WITH KHAH WITH ALEF MAKSURA FINAL FORM	FDFE	(This position shall not be used)
FDA9	ARABIC LIGATURE SAD WITH HAH WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDAA	ARABIC LIGATURE SHEEN WITH HAH WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDAB	ARABIC LIGATURE DAD WITH HAH WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDAC	ARABIC LIGATURE LAM WITH JEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDAE	ARABIC LIGATURE LAM WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDAF	ARABIC LIGATURE YEH WITH HAH WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB0	ARABIC LIGATURE YEH WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB1	ARABIC LIGATURE MEEM WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB2	ARABIC LIGATURE QAF WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB3	ARABIC LIGATURE NOON WITH HAH WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB4	ARABIC LIGATURE QAF WITH MEEM WITH HAH INITIAL FORM	FDFE	(This position shall not be used)
FDB5	ARABIC LIGATURE LAM WITH HAH WITH MEEM INITIAL FORM	FDFE	(This position shall not be used)
FDB6	ARABIC LIGATURE AIN WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB7	ARABIC LIGATURE KAF WITH MEEM WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDB8	ARABIC LIGATURE NOON WITH JEEM WITH HAH INITIAL FORM	FDFE	(This position shall not be used)
FDB9	ARABIC LIGATURE MEEM WITH KHAH WITH YEH FINAL FORM	FDFE	(This position shall not be used)
FDBA	ARABIC LIGATURE LAM WITH JEEM WITH MEEM INITIAL FORM	FDFE	(This position shall not be used)
FDBB	ARABIC LIGATURE KAF WITH MEEM WITH MEEM FINAL FORM	FDFE	(This position shall not be used)
FDBC	ARABIC LIGATURE LAM WITH JEEM WITH MEEM FINAL FORM	FDFE	(This position shall not be used)

Group 00

Plane 00

Row FD

Table 159 - Row FE: CJK Compatibility Forms

	FE3	FE4
0	 FE30	 FE40
1	 FE31	 FE41
2	 FE32	 FE42
3	 FE33	 FE43
4	 FE34	 FE44
5	 FE35	 FE45
6	 FE36	 FE46
7	 FE37	 FE47
8	 FE38	 FE48
9	 FE39	 FE49
A	 FE3A	 FE4A
B	 FE3B	 FE4B
C	 FE3C	 FE4C
D	 FE3D	 FE4D
E	 FE3E	 FE4E
F	 FE3F	 FE4F

G = 00
P = 00

Table 159 - Row FE: CJK Compatibility Forms

HEX	NAME	HEX	NAME
FE30	PRESENTATION FORM FOR VERTICAL TWO DOT LEADER		
FE31	PRESENTATION FORM FOR VERTICAL EM DASH		
FE32	PRESENTATION FORM FOR VERTICAL EN DASH		
FE33	PRESENTATION FORM FOR VERTICAL LOW LINE		
FE34	PRESENTATION FORM FOR VERTICAL WAVY LOW LINE		
FE35	PRESENTATION FORM FOR VERTICAL LEFT PARENTHESIS		
FE36	PRESENTATION FORM FOR VERTICAL RIGHT PARENTHESIS		
FE37	PRESENTATION FORM FOR VERTICAL LEFT CURLY BRACKET		
FE38	PRESENTATION FORM FOR VERTICAL RIGHT CURLY BRACKET		
FE39	PRESENTATION FORM FOR VERTICAL LEFT TORTOISE SHELL BRACKET		
FE3A	PRESENTATION FORM FOR VERTICAL RIGHT TORTOISE SHELL BRACKET		
FE3B	PRESENTATION FORM FOR VERTICAL LEFT BLACK LENTICULAR BRACKET		
FE3C	PRESENTATION FORM FOR VERTICAL RIGHT BLACK LENTICULAR BRACKET		
FE3D	PRESENTATION FORM FOR VERTICAL LEFT DOUBLE ANGLE BRACKET		
FE3E	PRESENTATION FORM FOR VERTICAL RIGHT DOUBLE ANGLE BRACKET		
FE3F	PRESENTATION FORM FOR VERTICAL LEFT ANGLE BRACKET		
FE40	PRESENTATION FORM FOR VERTICAL RIGHT ANGLE BRACKET		
FE41	PRESENTATION FORM FOR VERTICAL LEFT CORNER BRACKET		
FE42	PRESENTATION FORM FOR VERTICAL RIGHT CORNER BRACKET		
FE43	PRESENTATION FORM FOR VERTICAL LEFT WHITE CORNER BRACKET		
FE44	PRESENTATION FORM FOR VERTICAL RIGHT WHITE CORNER BRACKET		
FE45	SESAME DOT		
FE46	WHITE SESAME DOT		
FE47	PRESENTATION FORM FOR VERTICAL LEFT SQUARE BRACKET		
FE48	PRESENTATION FORM FOR VERTICAL RIGHT SQUARE BRACKET		
FE49	DASHED OVERLINE		
FE4A	CENTRELINE OVERLINE		
FE4B	WAVY OVERLINE		
FE4C	DOUBLE WAVY OVERLINE		
FE4D	DASHED LOW LINE		
FE4E	CENTRELINE LOW LINE		
FE4F	WAVY LOW LINE		

Group 00

Plane 00

Row FE